

[Manuals.plus](#) /

› [Bestier](#) /

› Bestier D16" x H18" Chrome Crystal Raindrop Pendant Chandelier User Manual

Bestier 611885202627

Bestier D16" x H18" Chrome Crystal Raindrop Pendant Chandelier User Manual

Model: 611885202627

1. INTRODUCTION

Thank you for choosing the Bestier D16" x H18" Chrome Crystal Raindrop Pendant Chandelier. This manual provides essential information for the safe installation, operation, and maintenance of your new lighting fixture. Please read these instructions thoroughly before beginning installation and retain them for future reference.



Image 1.1: Bestier D16" x H18" Chrome Crystal Raindrop Pendant Chandelier.

2. SAFETY INFORMATION

- **WARNING:** To avoid electric shock, ensure power is turned off at the circuit breaker before installation.

- All electrical connections must be in accordance with local codes, ordinances, and the National Electric Code (NEC). Consult a qualified electrician if you are unfamiliar with proper electrical wiring.
- Wear gloves when handling the crystal components to prevent fingerprints and ensure a clean finish.
- Do not exceed the maximum wattage specified for the bulbs.
- Ensure the fixture is securely mounted to a structurally sound ceiling junction box capable of supporting the fixture's weight.

3. PACKAGE CONTENTS

Verify that all components are present and undamaged before beginning assembly.

- Mounting Bracket and Hardware
- Canopy and Chain
- Fixture Frame with Bulb Sockets (3 x E12)
- Crystal Raindrop Accents (various sizes)
- Small Metal Rings for Crystal Attachment
- Instruction Manual

4. SETUP AND INSTALLATION

Assembly of this chandelier requires careful attention to detail and can be time-consuming due to the numerous crystal components. It is highly recommended to assemble the main fixture frame and attach the crystal elements before hanging the entire unit from the ceiling.

4.1 Pre-Installation

1. Turn off power at the main circuit breaker.
2. Unpack all components and lay them out on a clean, soft surface to prevent scratches.
3. Identify all parts using the package contents list.

4.2 Assembling the Fixture Frame

The main fixture frame typically comes partially assembled. Attach any arms or decorative elements to the central body as per the included diagrams. Ensure all connections are secure.



Image 4.1: Assembly of the chandelier arms to the central body.

4.3 Attaching Crystal Elements

Each crystal raindrop accent is attached to the fixture frame using small metal rings. Carefully open each ring, hook it through the crystal, and then through the designated hole on the fixture frame. Close the ring securely. This process is repetitive and requires patience.



Image 4.2: Detail of crystal attachment points.

4.4 Mounting the Fixture

1. Attach the mounting bracket to the ceiling junction box using the provided screws.
2. Connect the electrical wires: black to black (live), white to white (neutral), and bare copper to bare copper (ground). Secure connections with wire nuts.
3. Thread the fixture's chain through the canopy. The chain length is adjustable; use pliers to remove links as needed to achieve the desired hanging height. The fixture can also be installed as a flush mount by removing the chain and directly attaching the canopy to the mounting bracket.
4. Secure the canopy to the mounting bracket.

4.5 Bulb Installation

This fixture requires 3 E12 base bulbs (not included). Ensure the bulbs are compatible with the fixture's voltage (110 Volts) and do not exceed the maximum wattage of 120 watts (40 watts per bulb).



Image 4.3: Example of an E12 Candelabra Base Bulb.

4.6 Installation Video Guide

For a visual guide on the unboxing and assembly process, please refer to the video below:

Your browser does not support the video tag.

Video 4.1: Unboxing and assembly review of the Bestier Chandelier.

5. OPERATING INSTRUCTIONS

Once installed and bulbs are in place, restore power at the circuit breaker. The chandelier can be operated via a standard wall switch. If connected to a compatible dimmer switch, the light output can be adjusted. The fixture features an 'Instant On' capability.

6. MAINTENANCE

6.1 Cleaning

- **Always turn off power before cleaning.**
- For the metal frame: Wipe with a soft, dry cloth. Do not use abrasive cleaners or polishes as they may damage the finish.
- For the crystal accents: Gently wipe with a soft, lint-free cloth dampened with water or a mild glass cleaner. Avoid spraying cleaner directly onto the crystals or electrical components.

6.2 Bulb Replacement

Ensure power is off before replacing bulbs. Allow bulbs to cool completely. Unscrew old bulbs and replace with new E12 base bulbs, ensuring they meet the specified voltage and wattage requirements.

7. TROUBLESHOOTING

- **Light does not turn on:**
 - Check if the power is on at the circuit breaker.
 - Ensure bulbs are securely screwed in and not burnt out.
 - Verify electrical connections are correct and secure.
- **Lights flicker:**

- Ensure bulbs are fully tightened.
- If using a dimmer, ensure it is compatible with the bulbs and fixture.
- Check for loose wiring connections.
- **Crystals appear dull:**
 - Clean crystals as per maintenance instructions.

8. SPECIFICATIONS



Image 8.1: Chandelier dimensions.

Feature	Detail
Brand	Bestier
Model Number	611885202627
Dimensions (Diameter x Height)	16 inches x 18 inches
Ceiling Plate Dimensions	Diameter 5 inches x Height 2 inches
Adjustable Hanging Chain	Max Length 40 inches
Color	Chrome
Material	Crystal
Bulb Base	E12
Number of Light Sources	3
Max Wattage	120 watts (40 watts per bulb)
Voltage	110 Volts
Installation Type	Hanging from the ceiling (can be flush-mounted)
Assembly Required	Yes
Indoor/Outdoor Usage	Indoor use only

9. WARRANTY AND SUPPORT

Warranty information for your Bestier Chandelier is typically provided with your purchase documentation. Please refer to these documents for details regarding coverage and terms. For product support, technical assistance, or to inquire about replacement parts, please contact Bestier customer service directly through their official website or the retailer where the product was purchased.

ASK A QUESTION ABOUT THIS MANUAL

Ask about setup, troubleshooting, compatibility, parts, safety, or missing instructions. Manuals+ will review the question and use this page’s manual context to help answer it.

Name

Anonymous

Email

you@example.com

After a successful submission, we securely hash the supplied account or form email before sending it to Microsoft Advertising for conversion attribution. [Privacy details](#).

Question

Example: How do I reset this device or fix this error?

Details

Model number, symptoms, what you tried, or the section of the manual you are using.

Submit question

Open the live page

<https://manuals.plus/asin/B07DDM9FYC>

More documents and user manuals: <https://manuals.plus/>