

Manuals+

[Q & A](#) | [Deep Search](#) | [Upload](#)

manuals.plus /

› [Monte Carlo](#) /

› [Monte Carlo Maverick II 3MAVR52RZW 52-inch Outdoor Ceiling Fan Instruction Manual](#)

Monte Carlo 3MAVR52RZW

Monte Carlo Maverick II 3MAVR52RZW 52-inch Outdoor Ceiling Fan Instruction Manual

Model: 3MAVR52RZW

INTRODUCTION

This manual provides detailed instructions for the safe installation, operation, and maintenance of your Monte Carlo Maverick II 3MAVR52RZW 52-inch Outdoor Ceiling Fan. Please read all instructions carefully before beginning installation and retain this manual for future reference. This fan is designed for outdoor, damp location use and features a 6-speed hand-held remote control.

SAFETY INFORMATION

WARNING: To reduce the risk of fire, electric shock, or personal injury, always follow these safety guidelines:

- Turn off power at the circuit breaker or fuse box before installation or servicing.
- All wiring must be in accordance with national and local electrical codes. Consult a qualified electrician if you are unsure about wiring procedures.
- The fan must be mounted to a structurally sound outlet box or support system capable of supporting a minimum of 35 lbs (15.9 kg).
- Ensure the mounting location allows for a minimum of 7 feet (2.1 meters) clearance from the floor to the blade trailing edge.
- Do not operate the fan with damaged blades or housing.
- Avoid placing objects in the path of the fan blades.
- This fan is suitable for damp locations. Do not expose to direct water spray.

PACKAGE CONTENTS

Verify that all components listed below are included in your package:

- Fan Motor Housing
- 3 Balsa Wood Blades
- Downrod (6-inch)

- Mounting Bracket
- Canopy
- Hand-Held Remote Control
- Receiver for Remote Control
- Hardware Pack (screws, washers, wire nuts, etc.)
- Instruction Manual



Image: Close-up of the fan's motor housing and blade attachment, showing the matte white finish and precision design.

SETUP AND INSTALLATION

Proper installation is critical for the safe and efficient operation of your ceiling fan. If you are not comfortable performing electrical work, consult a licensed electrician.

Pre-Installation Steps:

1. **Power Disconnection:** Ensure power is completely off at the main circuit breaker.
2. **Mounting Location:** Confirm the ceiling joist or support structure can hold the fan's weight and that there is adequate clearance for the blades.
3. **Unpacking:** Carefully remove all components from the packaging. Keep the packaging until installation is complete.

Mounting the Fan:

1. Attach the mounting bracket to the ceiling outlet box using the provided screws and washers. Ensure it is securely fastened.
2. Assemble the downrod to the fan motor housing, feeding the electrical wires through the downrod.

3. Carefully lift the fan assembly and hang it from the mounting bracket.

Wiring:

1. Connect the fan's electrical wires to the household wiring according to the wiring diagram provided in the separate wiring guide (if applicable) and local electrical codes. Typically, this involves connecting live, neutral, and ground wires.
2. Install the remote control receiver into the canopy, ensuring all connections are secure.

Blade Attachment:

1. Attach each of the three balsa wood blades to the fan motor housing using the screws provided. Ensure all screws are tightened evenly to prevent wobbling.



Image: Dimensional diagram of the fan, indicating a 52-inch diameter, 11.5-inch overall height, and a 6-inch downrod.

OPERATING INSTRUCTIONS

Your Monte Carlo Maverick II fan is operated by a hand-held remote control.

Remote Control Setup:

1. Install two AAA batteries (not included) into the remote control. Ensure correct polarity.
2. The remote control is pre-paired with the fan's receiver. If pairing is lost, refer to the troubleshooting section or the

separate remote control manual for re-pairing instructions.

Remote Control Functions:

- **Power Button:** Turns the fan ON or OFF.
- **Fan Speed Buttons (1-6):** Adjusts the fan speed from 1 (lowest) to 6 (highest).
- **Reverse Function Button:** Changes the direction of blade rotation. This function is typically used to create a downdraft (cooling effect) in warmer weather and an updraft (to circulate warm air) in cooler weather. Ensure the fan is off or at a low speed before changing direction.

MAINTENANCE

Regular maintenance ensures the longevity and optimal performance of your ceiling fan.

- **Cleaning:** Periodically wipe the fan blades and motor housing with a soft, damp cloth. Do not use abrasive cleaners or solvents, as these can damage the finish.
- **Blade Care:** Inspect blades for any signs of damage or warping. Replace damaged blades immediately.
- **Tightness Check:** Annually check all screws on the motor housing, downrod, and mounting bracket to ensure they are securely tightened. Loose connections can cause wobbling or noise.
- **Motor Lubrication:** The DC motor is permanently lubricated and does not require additional oiling.

TROUBLESHOOTING

If you experience issues with your fan, consult the following common problems and solutions:

Problem	Possible Cause	Solution
Fan does not start	No power to the fan; Remote control batteries are dead; Incorrect wiring; Remote not paired.	Check circuit breaker; Replace remote batteries; Verify wiring connections; Re-pair remote control.
Fan wobbles excessively	Loose blade screws; Unbalanced blades; Loose mounting bracket.	Tighten all blade screws; Check for bent blades; Ensure mounting bracket is secure; Use a blade balancing kit if necessary.
Remote control not working	Dead batteries; Remote not paired; Obstruction between remote and receiver.	Replace batteries; Re-pair remote; Ensure clear line of sight to fan receiver.
Noisy operation	Loose screws; Motor issues; Blades hitting an obstruction.	Check and tighten all screws; Ensure no obstructions are near blades; If motor noise persists, contact customer support.

SPECIFICATIONS

Detailed technical specifications for the Monte Carlo Maverick II 3MAVR52RZW ceiling fan:

Brand: Monte Carlo

Model Name: Maverick II

Part Number: 3MAVR52RZW

Color: Matte White-white Blades

Electric Fan Design: Ceiling Fan

Power Source: AC/DC

Style: Farmhouse

Product Dimensions: 52"D x 52"W x 11.5"H

Room Type: Living Room (suitable for outdoor/damp locations)

Special Feature: Remote Control

Recommended Uses: Ventilating

Finish Type: Matte

Number of Blades: 3

Air Flow Capacity: 3807 Cubic Feet Per Minute (CFM)

Blade Length: 52 Inches

Speed: 6 RPM (6-speed control)

Voltage: 120 Volts

Item Weight: 10.4 Pounds

Included Components: Remote

Indoor/Outdoor Usage: Outdoor

Specification Met: CUL Approved, Energy Star

Control Method: Remote

Efficiency: ENERGY STAR qualified

Number of Power Levels: 6

Motor Type: DC (85 x 38 mm)

Installation Type: Flat Ceiling Mount (Downrod Mount)

UPC: 014817586336

Batteries Required for Remote: 2 AAA batteries



MAVERICK 52" OUTDOOR CEILING FAN



MOUNTING TYPE	Downrod Mount
REMOTE	Hand Held Remote
LIGHT KIT	N/A
BULBS	N/A
DIMMABLE	N/A
AIRFLOW	3807 CFM-Average, 5889 CFM-High
MOTOR SIZE	85 x 28 mm DC Motor

Image: Key specifications table, including mounting type (Downrod Mount), remote type (Hand Held Remote), airflow (3807 CFM Average), and motor size (85 x 28 mm DC Motor).

WARRANTY INFORMATION

The Monte Carlo Maverick II 3MAVR52RZW ceiling fan comes with a limited lifetime warranty. This warranty covers defects in materials and workmanship under normal use and service. For specific terms, conditions, and claim procedures, please refer to the warranty card included with your product or contact Monte Carlo customer support.

CUSTOMER SUPPORT

If you have any questions, require assistance with installation, or need to report a problem not covered in this manual, please contact Monte Carlo customer support. Have your model number (3MAVR52RZW) and purchase date ready when contacting support.

For further assistance, please visit the official Monte Carlo website or refer to the contact information provided in your product packaging.

