

## Manuals+

[Q & A](#) | [Deep Search](#) | [Upload](#)

manuals.plus /

› [Rii](#) /

› [Rii BT11 Ultra-Thin Bluetooth Wireless Keyboard with Multi-Function Touchpad User Manual](#)

### Rii BT11

# Rii BT11 Ultra-Thin Bluetooth Wireless Keyboard User Manual

Model: BT11

## 1. INTRODUCTION

---

This manual provides detailed instructions for the Rii BT11 Ultra-Thin Bluetooth Wireless Keyboard. Please read this manual thoroughly before using the product to ensure proper operation and to maximize its lifespan. This keyboard is designed for use with various devices including Windows, Linux, macOS, iOS (touchpad function not supported), Android, tablets, and smartphones.



Image 1.1: Front view of the Rii BT11 Ultra-Thin Bluetooth Wireless Keyboard, showcasing its compact design and full AZERTY layout with integrated touchpad.

## 2. PACKAGE CONTENTS

Verify that all items are present in the package:

- Rii BT11 Bluetooth Wireless Keyboard
- USB Charging Cable
- User Manual (this document)

## 3. PRODUCT OVERVIEW

Familiarize yourself with the keyboard's components and controls.

## Touche de Commutateur pour Pavé tactile



Bouton Gauche de la Souris

Bouton Droit de la Souris

- |                               |                                 |
|-------------------------------|---------------------------------|
| <b>1</b> Commutateur          | <b>2</b> Voyant de Connection   |
| <b>3</b> Voyant de Pouissance | <b>4</b> Touches pour connecter |

Image 3.1: Diagram of the Rii BT11 keyboard highlighting key features. (1) Switch, (2) Connection Indicator, (3) Power Indicator, (4) Connection Keys (Fn+Q/W/E for different OS), Left Mouse Button (under touchpad), Right Mouse Button (under touchpad), Touchpad Switch Key (Fn+Space).

- 1. Switch:** Power ON/OFF switch for the keyboard.
- 2. Connection Indicator:** LED light indicating Bluetooth connection status.
- 3. Power Indicator:** LED light indicating power status and charging.
- 4. Connection Keys:** Use with the Function (Fn) key to switch between operating systems (Fn+Q for iOS, Fn+W for Android, Fn+E for Windows).
- 5. Left Mouse Button:** Integrated into the touchpad area.
- 6. Right Mouse Button:** Integrated into the touchpad area.
- 7. Touchpad Switch Key:** Fn + Spacebar to enable/disable the touchpad.

## 4. SETUP

### 4.1 Charging the Keyboard

Before initial use, fully charge the keyboard. Connect the supplied USB charging cable to the keyboard's charging port and the other end to a USB power source (e.g., computer USB port, USB wall adapter). The Power Indicator LED will

illuminate during charging and turn off when fully charged.

## COMPACT ET ULTRA-MINCE



Taille: 25.7cm\*17.2cm\*0.7cm.

Image 4.1: Information on the Rii BT11's battery specifications: 280mAh Lithium battery, less than 4 hours charging time, 40 hours uninterrupted working time, and 90 days standby time.

### 4.2 Bluetooth Pairing

Follow these steps to pair your Rii BT11 keyboard with your device:

1. Ensure the keyboard is fully charged.
2. Turn on the keyboard using the **Switch** (1) located on the side. The Power Indicator LED will light up briefly.
3. Press the **Fn** key and one of the **Connection Keys** (Q, W, or E) simultaneously to select the appropriate operating system mode for your device:
  - **Fn + Q:** For iOS devices (iPad, iPhone). Note: Touchpad function is not supported on iOS.
  - **Fn + W:** For Android devices.
  - **Fn + E:** For Windows devices.

After selecting the mode, the Connection Indicator LED (2) will start blinking, indicating the keyboard is in pairing

mode.

4. On your device (tablet, smartphone, computer), go to the Bluetooth settings.
5. Enable Bluetooth and search for available devices.
6. Select "Rii BT11" from the list of found devices.
7. If prompted, enter the pairing code displayed on your device using the Rii BT11 keyboard and press **Enter**.
8. Once successfully paired, the Connection Indicator LED will stop blinking and remain solid for a few seconds, then turn off to save power. The keyboard is now ready for use.

*Note: The keyboard will automatically attempt to reconnect to the last paired device when powered on. If it fails to connect, repeat the pairing process.*

## 5. OPERATING INSTRUCTIONS

---

### 5.1 Basic Keyboard Functions

The Rii BT11 features a standard AZERTY keyboard layout. All standard typing functions operate as expected.

### 5.2 Touchpad Operation

The integrated multi-touch touchpad allows for precise cursor control and gesture support on compatible operating systems (Windows, Android, Linux). The touchpad is not supported on iOS devices.

- **Single Finger Tap:** Left-click.
- **Two Finger Tap:** Right-click.
- **Two Finger Scroll:** Scroll up/down or left/right.
- **Pinch to Zoom:** Zoom in/out (supported on some applications/OS).

To enable or disable the touchpad, press **Fn + Spacebar**.



# TOUCHEPAD ET RACCOURCIS PRATIQUES

Image 5.1: A hand demonstrating the use of the multi-function touchpad on the Rii BT11 keyboard, highlighting its utility for navigation.

## 5.3 Function Keys (Fn Combinations)

The keyboard includes dedicated function keys (F1-F12) and multimedia keys accessible via the **Fn** key. Refer to the key labels for specific functions.

**Table 5.1: Common Fn Key Combinations**

Combination	Function
Fn + Q	Switch to iOS mode
Fn + W	Switch to Android mode
Fn + E	Switch to Windows mode
Fn + Spacebar	Enable/Disable Touchpad

Combination	Function
Fn + F1-F12	Multimedia and system control functions (e.g., volume, playback, brightness)

## 5.4 Power Saving Mode

To conserve battery life, the keyboard will enter sleep mode after 10 minutes of inactivity. To wake it up, press any key and wait approximately 3 seconds for it to reconnect.

## 6. MAINTENANCE

Proper maintenance ensures the longevity of your Rii BT11 keyboard.

- **Cleaning:** Use a soft, dry cloth to wipe the keyboard surface. For stubborn dirt, slightly dampen the cloth with water or a mild, non-abrasive cleaner. Do not use harsh chemicals or immerse the keyboard in liquid.
- **Storage:** Store the keyboard in a cool, dry place away from direct sunlight and extreme temperatures.
- **Battery Care:** Avoid fully discharging the battery frequently. Charge the keyboard regularly, especially if it will not be used for an extended period.
- **Handling:** Avoid dropping the keyboard or subjecting it to strong impacts. Do not attempt to disassemble the keyboard.

## 7. TROUBLESHOOTING

If you encounter issues with your Rii BT11 keyboard, refer to the following common problems and solutions:

**Table 7.1: Troubleshooting Guide**

Problem	Possible Cause	Solution
Keyboard does not turn on.	Low battery or power switch is off.	Charge the keyboard. Ensure the power switch is in the "ON" position.
Keyboard does not connect via Bluetooth.	Not in pairing mode, incorrect OS mode, device Bluetooth off, or already paired with another device.	<ul style="list-style-type: none"> <li>◦ Ensure the keyboard is in pairing mode (blinking Connection Indicator).</li> <li>◦ Verify the correct OS mode is selected (Fn+Q/W/E).</li> <li>◦ Ensure Bluetooth is enabled on your device.</li> <li>◦ Forget "Rii BT11" from your device's Bluetooth list and re-pair.</li> <li>◦ Move the keyboard closer to the device.</li> </ul>
Keys are not responding.	Keyboard is in sleep mode, low battery, or connection issue.	<ul style="list-style-type: none"> <li>◦ Press any key to wake the keyboard.</li> <li>◦ Charge the keyboard.</li> <li>◦ Reconnect the Bluetooth connection.</li> </ul>

Problem	Possible Cause	Solution
Touchpad is not working.	Touchpad disabled, or device is iOS.	<ul style="list-style-type: none"> <li>◦ Press Fn + Spacebar to enable the touchpad.</li> <li>◦ Note that the touchpad function is not supported on iOS devices.</li> </ul>
Keyboard frequently disconnects.	Low battery, interference, or device too far.	<ul style="list-style-type: none"> <li>◦ Charge the keyboard.</li> <li>◦ Ensure no strong electromagnetic interference sources are nearby.</li> <li>◦ Keep the keyboard within the effective Bluetooth range (typically 10 meters).</li> </ul>

## 8. SPECIFICATIONS

Key technical specifications for the Rii BT11 keyboard:

- **Model:** BT11
- **Brand:** Rii
- **Connectivity:** Bluetooth
- **Layout:** AZERTY
- **Compatible Operating Systems:** Windows, Android, Linux/Ubuntu, iOS (keyboard only, touchpad not supported)
- **Compatible Devices:** Laptop, Smartphone, Tablet, Smart TV
- **Battery Type:** Lithium-ion (Lithium-polymer)
- **Battery Capacity:** 280mAh
- **Charging Time:** < 4 hours
- **Working Time:** 40 hours (uninterrupted)
- **Standby Time:** 90 days
- **Material:** Plastic
- **Dimensions:** Approximately 25.7cm x 17.2cm x 0.7cm (Ultra-thin design)
- **Special Features:** Ultra-thin, Multi-touch Touchpad, Power Saving Mode, Wide Compatibility

# LARGE COMPATIBILITÉ

Fonctionne avec les tablettes, les smartphones, les téléviseurs intelligents et les ordinateurs



Image 8.1: The Rii BT11 keyboard showcasing its compact and ultra-thin profile, with dimensions of 25.7cm x 17.2cm x 0.7cm.



Image 8.2: Features of the Rii BT11 keyboard, including scissor keys for comfortable typing, durable ABS material construction, and design for quiet and comfortable typing.

## 9. WARRANTY AND SUPPORT

For warranty information and technical support, please refer to the product packaging or contact Rii customer service directly. Information regarding spare parts availability and software updates is not provided in the product specifications. For further assistance, please visit the official Rii website or contact their customer support channels.