

Ariete 2761

Ariete 2761 Handy Force 2-in-1 Corded Electric Broom and Handheld Vacuum Cleaner User Manual

1. INTRODUCTION

Thank you for choosing the Ariete 2761 Handy Force 2-in-1 Electric Broom and Handheld Vacuum Cleaner. This versatile appliance is designed for efficient and convenient cleaning of various surfaces in your home. Featuring cyclonic technology and a HEPA filter, it ensures thorough dust removal and improved air quality. Please read this manual carefully before use to ensure safe and optimal operation.

2. SAFETY INSTRUCTIONS

- Always ensure the power supply voltage matches the rating on the appliance.
- Do not use the appliance with a damaged cord or plug. Contact authorized service personnel for repairs.
- Do not immerse the appliance, cord, or plug in water or other liquids.
- Unplug the appliance from the power outlet when not in use, before cleaning, or before changing accessories.
- Keep hair, loose clothing, fingers, and all parts of the body away from openings and moving parts.
- Do not vacuum flammable or combustible materials, hot ashes, or sharp objects.
- Use only as described in this manual. Use only manufacturer's recommended attachments.
- This appliance is for household use only.

3. PRODUCT OVERVIEW

The Ariete 2761 Handy Force is a powerful and lightweight 2-in-1 cleaning solution. It combines the functionality of a corded electric broom for floors and a portable handheld vacuum for smaller tasks and hard-to-reach areas.

Key Features:

- **2-in-1 Design:** Easily converts from a vertical stick vacuum to a handheld unit.
- **Cyclonic Technology:** Provides strong, consistent suction for effective dust, mite, and bacteria removal without a bag.

- **HEPA Filter:** Captures fine dust particles and allergens, ideal for allergy sufferers and pet owners.
- **Telescopic Tube:** Adjustable length for comfortable use and reaching high areas.
- **Universal Brush:** Suitable for deep cleaning various floor types including terracotta, marble, porcelain stoneware, ceramic, and carpets.
- **Lightweight and Ergonomic:** Designed for easy maneuverability and comfortable handling.
- **Wall Mounting Support:** For convenient storage.

Components Included:

- Electric Broom Unit
- Crevice Nozzle
- Fabric Brush
- Multi-language Instruction Booklet



Image: The Ariete 2761 Handy Force electric broom in its full upright configuration, cleaning a white rug on a tiled floor. The red telescopic tube and black floor brush are visible.

4. SETUP

Assembly:

1. **Attach the Telescopic Tube:** Insert the telescopic tube into the main motor unit until it clicks securely into place.
2. **Attach the Floor Brush:** Connect the universal floor brush to the bottom end of the telescopic tube, ensuring it is firmly attached.
3. **For Handheld Use:** To use as a handheld vacuum, detach the telescopic tube and floor brush from the main motor unit. Attach the desired accessory (crevice nozzle or fabric brush) directly to the motor unit's suction opening.

Wall Mounting (Optional):

The appliance includes a wall mounting support for convenient storage. Choose a suitable location, ensuring it is near a power outlet and away from heat sources or moisture. Secure the support to the wall using appropriate screws and anchors (not included).

5. OPERATING INSTRUCTIONS

Using as an Electric Broom:

1. Ensure the telescopic tube and floor brush are securely assembled.
2. Plug the power cord into a suitable electrical outlet (220V). The cord length is 5 meters.
3. Press the ON/OFF button (Push Button control type) located on the main unit to start the vacuum cleaner.
4. Guide the floor brush over the surfaces to be cleaned. The universal brush is effective on various floor types and carpets.
5. To adjust the length of the telescopic tube, press the release button and extend or retract the tube to your desired height.
6. When finished, press the ON/OFF button again to turn off the appliance and unplug it from the outlet.

Using as a Handheld Vacuum:

1. Detach the telescopic tube and floor brush from the main motor unit.
2. Attach the crevice nozzle for narrow spaces or the fabric brush for upholstery and textiles.
3. Plug the power cord into an electrical outlet.
4. Press the ON/OFF button to activate the handheld vacuum.
5. Use the handheld unit to clean furniture, car interiors, shelves, or other areas requiring precise cleaning.
6. When finished, press the ON/OFF button to turn off the appliance and unplug it.



Image: A person using the Ariete 2761 Handy Force in handheld mode to clean dust from a bookshelf. The compact motor unit with the dustbin and a nozzle attachment is visible.



Image: The Ariete 2761 Handy Force in handheld mode, being used to vacuum the interior of a car, specifically the dashboard area. A brush attachment is connected to the unit.

6. MAINTENANCE

Regular maintenance ensures optimal performance and extends the life of your Ariete 2761 Handy Force.

Emptying the Dustbin:

1. Ensure the appliance is unplugged from the power outlet.
2. Locate the dustbin release button or latch on the main motor unit.
3. Carefully remove the dustbin.
4. Empty the collected dust and debris into a waste bin.
5. Reattach the dustbin to the motor unit, ensuring it clicks securely into place.

Cleaning the HEPA Filter:

The HEPA filter should be cleaned regularly to maintain suction power and filtration efficiency.

1. With the dustbin removed, locate and carefully extract the HEPA filter.
2. Tap the filter gently over a waste bin to dislodge accumulated dust.

- If necessary, rinse the filter under cold running water. Ensure it is completely dry before reinserting it into the vacuum cleaner. **Do not use detergents or hot water.**
- Once dry, place the HEPA filter back into its compartment and reattach the dustbin.



Image: Close-up of the Ariete 2761 Handy Force's HEPA filter, highlighting its role in trapping dust, mites, and allergens.

7. TROUBLESHOOTING

If you encounter issues with your Ariete 2761 Handy Force, refer to the following common problems and solutions:

Problem	Possible Cause	Solution
Appliance does not turn on	Not plugged in; power outlet fault; damaged cord/plug	Check power connection; test outlet with another device; contact service if cord/plug damaged.
Loss of suction power	Full dustbin; clogged filter; blockage in nozzle/tube	Empty dustbin; clean HEPA filter; check and clear any blockages.
Unusual noise during operation	Blockage; foreign object in brush/tube	Turn off and unplug; inspect for and remove any foreign objects or blockages.
Dust escaping from appliance	Dustbin not properly closed; filter not correctly installed or damaged	Ensure dustbin is securely closed; check filter installation; replace filter if damaged.

8. SPECIFICATIONS

Specification	Detail
Brand	Ariete
Model Name / Number	2761
Power Source	Corded Electric
Power (Electrical)	600 Watts
Voltage	220 Volts

Specification	Detail
Amperage	3 Amperes
Filter Type	HEPA Filter
Special Features	HEPA, Lightweight, Portable, Bagless, Cyclonic Technology
Recommended Surfaces	All types of floors, carpets, and rugs
Noise Level	80 Decibels
Item Weight	2.78 Kilograms
Item Dimensions (LxWxH)	27L x 23W x 122H cm
Cord Length	5 meters
Control Type	Push Button
Color	Red/Black
Country of Origin	China

9. WARRANTY AND SUPPORT

The Ariete 2761 Handy Force comes with a manufacturer's warranty of **2 years**. This warranty covers defects in materials and workmanship under normal use.

For warranty claims, technical support, or spare parts, please contact Ariete customer service or the retailer from whom you purchased the product. Keep your proof of purchase for warranty validation.

Availability of spare parts in the EU is guaranteed for 2 years.