

Feiss EC1009BBS

Feiss Generation Lighting Brianna 9-Light Medium Chandelier Instruction Manual

Model: EC1009BBS | Finish: Burnished Brass

1. IMPORTANT SAFETY INFORMATION

Please read and understand all instructions before beginning installation. Failure to do so may result in electric shock, fire, or other injuries that could be fatal or cause property damage. All electrical connections must be in accordance with local codes, ordinances, or the National Electric Code (NEC).

- **WARNING:** To avoid electric shock, disconnect power at the circuit breaker or fuse box before installation.
- **CAUTION:** All wiring connections must be made by a qualified electrician.
- This fixture is designed for indoor use only and is Damp Rated.
- Do not exceed the maximum wattage specified for each bulb.

2. PACKAGE CONTENTS

Verify that all parts listed below are included in your package. If any parts are missing or damaged, contact your retailer for assistance.

- Chandelier Fixture (A)
- Mounting Hardware Kit (B) - Includes mounting strap, outlet box screws, wire nuts, ground screw.
- Canopy (C)
- Chain/Stem (D) - Length may vary.
- Bulbs (Not included, purchase separately)



Image 1: Full view of the Feiss Brianna 9-Light Medium Chandelier in Burnished Brass. This image displays the complete fixture, including the central stem, nine curved arms, and bulb sockets, ready for ceiling installation.

3. SETUP AND INSTALLATION

This fixture is designed for ceiling installation. Assembly is not required for the main fixture body, simplifying the installation process.

1. **Turn Off Power:** Before starting, ensure the power to the junction box is turned off at the circuit breaker or fuse box.
2. **Prepare Mounting:** Attach the mounting strap (part of B) to the outlet box using the provided outlet box screws. Ensure the strap is securely fastened.
3. **Adjust Hanging Height (if applicable):** If your chandelier uses a chain or adjustable stem (D), determine the desired hanging height and adjust the chain/stem length accordingly.
4. **Wiring:**

- Connect the bare copper or green ground wire from the fixture to the ground wire from the outlet box using a wire nut. Secure the ground wire to the mounting strap with the ground screw.
 - Connect the white wire from the fixture to the white (neutral) wire from the outlet box using a wire nut.
 - Connect the black wire from the fixture to the black (hot) wire from the outlet box using a wire nut.
 - Ensure all wire connections are secure and tucked neatly into the outlet box.
5. **Mount Fixture:** Carefully lift the chandelier and attach the canopy (C) to the mounting strap, securing it with the provided screws or decorative nuts. Ensure the fixture is firmly attached to the ceiling.
 6. **Install Bulbs:** Insert nine (9) incandescent bulbs (max 60 Watts each) into the fixture's sockets. Refer to the fixture's socket for the exact base type (e.g., E12 Candelabra). Do not overtighten.
 7. **Restore Power:** Once installation is complete, restore power at the circuit breaker or fuse box.



Image 2: A detailed close-up of the chandelier's bulb sockets and arms. This view highlights the Burnished Brass finish and the design of the individual light points where bulbs are installed.

4. OPERATING INSTRUCTIONS

The Feiss Brianna Chandelier operates via a standard wall switch connected to the fixture's electrical circuit.

- **Turning On/Off:** Flip the wall switch to the 'ON' position to illuminate the chandelier. Flip it to the 'OFF' position to turn off the lights.
- **Bulb Replacement:** Ensure power is off at the circuit breaker before replacing any bulbs. Allow bulbs

to cool completely before touching. Unscrew old bulbs and screw in new ones of the correct type and wattage.

5. MAINTENANCE

Regular maintenance will help preserve the appearance and functionality of your chandelier.

- **Cleaning:** Dust the fixture regularly with a soft, dry cloth. For more thorough cleaning, wipe with a damp cloth using only mild soap and water. Avoid abrasive cleaners, solvents, or polishes as they may damage the finish.
- **Bulb Check:** Periodically check that all bulbs are securely seated in their sockets.
- **Electrical Connections:** If you notice any flickering or intermittent operation, ensure all electrical connections are secure. If issues persist, consult a qualified electrician.

6. TROUBLESHOOTING

If you encounter issues with your chandelier, refer to the following common problems and solutions:

- **Light does not turn on:**
 - Check if the wall switch is in the 'ON' position.
 - Verify that the circuit breaker is not tripped.
 - Ensure bulbs are correctly installed and not burnt out. Replace if necessary.
 - Check wiring connections at the junction box and fixture. Ensure they are secure.
- **Lights flicker:**
 - Ensure bulbs are fully screwed into their sockets.
 - Check for loose wiring connections.
 - If using a dimmer switch, ensure it is compatible with incandescent bulbs and rated for the total wattage of the fixture.
- **Fixture hums:**
 - Some dimmers can cause humming. Ensure dimmer compatibility.
 - Loose wiring can also cause humming. Check connections.

If problems persist after attempting these solutions, contact a qualified electrician or customer support.

7. SPECIFICATIONS

Brand	Feiss
Model Number	EC1009BBS
Collection	Brianna
Finish Color	Burnished Brass
Material	Steel, Brass, Nickel
Dimensions (W x L x H)	30 x 30 x 25.75 inches

Item Weight	13 pounds
Number of Lights	9
Lamping Type	Incandescent
Max Wattage per Bulb	60 Watts
Voltage	120 Volts
Moisture Rating	Damp Rated
Installation Type	Ceiling Mount (Chandelier)
Assembly Required	No (for main fixture body)

8. WARRANTY INFORMATION

Feiss products are manufactured to high standards and are backed by a manufacturer's warranty. Specific warranty details, including coverage duration and terms, are typically provided with the product packaging or can be obtained directly from the manufacturer's website. Please retain your proof of purchase for warranty claims.

9. CUSTOMER SUPPORT

For further assistance, technical support, or to inquire about replacement parts, please contact Feiss customer service. You can often find contact information on the manufacturer's website or through your original retailer.

You may also visit the official Feiss store for more product information and support resources:

[Feiss Official Store on Amazon](#)