



[Manuals.plus](#) /

› [Golden Lighting](#) /

› Golden Lighting Mirabella 6 Light Chandelier (Model 7644-6 PW) Instruction Manual

## Golden Lighting 7644-6 PW

# Golden Lighting Mirabella 6 Light Chandelier (Model 7644-6 PW) Instruction Manual

## INTRODUCTION

---

This manual provides detailed instructions for the safe installation, operation, and maintenance of your Golden Lighting Mirabella 6 Light Chandelier. Please read all instructions carefully before beginning installation and retain this manual for future reference. This chandelier, Model 7644-6 PW, features a pewter finish, graceful sweeping arms, and crystal-clear glass beads, designed to create a stylish focal point in your living or dining area.



Figure 1: Full view of the Golden Lighting Mirabella 6 Light Chandelier, showcasing its pewter finish and crystal bead drapes.

## SAFETY INFORMATION

---

- **WARNING:** To avoid electric shock, ensure power is turned off at the circuit breaker or fuse box before installation, servicing, or changing bulbs.
- All wiring must be in accordance with national and local electrical codes. If you are unsure about wiring, consult a qualified electrician.
- Do not exceed the maximum wattage specified for the bulbs.
- Handle glass components with care to prevent breakage and injury.
- Ensure the mounting surface can support the weight of the fixture.
- This fixture is designed for indoor use only.

## PACKAGE CONTENTS

---

Carefully unpack your chandelier and identify all parts. Keep all packaging materials until you are certain all parts are present and in good condition. If any parts are missing or damaged, do not attempt to assemble or install the fixture.

- Chandelier Fixture Body (with arms and wiring)
- Mounting Canopy
- Mounting Strap/Bracket
- Chain and Quick Links
- Crystal-Clear Glass Bead Strands and Pendants
- Mounting Hardware (screws, wire nuts, ground screw)
- Instruction Manual

*Note: Light bulbs are typically not included and must be purchased separately. Refer to the Specifications section for recommended bulb type and wattage.*

## SETUP AND INSTALLATION

---

Professional installation by a qualified electrician is recommended.

1. **Turn Off Power:** Locate the circuit breaker or fuse box for the room where you are installing the chandelier and turn off the power. Verify the power is off using a voltage tester.
2. **Prepare Mounting Location:** Ensure the existing electrical junction box is securely mounted to the building structure and can support the weight of the chandelier.
3. **Install Mounting Strap:** Attach the mounting strap/bracket to the junction box using the screws provided.
4. **Adjust Chain Length:** Determine the desired hanging height for your chandelier. Open a chain link using pliers and remove excess chain. Attach one end of the chain to the top loop of the chandelier fixture and the other end to the mounting canopy loop using the quick links.
5. **Wire the Fixture:** Carefully lift the chandelier and support its weight. Connect the fixture's wires to the house wires using wire nuts:
  - Connect the bare copper (ground) wire from the fixture to the bare copper (ground) wire from the junction box. Secure with a ground screw to the mounting strap.
  - Connect the ribbed or marked (neutral) wire from the fixture to the white (neutral) wire from the junction box.
  - Connect the smooth or unmarked (hot) wire from the fixture to the black (hot) wire from the junction box.Ensure all connections are secure and tuck wires neatly into the junction box.
6. **Secure Canopy:** Slide the canopy up the chain and secure it flush against the ceiling, covering the junction box. Use the provided collar ring or screws to fasten the canopy in place.
7. **Install Light Bulbs:** Screw in the recommended incandescent bulbs (or equivalent LED bulbs) into each of the 6 sockets. Do not exceed 60 watts per bulb.
8. **Attach Crystal Drapes:** Carefully hang the crystal-clear glass bead strands onto the designated hooks or loops on the chandelier arms and central column. Refer to the product image for the intended arrangement.



Figure 2: Close-up view of the chandelier's canopy and chain, illustrating the connection point to the ceiling.



Figure 3: Detailed view of the crystal-clear glass beads, showing their arrangement on the chandelier arms.

## OPERATING INSTRUCTIONS

---

Once installed, the Golden Lighting Mirabella Chandelier operates via a standard wall switch connected to the electrical circuit. There are no special controls on the fixture itself.

- **Turning On/Off:** Use the wall switch to turn the chandelier lights on or off.
- **Bulb Replacement:** To replace a bulb, ensure the power is turned off at the wall switch and preferably at the circuit breaker. Allow bulbs to cool completely before touching. Unscrew the old bulb and screw in a new one of the correct type and wattage (E12 Candelabra base, max 60W incandescent or LED equivalent).

## MAINTENANCE

---

Regular maintenance will help preserve the appearance and functionality of your chandelier.

- **Cleaning:** Turn off power before cleaning. Dust the fixture regularly with a soft, dry cloth. For more thorough cleaning, use a slightly damp cloth with mild soap and water, then dry immediately. Avoid abrasive cleaners or solvents, as they can damage the finish.

- **Crystal Cleaning:** The crystal-clear glass beads can be gently wiped with a soft, lint-free cloth dampened with a glass cleaner solution. Ensure no liquid drips into electrical components.
- **Inspections:** Periodically check all connections and mounting hardware to ensure they remain secure.

## TROUBLESHOOTING

If you experience issues with your chandelier, refer to the following common problems and solutions:

Problem	Possible Cause	Solution
Light does not turn on.	No power to the fixture; Loose wiring; Faulty bulb.	Check circuit breaker/fuse. Ensure wall switch is on. Verify all wire connections are secure. Replace bulb.
Lights flicker.	Loose bulb; Loose wiring connection; Incompatible dimmer switch.	Tighten bulbs. Check wire connections. Ensure dimmer switch is compatible with incandescent/LED bulbs.
Fixture is unstable or wobbles.	Mounting hardware not secure; Junction box not adequately supported.	Ensure mounting strap and canopy are tightly secured. Consult an electrician to reinforce the junction box if necessary.

## SPECIFICATIONS

Feature	Detail
Brand	Golden Lighting
Model Name	Mirabella
Part Number	7644-6 PW
Color	Silver (Pewter Finish)
Material	Alloy Steel, Crystal-Clear Glass Beads
Style	Modern
Light Fixture Form	Chandelier
Product Dimensions	25.5"L x 25.5"W x 25.75"H
Item Weight	7.35 pounds
Indoor/Outdoor Usage	Indoor
Power Source	Corded Electric
Installation Type	Semi Flush Mount (Chain Hung)
Light Source Type	Incandescent (compatible with LED)
Number of Light Sources	6

Feature	Detail
Voltage	120 Volts
Wattage (Max per bulb)	60 watts
Embellishment	Crystal
Safety Rating	UL Listed
Assembly Required	Yes

## WARRANTY

---

This Golden Lighting Mirabella Chandelier is covered by a 443-year limited manufacturer's warranty. Please retain your proof of purchase for warranty claims. For specific details regarding warranty coverage and terms, refer to the documentation included with your product or contact Golden Lighting customer service.

## SUPPORT

---

If you have any questions regarding the installation, operation, or maintenance of your Golden Lighting Mirabella Chandelier, or if you require technical assistance, please contact Golden Lighting customer support. It is recommended to consult a qualified electrician for any complex electrical issues or if you are unsure about any installation steps.

For further information, you may visit the official Golden Lighting website or refer to the contact details provided on your product packaging.