

[Manuals.plus](#) /

› [Canarm](#) /

› Canarm Vesta 2-Light Flush Mount Ceiling Light Instruction Manual

Canarm IFM564B13BGY

Canarm Vesta 2-Light Flush Mount Ceiling Light

Model: IFM564B13BGY

IMPORTANT SAFETY INFORMATION

Please read and understand all instructions before beginning installation. Failure to do so may result in electric shock, fire, or other injuries that could be fatal or cause property damage.

- **WARNING:** Risk of electric shock. Disconnect power at the circuit breaker or fuse box before installation or servicing.
- All electrical connections must be in accordance with local codes, ordinances, or the National Electric Code (NEC). Consult a qualified electrician if you are unfamiliar with proper electrical wiring connections.
- Use only UL/cUL listed wire connectors suitable for the size, type, and number of conductors.
- Do not exceed the recommended wattage for bulbs. Refer to the fixture marking for maximum wattage.
- Handle the fixture with care. Avoid dropping or striking the fixture, as this may cause damage.
- Keep combustible materials away from the light fixture.

PACKAGE CONTENTS

Verify that all components are present before beginning installation:

- Vesta 2-Light Flush Mount Ceiling Light Fixture
- Mounting Hardware (screws, wire nuts, mounting bracket)
- Instruction Manual



Image: The Vesta 2-Light Flush Mount Ceiling Light, featuring a brushed grey finish and wood beads, installed on a ceiling in a room setting.

INSTALLATION INSTRUCTIONS

The Vesta Flush Mount Ceiling Light features an Easy Connect system for simplified installation. Follow these steps carefully:

1. **Turn Off Power:** Before starting, ensure the power to the junction box is turned off at the circuit breaker or fuse box.
2. **Prepare Mounting:** Attach the mounting bracket (included) to the junction box using the provided screws. Ensure it is securely fastened.
3. **Wiring Connections:**
 - Connect the bare copper ground wire from the fixture to the ground wire from the junction box (usually bare copper or green) using a wire nut.
 - Connect the white wire from the fixture to the white (neutral) wire from the junction box using a wire nut.
 - Connect the black wire from the fixture to the black (hot) wire from the junction box using a wire nut.

Note: If your house wiring does not include a ground wire, consult a qualified electrician.

4. **Attach Fixture:** Carefully align the fixture with the mounting bracket and secure it using the provided screws. Ensure no wires are pinched during this step.
5. **Install Bulbs:** Insert two 60W Type A bulbs (not included) into the sockets. Do not exceed the maximum wattage.
6. **Restore Power:** Once the fixture is securely installed and bulbs are in place, restore power at the circuit breaker.



Image: A detailed view of the Vesta ceiling light, highlighting its brushed grey metal frame and decorative wood beads.

OPERATION

The Vesta 2-Light Flush Mount Ceiling Light is operated via a standard wall switch connected to the circuit. Ensure the light bulbs are correctly installed before operation.

- **Turning On/Off:** Flip the wall switch to the "ON" position to illuminate the fixture. Flip it to the "OFF" position to turn off the light.
- **Bulb Type:** This fixture requires two Type A bulbs, up to 60W each. Incandescent bulbs are supported.
- **Dimming:** This fixture is noted as "Not Dimmable" in the specifications. Do not use with dimmer switches.

MAINTENANCE

Regular maintenance ensures the longevity and optimal performance of your Vesta ceiling light.

- **Cleaning:**
 - Always disconnect power before cleaning.
 - Wipe the fixture with a soft, dry cloth.
 - Do not use abrasive cleaners, solvents, or polishes as they may damage the finish.
 - For the wood beads, a dry or slightly damp cloth is recommended. Avoid excessive moisture.
- **Bulb Replacement:**
 - Turn off power at the circuit breaker before replacing bulbs.
 - Allow bulbs to cool completely before touching.
 - Unscrew the old bulb and screw in a new 60W Type A bulb.
 - Ensure the replacement bulb matches the specified wattage and type.

TROUBLESHOOTING

Problem	Possible Cause	Solution
Light does not turn on.	• Power is off at the circuit breaker. • Loose wire connections. • Defective bulb. • Faulty wall switch.	• Check the circuit breaker and ensure power is on. • Turn off power, check all wire connections. • Replace the bulb with a new one. • Consult a qualified electrician to inspect the switch.
Light flickers.	• Loose bulb. • Incorrect bulb type or wattage. • Loose wire connections.	• Tighten the bulb securely. • Ensure bulbs are 60W Type A. • Turn off power, check all wire connections.
Fixture hums.	• Incompatible dimmer switch (fixture is not dimmable). • Loose wiring.	• Remove any dimmer switch and replace with a standard ON/OFF switch. • Turn off power, check all wire connections.

SPECIFICATIONS

Model Name:	Vesta
Model Number:	IFM564B13BGY
Brand:	Canarm
Light Fixture Form:	Close to Ceiling / Flush Mount
Material:	Metal (Brushed finish), Wood (Beads)
Number of Light Sources:	2
Light Source Type:	Incandescent
Max Wattage per Bulb:	60W Type A
Voltage:	120 Volts
Dimmable:	No
Item Dimensions (L x W x H):	13"L x 4.38"W x 8.75"H
Item Weight:	4.62 Pounds
Indoor/Outdoor Usage:	Indoor
Required Assembly:	Yes

WARRANTY AND SUPPORT

This Canarm Vesta 2-Light Flush Mount Ceiling Light is covered by a **1-year manufacturer's warranty** from the date of purchase. For warranty claims, technical assistance, or replacement parts, please contact Canarm customer support directly. Keep your proof of purchase for warranty validation.

Contact information for Canarm can typically be found on their official website or on the product packaging.

ASK A QUESTION ABOUT THIS MANUAL

Ask about setup, troubleshooting, compatibility, parts, safety, or missing instructions. Manuals+ will review the question and use this page's manual context to help answer it.

Name

Anonymous

Email

you@example.com

After a successful submission, we securely hash the supplied account or form email before sending it to Microsoft Advertising for conversion attribution. [Privacy details](#).

Question

Example: How do I reset this device or fix this error?

Details

Model number, symptoms, what you tried, or the section of the manual you are using.

Submit question