

Al-Harameen HA-5115

Al-Harameen HA-5115 Islamic Mosque Digital Clock User Manual

INTRODUCTION

This manual provides detailed instructions for the setup, operation, and maintenance of your Al-Harameen HA-5115 Islamic Mosque Digital Clock. Designed to display accurate prayer times and offer various useful features, this clock is an essential addition to any home or mosque. Please read this manual thoroughly to ensure proper use and to maximize the functionality of your device.

KEY FEATURES

- **Full Azan for All Prayers:** Enjoy high-quality Azan sound for all five daily prayers with adjustable volume control.
- **Multiple Calendar Systems:** Features six pre-programmed calendar systems, allowing you to select the most appropriate one for your city. Includes local Taqweem for Saudi Arabia (Umm Al-Qura), Gulf countries, Jordan, Palestine, Egypt, North America (ISNA), Indian Subcontinent (University of Islamic Sciences), and Europe (World Islamic Organization). Specific calculation methods like Hanafi for ASR 18:17, MWL 19:17, Egyptian 18:18, University of Islamic Sciences Karachi 15:15, and ISNA 1:30 are supported.
- **Automatic Iqamah Alarm:** A unique alarm that adjusts daily to maintain a consistent time difference relative to the Azan, ensuring you wake up at the desired interval after Fajr Azan.
- **Daily Alarm:** A standard alarm that rings at the same time every day, with an option to disable it on weekends.
- **Hijri and Gregorian Calendars:** Displays both Hijri and Gregorian dates, alternating every 10 seconds, or you can choose to display only one. The Hijri calendar is based on astronomical moon sighting in Makkah.
- **Temperature Display:** Shows temperature readings in both Celsius (°C) and Fahrenheit (°F).
- **Daylight Saving Time (DST) Option:** Includes an option to enable or disable DST for regions that observe it.
- **Gentle Prayer Reminder:** Provides a subtle reminder when the Azan sound is turned off.
- **Adjustable Prayer Time Difference:** Easily adjust prayer times for city outskirts or specific locations.
- **Ascending Alarm Sound:** All alarms feature a gentle wake-up sound that gradually increases in volume.
- **Battery Backup:** Equipped with a charger battery to save programmed settings during power outages.

PACKAGE CONTENTS

Please ensure all items are present in the package:

- Al-Harameen HA-5115 Islamic Mosque Digital Clock
- Power Adapter (Input: 100-240V, Output: DC 9V)
- Remote Control
- User Manual (this document)

SETUP

1. Power Connection

1. Unpack the clock and its accessories carefully.
2. Connect the provided power adapter to the DC 9V input port on the back of the clock.
3. Plug the power adapter into a standard electrical outlet (100-240V, 50/60Hz).
4. The clock will power on, and the display will illuminate.

2. Initial Settings (Using Remote Control)

Upon first power-on or after a long power outage, you may need to set the basic parameters.

- **Set Current Time:** Use the 'TIME' button on the remote to enter time setting mode. Use the arrow keys (Up/Down) to adjust hours and minutes, and 'OK' or 'SET' to confirm.
- **Set Current Date:** Use the 'DATE' button to set the Gregorian date. Adjust year, month, and day using arrow keys and confirm.
- **Select City:** Press the 'CITY' button. Use the arrow keys to navigate through the pre-programmed cities. Select your city or the nearest major city. This will automatically set the correct prayer times based on the selected city's coordinates.
- **Choose Calendar System:** Press the 'CAL' or 'METH' button to cycle through the available prayer time calculation methods (e.g., Umm Al-Qura, MWL, ISNA, Egyptian). Select the one appropriate for your region.
- **Adjust Prayer Time Difference:** If you are in an area not precisely covered by the selected city, or in city outskirts, use the 'ADJ' button to fine-tune individual prayer times (Fajr, Shurooq, Dhuhr, Asr, Maghrib, Isha) by adding or subtracting minutes.
- **Daylight Saving Time (DST):** Press the 'DST' button to toggle Daylight Saving Time ON or OFF, if applicable to your region.



Image: The Al-Harameen HA-5115 clock displayed in a modern living room environment, showcasing its aesthetic integration into home decor.

OPERATING INSTRUCTIONS

1. Azan and Volume Control

- The clock will automatically play the full Azan at each prayer time.
- Use the 'VOL+' and 'VOL-' buttons on the remote control to adjust the Azan volume to your preference.
- To mute the Azan, press the 'MUTE' button. A gentle prayer reminder will activate if Azan sound is off.

2. Setting Alarms

- **Automatic Iqamah Alarm:** Press the 'IQAMAH' button. Use arrow keys to set the desired time difference (in minutes) after the Azan for the Iqamah alarm. This alarm will automatically adjust daily with the changing prayer times.
- **Daily Alarm:** Press the 'ALARM' button. Set a specific time for a regular daily alarm. You can also set this alarm not to ring on weekends by pressing the 'WEEKEND' button while in alarm setting mode. All alarms feature an ascending sound.

3. Display Modes

- **Calendar Display:** The clock automatically alternates between Hijri and Gregorian dates every 10 seconds. To display only one, press the 'H-G' button when the desired calendar is shown.
- **Temperature Display:** The current temperature is displayed in both Celsius and Fahrenheit. No specific action is usually required to view this, as it's part of the standard display.

MAINTENANCE

- **Cleaning:** Use a soft, dry cloth to clean the clock's surface. Do not use abrasive cleaners or solvents, as they may damage the display or casing.
- **Power:** Ensure the clock is connected to a stable power source. The internal battery backup maintains settings during brief power interruptions.
- **Placement:** Place the clock in a dry, indoor environment, away from direct sunlight, extreme temperatures, and high humidity to ensure longevity and accurate temperature readings.

TROUBLESHOOTING

Problem	Possible Cause	Solution
Clock not powering on	Power adapter not connected or faulty outlet.	Check power adapter connection. Try a different electrical outlet.
Incorrect prayer times	Incorrect city or calculation method selected.	Re-select your city and prayer time calculation method. Use the 'ADJ' function for fine-tuning if necessary.
Azan sound not playing	Volume is too low or muted.	Increase volume using 'VOL+' or unmute using 'MUTE' button.
Remote control not working	Batteries are dead or remote is out of range.	Replace remote control batteries. Ensure you are within effective range and pointing the remote at the clock.
Iqamah alarm not adjusting	Iqamah alarm feature not enabled or set incorrectly.	Ensure the Iqamah alarm is set and enabled. Verify the prayer times are correct for the day.

SPECIFICATIONS



Image: The Al-Harameen HA-5115 clock showing its physical dimensions: 36 cm width and 48 cm height.

Feature	Detail
Brand	Al-Harameen
Model Number	HA-5115
Color	Black

Feature	Detail
Display Type	Digital
Style	Automatic
Special Feature	Alarm
Power Source	AC (100-240V, 50/60Hz) with DC 9V output; Battery backup for settings.
Room Type	Indoor (e.g., Kitchen, Living Room, Mosque)
Shape	Rectangular (with arched top design)
Indoor/Outdoor Use	Indoor
Material	TPU
Product Dimensions (Approx.)	36 cm (Width) x 48 cm (Height)
Net Weight (Approx.)	2.83 kg
Shipping Dimensions (Approx.)	48 x 47.5 x 5 cm
Country of Origin	China

WARRANTY AND SUPPORT

Specific warranty information for the Al-Harameen HA-5115 Islamic Mosque Digital Clock is not provided in the product details. Please refer to your purchase documentation or contact the retailer for warranty terms and conditions.

For technical support or further assistance, please contact the manufacturer or your point of purchase. Keep your purchase receipt and model number (HA-5115) handy when seeking support.