



Manuals.plus /

- › Pyle /
- › Pyle PPHP1299WU.5 Karaoke Portable PA Speaker System User Manual

## Pyle PPHP1299WU.5

# Pyle PPHP1299WU.5 Karaoke Portable PA Speaker System User Manual

Model: PPHP1299WU.5

## INTRODUCTION

This manual provides essential information for the safe and effective operation of your Pyle PPHP1299WU.5 Karaoke Portable PA Speaker System. Please read this manual thoroughly before using the product and retain it for future reference.

The Pyle PPHP1299WU.5 is a powerful and versatile portable PA speaker system designed for various applications, including karaoke, public address, outdoor events, and parties. It features wireless Bluetooth connectivity, USB/SD card readers, multiple audio inputs, and a built-in rechargeable battery for extended use. The integrated rolling wheels and extendable handle ensure easy portability.



Image: The Pyle PPHP1299WU.5 portable PA speaker system, showcasing its main unit, two wireless handheld microphones, and the remote control. The speaker features a black finish with a durable grille and integrated handle.

## WHAT'S IN THE BOX

Carefully unpack the box and ensure all items listed below are present and in good condition. If any items are missing or damaged, contact your retailer immediately.

- PA Speaker Unit
- (2) Wireless Handheld Microphones
- Attachable Mic Holders
- Remote Control
- Power/Charging Cable
- (4) 'AA' Batteries (for microphones)
- (2) 'AAA' Batteries (for remote control)



# WHAT'S IN THE BOX

1. PA Speaker
2. (2) Wireless Handheld Microphones
3. Attachable Mic Holders
4. Remote Control



Image: A visual representation of the product's packaging contents, including the main PA speaker unit, two wireless microphones, microphone holders, and the remote control. Key dimensions of the speaker are also indicated.

## SETUP

1. **Initial Charging:** Before first use, fully charge the speaker's built-in battery. Connect the power/charging cable to the AC IN port on the rear panel and plug it into a standard wall outlet. The charging indicator will illuminate.

# Built-in Rechargeable Battery

FOR INDOOR

OUTDOOR USE



**POWER OUTPUT  
1000 WATT MAX**



**BATTERY 12V  
5000MAH**

Image: The Pyle PA speaker highlighting its built-in rechargeable battery, suitable for both indoor and outdoor use. Text overlays indicate a 1000 Watt maximum power output and a 12V 5000mAh battery capacity.

2. **Microphone Setup:** Insert the provided 'AA' batteries into each wireless microphone. Ensure correct polarity.
3. **Remote Control Setup:** Insert the provided 'AAA' batteries into the remote control. Ensure correct polarity.
4. **Positioning:** Place the PA speaker on a stable, flat surface. For optimal sound dispersion, position it in a central location within the listening area. The integrated rolling wheels and extendable handle allow for easy transport.

A person is shown from the waist down, wearing dark blue jeans and white sneakers, pulling a black Pyle PA speaker. The speaker is upright and has a long, extendable black handle that the person is holding. The speaker has a mesh grille on the front and a Pyle logo. The background is a paved outdoor area with a white line. Two callout boxes with red text and dotted lines point to the handle and the wheels.

**Extendable  
Carry Handle**

**Rolling Caster  
Wheels**

Image: A person demonstrating the portability of the Pyle PA speaker, pulling it along using its extendable carry handle and integrated rolling caster wheels.

## OPERATING INSTRUCTIONS

### Control Panel Overview

Familiarize yourself with the control panel located on the rear of the speaker. It includes various inputs, volume controls, and mode selection buttons.



Image: The rear control panel of the Pyle PA speaker, detailing features such as the SD card reader, USB flash reader, wireless connectivity options, FM radio with digital display, and inputs for two wireless microphones.

## Power On/Off

Press the **POWER** button on the rear panel to turn the unit on or off.

## Volume and Tone Adjustment

- Use the **MASTER VOLUME** knob to adjust the overall output volume.
- Adjust **BASS** and **TREBLE** knobs to fine-tune the audio tone.
- Individual volume controls are available for microphone and guitar inputs.

## Bluetooth Connectivity

1. Turn on the speaker and press the **MODE** button until "BLUETOOTH" is displayed on the screen.
2. Enable Bluetooth on your mobile device (smartphone, tablet, PC).
3. Search for Bluetooth devices and select "PYLEUSA" from the list.
4. Once paired, you can stream audio wirelessly from your device to the speaker.

# Bluetooth Wireless Music Streaming Ability



Image: A user wirelessly streaming music to the Pyle PA speaker using Bluetooth technology from their smartphone, demonstrating the speaker's wireless music streaming capability.

## USB/SD Card Playback

- Insert a USB flash drive or SD card into the respective slot on the control panel.
- The speaker will automatically switch to USB/SD mode and begin playing compatible audio files (MP3).
- Use the playback controls (Play/Pause, Next, Previous) on the speaker or remote control.

## Microphone Usage

- Turn on the wireless microphones. They should automatically pair with the speaker.
- Adjust the **MIC VOLUME** knob to control the microphone's output level.
- For wired microphones or guitars, connect them to the **1/4" MIC/GUITAR INPUTS**.



Image: A group of friends engaged in a karaoke session, with one individual singing into a microphone, demonstrating the Pyle PA speaker system's use in a social setting.

## FM Radio

- Press the **MODE** button to select FM radio mode.
- Press the **PLAY/PAUSE** button to auto-scan and save available stations.
- Use the **PREVIOUS/NEXT** buttons to navigate through saved stations.

## External Device Connection (RCA)

- Connect external audio sources (e.g., CD player, mixer) to the **RCA (L/R) LINE INPUT**.
- Use the **RCA (L/R) LINE OUTPUT** to connect to additional speaker systems.

## MAINTENANCE

- **Cleaning:** Use a soft, dry cloth to clean the exterior of the speaker. Do not use abrasive cleaners or solvents.
- **Storage:** When not in use for extended periods, store the speaker in a cool, dry place, away from direct sunlight

and extreme temperatures.

- **Battery Care:** To prolong battery life, fully charge the unit before storing it for long periods. Recharge the battery every 3-6 months if not in regular use.
- **Ventilation:** Ensure the speaker's ventilation openings are not blocked during operation to prevent overheating.

## TROUBLESHOOTING

Problem	Possible Cause	Solution
No power	Battery drained; Power cable not connected; Unit off.	Charge the battery; Ensure power cable is securely connected; Press the POWER button.
No sound output	Volume too low; Incorrect input mode selected; Device not connected properly.	Increase MASTER VOLUME; Press MODE button to select correct input; Check cable connections or Bluetooth pairing.
Microphone not working	Microphone batteries low/dead; Microphone off; MIC VOLUME too low; Microphone not paired (wireless).	Replace microphone batteries; Turn on microphone; Increase MIC VOLUME; Ensure wireless microphones are paired.
Bluetooth not connecting	Speaker not in Bluetooth mode; Device too far; Device already connected to another speaker.	Select Bluetooth mode on speaker; Move device closer; Disconnect from other devices and try again.
Distorted sound	Volume too high; Input source distortion; Speaker placed too close to obstacles.	Reduce volume; Check audio source; Reposition speaker.

## SPECIFICATIONS

**Model:** PPHP1299WU.5

**Power Output:** 1000 Watts (Peak) / 500 Watts (RMS)

**Speaker Type:** 2-Way Full Range Audio Projection Loudspeaker

**Woofers:** 12 inches

**Tweeter:** 1.34 inches

**Impedance:** 4 Ohm

**Frequency Response:** 18 KHz

**Connectivity:** Bluetooth, USB, SD Card, RCA (L/R) Line Input, 1/4" Microphone/Guitar Inputs

**Wireless Microphones:** 2 UHF Microphones

**Battery:** Built-in Rechargeable (12V 5000mAh)

**Power Source:** Battery Powered / AC Powered

**Material:** Plastic, Metal

**Product Dimensions (L x W x H):** 14.7" x 12.2" x 22.8" (approx. 12.6 x 15.16 x 23.04 inches)

**Item Weight:** 36.3 Pounds

**UPC:** 842893118437

## WARRANTY AND SUPPORT

Pyle products are designed and manufactured to the highest standards. For warranty information and technical

support, please refer to the warranty card included with your product or visit the official Pyle website. Keep your purchase receipt as proof of purchase for warranty claims.

For further assistance, you may also refer to the official user manual PDF available online [Pyle PPHP1299WU.5 User Manual PDF](#)