

DALI 243721

DALI Katch G2 Portable Bluetooth Speaker User Manual

Model: 243721

INTRODUCTION

The DALI Katch G2 is a portable Bluetooth speaker designed to deliver high-quality audio in a compact form factor. It combines advanced digital technology with unique design insights to provide a rich sound experience. This manual provides essential information for setting up, operating, maintaining, and troubleshooting your DALI Katch G2 speaker.



Front view of the DALI Katch G2 Portable Bluetooth Speaker in Iron Black.

WHAT'S IN THE BOX

Ensure all items are present before proceeding with setup:

- DALI Katch G2 Portable Bluetooth Speaker
- Power Adapter (15V)
- USB Charge Output Cable
- Quick Start Guide / User Manual
- Carrying Pouch (may vary by region)

SETUP

1. Charging the Speaker

Before first use, fully charge your DALI Katch G2. The powerful 3300mAh internal battery provides up to 30 hours of playtime on a full charge. A full charge typically takes 2 hours using the supplied 15V power adapter.

- Connect the supplied power adapter to the charging port on the speaker.
- Plug the adapter into a wall outlet.
- The power level indicator lights will illuminate to show charging status.

2. Powering On/Off

Press and hold the power button located on the top panel of the speaker to turn it on or off. The power indicator lights will confirm the status.



Top panel controls including the power button and leather strap.

3. Bluetooth Pairing

The DALI Katch G2 features Bluetooth 5.0 for improved connection range and stability, supporting apt-X, apt-X HD, and AAC codecs for high-quality audio streaming.

1. Turn on the DALI Katch G2.
2. Press the Bluetooth pairing button (usually indicated by a Bluetooth symbol) on the speaker. The

indicator light will flash, indicating it's in pairing mode.

3. On your device (smartphone, tablet, computer), go to Bluetooth settings and select "DALI Katch G2" from the list of available devices.
4. Once connected, the Bluetooth indicator light on the speaker will become solid.

NFC Pairing: For devices with NFC, simply tap your NFC-enabled device to the NFC area on the speaker to initiate pairing.

Stereo Pairing: You can connect two DALI Katch G2 speakers wirelessly to create a stereo sound system. Refer to the detailed instructions in the full user manual for specific steps on stereo pairing.



Two DALI Katch G2 speakers can be paired for a stereo experience.

4. Wired Connection (AUX)

For analog audio sources, the DALI Katch G2 includes a 3.5mm stereo mini-jack input.

- Connect one end of a 3.5mm audio cable (not included) to the AUX input port on the speaker.
- Connect the other end to the headphone jack or audio output of your device.
- The speaker will automatically switch to AUX input mode when a cable is detected.



Rear view of the speaker, showing the input ports.

OPERATING THE SPEAKER

Controls

The top panel of the DALI Katch G2 features several buttons for easy control:

- **Power Button:** Press and hold to turn the speaker on/off. A quick press activates the power level indicator lights.
- **Bluetooth Button:** Initiates Bluetooth pairing mode.
- **Volume Up (+):** Increases the playback volume.
- **Volume Down (-):** Decreases the playback volume.
- **Audio Profile Button:** Toggles between different audio profiles (e.g., Clear, Warm) for customized sound.

Charging External Devices

The DALI Katch G2 can also be used as a power bank to charge your mobile devices via its USB output (5V/1A).

- Connect your device's charging cable to the USB output port on the speaker.
- Your device will begin charging automatically.



The DALI Katch G2 can charge your smartphone via its USB output.

Product Overview Video

Watch this official video for a brief overview of the DALI Katch G2's features and design.

Your browser does not support the video tag.

Video: Official DALI Katch G2 Portable Bluetooth Speaker overview (24 seconds).

MAINTENANCE

Proper care will ensure the longevity of your DALI Katch G2 speaker.

- **Cleaning:** Use a soft, dry cloth to clean the speaker's surface. Do not use abrasive cleaners or solvents.
- **Storage:** Store the speaker in a cool, dry place when not in use. Avoid extreme temperatures.
- **Battery Care:** To prolong battery life, avoid fully discharging the battery frequently. Charge it regularly, even if not in use for extended periods.
- **Water Resistance:** Please note that the DALI Katch G2 is *not* waterproof. Avoid exposure to water or excessive moisture.



The DALI Katch G2 is designed for portability, but care should be taken to protect it from elements.

TROUBLESHOOTING

If you encounter issues with your DALI Katch G2, refer to the table below for common problems and solutions.

Problem	Possible Cause	Solution
Speaker does not turn on	Low battery; Power adapter not connected	Charge the speaker fully; Ensure power adapter is securely connected to speaker and outlet
No sound	Volume too low; Incorrect input source; Device not paired	Increase volume on speaker and device; Select correct input (Bluetooth/AUX); Re-pair Bluetooth device
Bluetooth pairing fails	Speaker not in pairing mode; Device too far; Interference	Ensure speaker is in pairing mode; Move device closer (within 100 meters); Turn off other Bluetooth devices
Poor sound quality	Low battery; Device too far; Audio source quality	Charge the speaker; Move device closer; Try a different audio source or file

TECHNICAL SPECIFICATIONS

Key specifications for the DALI Katch G2 Portable Bluetooth Speaker:

Feature	Specification
Model Name	MD-Rrllapo-8160
Speaker Type	Woofer
Special Feature	Portable
Recommended Uses	For Music Players
Compatible Devices	Smartphone
Woofer Diameter	3.5 Inches
Tweeter Diameter	21 Millimeters
Unit Count	1.0 Count
Controller Type	Battery Powered
Battery Life	30 Hours
Charging Time	2 Hours
Item Weight	1.1 Kilograms (2.42 pounds)
Is Waterproof	FALSE
Wireless Communication Technology	Bluetooth
Bluetooth Range	100 Meters
Connectivity Technology	Bluetooth, USB
Audio Output Mode	Stereo
Speaker Maximum Output Power	25 Watts
Product Dimensions	14.21 x 10.04 x 2.91 inches

WARRANTY AND SUPPORT

Warranty Information







The DALI Katch G2 comes with a Limited Warranty. Please refer to the warranty card included in your product packaging or visit the official DALI website for detailed terms and conditions regarding warranty coverage and duration.

Customer Support

For technical assistance, troubleshooting beyond this manual, or warranty claims, please contact DALI customer support through their official website or the contact information provided in your product documentation. When contacting support, please have your product model number (243721) and purchase details ready.

© 2024 DALI. All rights reserved.

Related Documents - 243721

	DALI KATCH G2 Portable Bluetooth Speaker User Manual Comprehensive user manual for the DALI KATCH G2 portable Bluetooth speaker, covering setup, features like True Wireless Stereo and aptX HD, sound modes, connectivity, and technical specifications.
	DALI Touch Panels TD1-S to TD5-S: Features, Specifications, and Operation Comprehensive guide to DALI touch panels TD1-S, TD2-S, TD3-S, TD4-S, and TD5-S, covering features, technical specifications, wiring diagrams, key functions, and DALI address settings for lighting control systems.
	DALI WSR Wireless Subwoofer Receiver Manual - Setup and Operation Guide Comprehensive manual for the DALI WSR Wireless Subwoofer Receiver. Learn how to install, connect, and use the WSR with DALI SOUND HUB and SOUND HUB COMPACT for enhanced audio.
	DALI S25X Thermal Imaging Monocular Quick Start Guide Quick start guide for the DALI S25X series thermal imaging monocular, covering button functions, IR menu configuration, settings, and important usage notes.
	DALI Wall Mounted Touch Panels TD1-4S to TD5-4S User Manual and Technical Guide Comprehensive guide for DALI wall-mounted touch panels (TD1-4S, TD2-4S, TD3-4S, TD4-4S, TD5-4S). Covers features, technical specifications, wiring, operation, RF remote matching, and DALI address settings for single color, dual color, RGB, RGBW, and RGB+CCT lighting control.
	DA-4S 4 Push Button DALI Dimmer - User Manual Comprehensive user manual for the DA-4S 4 Push Button DALI Dimmer. Learn about its features, technical specifications, installation, wiring diagrams, and detailed DALI address setting procedures for unicast, group, scene, and broadcast modes.