Kichler 85069PN

Kichler Elan 85069PN Vada 2-Light LED Vanity Light Instruction Manual

Model: 85069PN

Overview Safety Contents Setup Operation Maintenance Troubleshooting Specifications Warranty Support

1. Product Overview

The Kichler Elan 85069PN Vada Vanity Light is a contemporary 2-light LED fixture designed for bathroom environments. Featuring a polished nickel finish and clear glass shades, this fixture provides efficient and stylish illumination. It is designed for general purpose lighting and is dimmable, offering versatile lighting control.



Figure 1: Kichler Elan 85069PN Vada 2-Light LED Vanity Light. This image shows the polished nickel fixture with two clear, textured glass shades, designed for modern bathroom aesthetics.

2. Important Safety Information

Please read and understand all instructions before beginning installation. Failure to do so may result in electric shock, fire, or other injuries that could be fatal or cause property damage.

- **WARNING:** Risk of electric shock. Disconnect power at the main circuit breaker or fuse box before installation or servicing.

- All electrical connections must be in accordance with local codes, ordinances, or the National Electric Code (NEC). Consult a qualified electrician if you are unfamiliar with proper electrical wiring connections.
- Do not install any fixture assembly closer than 6 inches from any combustible material.
- This fixture is designed for 120V AC power supply.
- Do not attempt to alter the fixture in any way.
- Handle glass components with care to prevent breakage.

3. What's in the Box

Carefully unpack the fixture and check that all components are present and undamaged. Retain all packaging materials until you are sure the product is working correctly.

- Elan 85069PN Vada Vanity Light Fixture
- Integrated LED Bulbs (included)
- Mounting Hardware (typically includes mounting plate, screws, wire nuts)
- Instruction Manual

4. Setup and Installation

Professional installation by a qualified electrician is recommended for safety and proper functionality. Ensure power is disconnected at the circuit breaker before proceeding.

1. **Prepare for Installation:**
    - Turn off power at the main fuse box or circuit breaker.
    - Remove the old fixture (if applicable).
    - Ensure the mounting surface is clean, dry, and structurally sound.
2. **Attach Mounting Plate:**
    - Secure the mounting plate to the junction box using the provided screws.
    - Ensure the mounting plate is level and firmly attached.
3. **Make Electrical Connections:**
    - Connect the fixture's black wire to the supply circuit's black (hot) wire.
    - Connect the fixture's white wire to the supply circuit's white (neutral) wire.
    - Connect the fixture's ground wire to the supply circuit's ground wire (bare copper or green).
    - Secure all connections with approved wire nuts and wrap with electrical tape for added safety.
4. **Mount the Fixture:**
    - Carefully align the fixture with the mounting plate and secure it using the provided screws or decorative nuts.
    - Ensure the fixture is flush against the wall and securely fastened.
5. **Install Glass Shades:**
    - Gently attach the glass shades to the fixture according to the specific design. Avoid overtightening.
6. **Restore Power:**
    - Turn on power at the main circuit breaker.
    - Test the fixture to ensure it functions correctly.

5. Operating Instructions

The Elan 85069PN Vada Vanity Light is designed for simple operation via a standard wall switch. It features integrated LED bulbs that do not require replacement.

- **Turning On/Off:** Use the wall switch connected to the fixture to turn the light on or off.
- **Dimming Function:** This fixture is dimmable. To utilize the dimming feature, ensure you have installed a compatible LED dimmer switch (sold separately) in your wall. Follow the dimmer switch manufacturer's instructions for proper operation.

- **Light Source:** The fixture uses integrated LED technology. Do not attempt to replace the LED components yourself.

6. Care and Maintenance

Proper care ensures the longevity and appearance of your vanity light.

- **Cleaning:**
  - Always disconnect power before cleaning.
  - Wipe the fixture with a soft, dry, or slightly damp cloth.
  - Do not use abrasive cleaners, solvents, or polishes as they may damage the finish.
  - Clean glass shades with a mild glass cleaner and a soft cloth.
- **Bulb Replacement:** The LED bulbs are integrated and not designed for user replacement. If the LEDs fail, contact customer support for assistance.
- **Inspection:** Periodically check all connections and mounting hardware for tightness.

7. Troubleshooting

If you experience issues with your vanity light, refer to the following common problems and solutions:

Problem	Possible Cause	Solution
Light does not turn on.	• Power is off at the circuit breaker. • Loose wire connections. • Faulty wall switch. • Integrated LED failure.	• Check the circuit breaker and ensure power is on. • Turn off power, then check and tighten all wire connections. • Test the wall switch with another device or replace it. • Contact customer support for integrated LED issues.
Light flickers or dims improperly.	• Incompatible dimmer switch. • Loose wire connections. • Voltage fluctuations.	• Ensure an LED-compatible dimmer switch is installed. • Turn off power, then check and tighten all wire connections. • Consult an electrician to check household voltage.
Fixture is loose.	• Mounting screws are not tight. • Mounting plate not securely fastened.	• Turn off power, then tighten all mounting screws. • Ensure the mounting plate is firmly attached to the junction box.

If these solutions do not resolve the issue, please contact Kichler customer support.

8. Product Specifications

Brand	Kichler
Model Number	85069PN
Product Name	Elan Vada Vanity Light
Finish	Polished Nickel
Material	Alloy Steel, Glass
Light Source Type	Integrated LED
Number of Lights	2
Total Wattage	26 Watts (13 Watts per light)
Brightness	750 Lumens
Color Temperature	3000 Kelvin

Voltage	120 Volts
Dimmable	Yes (with compatible LED dimmer)
Room Type	Bathroom
Mounting Type	Up/Down Lighting
Item Weight	7.71 Pounds
Product Dimensions	1 x 1 x 1 inches (Note: These dimensions appear to be placeholder values from the source data and may not reflect actual product size. Refer to packaging for accurate dimensions.)
UPC	887913570871

9. Warranty Information

This Kichler product is covered by a manufacturer's warranty. For specific details regarding the duration and terms of your warranty, please refer to the documentation included with your purchase or visit the official Kichler website. The warranty typically covers defects in materials and workmanship under normal use.
Please retain your proof of purchase for any warranty claims.

10. Customer Support

For technical assistance, replacement parts, or any questions not covered in this manual, please contact Kichler customer support:

- **Website:** www.kichler.com (for product information, FAQs, and contact details)
- **Phone:** Refer to the Kichler website for the most current customer service phone numbers.
- **Email:** Refer to the Kichler website for customer service email contact.

When contacting support, please have your model number (85069PN) and date of purchase readily available.

© 2023 Kichler. All rights reserved. Information subject to change without notice.

Ask a question about this manual

Ask about setup, troubleshooting, compatibility, parts, safety, or missing instructions. Manuals+ will review the question and use this page's manual context to help answer it.

Name

Anonymous

Email

you@example.com

After a successful submission, we securely hash the supplied account or form email before sending it to Microsoft Advertising for conversion attribution. Privacy details.

Question

Example: How do I reset this device or fix this error?

Details

Model number, symptoms, what you tried, or the section of the manual you are using.

Submit question