

Manuals+

[Q & A](#) | [Deep Search](#) | [Upload](#)

manuals.plus /

› [JONATHAN Y](#) /

› [JONATHAN Y Apollo JYL6134A 3-Light LED Pendant Light Instruction Manual](#)

JONATHAN Y JYL6134A

JONATHAN Y Apollo JYL6134A 3-Light LED Pendant Light Instruction Manual

Model: JYL6134A

INTRODUCTION

This manual provides essential instructions for the safe installation, operation, and maintenance of your JONATHAN Y Apollo JYL6134A 3-Light LED Pendant Light. Please read this manual thoroughly before beginning installation and retain it for future reference.

SAFETY INFORMATION

WARNING: Risk of electric shock. Disconnect power at the circuit breaker or fuse box before installation or servicing. Improper installation can result in injury or death.

- All electrical connections must be in accordance with local codes and ordinances, National Electric Code (NEC), and ANSI/NFPA 70-1999.
- Consult a qualified electrician if you are unsure about the installation process.
- This fixture must be hardwired. Professional installation is recommended.
- Do not connect this fixture to an ungrounded electrical system.
- Do not exceed the recommended wattage for bulbs.
- Ensure all connections are secure before restoring power.

PACKAGE CONTENTS

Verify that all components are present before beginning installation:

- Mounting Plate
- Canopy
- Pendant Shades (3)
- LED Bulbs (3)
- Mounting Hardware (screws, wire nuts)



Figure 1: Overview of the JONATHAN Y Apollo 3-Light LED Pendant Light components and features.

SETUP AND INSTALLATION

Professional installation by a qualified electrician is recommended for this hardwired fixture.

1. **Turn Off Power:** Before starting, ensure the power to the circuit is turned off at the main electrical panel.
2. **Prepare Mounting Plate:** Attach the mounting plate to the junction box in the ceiling using the provided screws.
3. **Adjust Pendant Height:** Each pendant's cord length is adjustable. Determine the desired hanging height for each light and secure the cord at the canopy.
4. **Wire Connections:** Connect the fixture's wires to the corresponding household wires (black to black, white to white, ground to ground) using the provided wire nuts. Ensure all connections are secure.
5. **Attach Canopy:** Carefully push the canopy up to the ceiling, covering the junction box and wiring. Secure it with the provided screws.
6. **Install Bulbs:** Screw the included LED bulbs into each pendant socket.
7. **Restore Power:** Once installation is complete and all connections are secure, restore power at the main electrical panel.

FEATURES



ADJUSTABLE



DIMMABLE



BULBS
INCLUDED



EASY
ASSEMBLY



TILTABLE

Figure 2: Key features for installation, including adjustable height and easy assembly.

Video 1: A brief product overview of the JONATHAN Y Apollo 3-Light LED Pendant Light, showcasing its design and features relevant to installation.

OPERATING INSTRUCTIONS

- **Power On/Off:** Operate the light using a standard ON/OFF wall switch.
- **Dimming Function:** This fixture is dimmable. To utilize the dimming feature, ensure you have a compatible dimmer switch installed and dimmable LED bulbs.
- **Adjustable Height:** The height of each pendant can be adjusted during installation to suit your preference and space requirements.

MAINTENANCE

- **Cleaning:** To clean the fixture, turn off the power and wipe with a soft, dry cloth. Do not use abrasive cleaners or solvents.
- **Bulb Replacement:** Ensure power is off before replacing bulbs. Use E26 base LED bulbs, not exceeding 40 watts per bulb.

TROUBLESHOOTING

Problem	Possible Cause	Solution
Light does not illuminate.	Power is off; loose wiring; faulty bulb.	Check circuit breaker; verify wire connections; replace bulb.
Light flickers.	Loose bulb; incompatible dimmer; unstable power supply.	Tighten bulb; ensure dimmer compatibility; consult electrician.
Pendant appears crooked.	Uneven cord adjustment.	Re-adjust cord length for desired alignment.

SPECIFICATIONS

Feature	Detail
Model Number	JYL6134A
Dimensions	33.5"L x 6"W x 10.5"H
Material	Metal
Color/Finish	Black/Brass Gold
Light Source Type	LED
Bulb Base	E26
Number of Lights	3
Max Wattage per Bulb	40 watts
Voltage	120 Volts
Brightness	800 Lumen (per included bulb)
Color Temperature	2700 Kelvin (Warm White)
Installation Type	Flush Mount (Ceiling Mount)
Special Features	Dimmable, Adjustable Height
Indoor/Outdoor Usage	Indoor
Item Weight	5.59 pounds



Figure 3: Detailed dimensions of the pendant light fixture.

WARRANTY AND SUPPORT

Warranty: This product comes with a 30-day manufacturer warranty for defects only. Normal wear and tear is not warranted. Visible damages not noted upon delivery will be determined to be customer damage and will not be warranted. All products are inspected upon arrival, and worn, dirty, or stained merchandise will not be accepted for warranty claims.

For warranty information or support, please contact the internet customer service center.



Video 2: Another product overview from JONATHAN Y, providing additional visual details of the pendant light.