Saved from manuals.plus.
Open the live page for links to other documents and user manuals.

Rii X1-BT

Rii Mini Wireless Keyboard with Touchpad X1-BT User Manual

Model: X1-BT

Product Overview

The Rii Mini Wireless Keyboard X1-BT is a versatile 4-in-1 device combining a wireless keyboard, touchpad, backlit keys, and a laser pointer. It supports both Bluetooth and 2.4G RF wireless connections, offering anti-interference and reliable connectivity. Designed for portability and ease of use, it features a QWERTY layout, an ultra-sensitive touchpad with 90-degree flip design, and a built-in rechargeable Lithium-ion battery. This compact keyboard is compatible with a wide range of devices including smartphones, PCs, notebooks, Smart TVs, HTPCs, Android TV Boxes, PS3, and XBOX.



Image: The Rii Mini Wireless Keyboard X1-BT, showcasing its compact design with a full QWERTY keyboard, touchpad, and a red laser pointer beam extending from the side.

Package Contents

Please verify that all items listed below are included in your package:

- 1 x Rii Mini Wireless Keyboard
- 1 x Wireless Dongle/Receiver (located inside the keyboard)
- 1 x Charging Data Cable
- 1 x User Manual



Image: The Rii Mini Wireless Keyboard, its USB wireless dongle, charging cable, and user manual, laid out to show all included components.

Setup Guide

1. Charging the Keyboard

The keyboard comes with a built-in rechargeable polymer Lithium-ion battery. Before first use, it is recommended to fully charge the device.

- Connect the supplied charging data cable to the keyboard's charging port.
- Connect the other end of the cable to a USB power source (e.g., computer USB port, USB wall adapter).
- The charging indicator light will illuminate during charging and turn off when fully charged.
- Charging Voltage: 4.2V - 5.05V.

2. Connecting to Your Device

The Rii Mini Wireless Keyboard supports two connection methods: 2.4G RF Wireless and Bluetooth.

2.1. 2.4G RF Wireless Connection (Plug and Play)

1. Locate the USB wireless dongle/receiver. It is stored inside the keyboard for convenience.
2. Insert the USB dongle into an available USB port on your device (PC, Smart TV, Android TV Box, etc.).
3. Turn on the Rii Mini Wireless Keyboard.
4. The keyboard should automatically connect to your device. No additional drivers are typically required.

2.2. Bluetooth Connection

For devices with Bluetooth capability and no available USB port, or for a more direct connection:

1. Ensure the keyboard is charged and turned on.
2. Activate Bluetooth on your host device (e.g., smartphone, tablet, smart TV).
3. Put the keyboard into Bluetooth pairing mode. (Specific key combination for pairing mode is not provided in the product description, typically this involves holding a Bluetooth button or Fn + a specific key. Refer to the small user manual included in the package for exact steps if needed).
4. On your device, search for new Bluetooth devices.
5. Select "Rii Mini Wireless Keyboard" or a similar name from the list of available devices.
6. Follow any on-screen prompts to complete the pairing process. You may be asked to enter a code displayed on your screen using the keyboard.



Image: The Rii Mini Wireless Keyboard surrounded by various compatible devices such as a notebook, smart TV, HTPC, laptop, TV box, and projector, illustrating its wide compatibility via 2.4G USB receiver and Bluetooth.

Operating Instructions

Keyboard Functionality

The keyboard features a full QWERTY layout, providing a familiar typing experience in a compact form factor.



Image: A close-up view of the Rii Mini Wireless Keyboard, highlighting its QWERTY key layout and compact design.

Touchpad Operation

The integrated touchpad allows for precise cursor control. It supports multi-touch gestures (if applicable, not specified but common for touchpads) and features a 90-degree flip design for convenient use in various orientations.

- **Single Finger Tap:** Left-click.
- **Two Finger Tap:** Right-click.
- **Two Finger Scroll:** Scroll up/down or left/right.
- **Drag and Drop:** Double-tap and hold the first tap, then drag.

Laser Pointer

The built-in laser pointer is ideal for presentations or highlighting specific areas on a screen.

- To activate the laser pointer, press the dedicated button usually located on the bottom side of the keyboard.
- Release the button to turn off the laser.
- **Caution:** Do not point the laser directly into eyes or at reflective surfaces.



Image: A hand holding the Rii Mini Wireless Keyboard, with its laser pointer beam directed towards a projection screen during a presentation, demonstrating its use as a remote control and pointer.

Backlight Function

The keyboard features a backlight for improved visibility in low-light conditions.

- To turn the backlight on/off, press the dedicated backlight key (often indicated by a light bulb icon or combined with the Fn key).
- The backlight color is a single color.



Image: A pair of hands holding the Rii Mini Wireless Keyboard in a dimly lit room, with the keyboard's backlight illuminated, enhancing visibility of the keys.

Power Saving Features

The keyboard is designed with power-saving features to extend battery life:

- **Auto Sleep:** The keyboard will automatically enter sleep mode after a period of inactivity.
- **Wake-up:** To wake the keyboard from sleep mode, press any key.
- Standby Time: 500-700 hours.

Maintenance

Proper maintenance ensures the longevity and optimal performance of your Rii Mini Wireless Keyboard.

- **Cleaning:** Use a soft, dry cloth to clean the surface of the keyboard and touchpad. For stubborn dirt, a slightly damp cloth can be used, but ensure no moisture enters the device. Avoid harsh chemicals or abrasive cleaners.
- **Battery Care:** To prolong battery life, avoid fully discharging the battery frequently. Charge the keyboard regularly, especially if it will be stored for an extended period. Do not expose the battery to extreme temperatures.

- **Storage:** When not in use, store the keyboard in a cool, dry place away from direct sunlight and extreme temperatures.
- **Handling:** Avoid dropping the keyboard or subjecting it to strong impacts, as this can damage internal components.

Troubleshooting

If you encounter issues with your Rii Mini Wireless Keyboard, please refer to the following common troubleshooting steps:

Keyboard Not Responding / No Connection

- **Check Battery:** Ensure the keyboard is sufficiently charged. Connect it to a power source and allow it to charge for a while.
- **Power On:** Verify that the keyboard's power switch is in the "ON" position.
- **USB Dongle (2.4G RF):**
  - Ensure the USB dongle is securely plugged into a working USB port on your device.
  - Try plugging the dongle into a different USB port.
  - Ensure your device has a standard USB interface.
- **Bluetooth Connection:**
  - Ensure Bluetooth is enabled on your host device.
  - Unpair and re-pair the keyboard from your device's Bluetooth settings.
  - Ensure the keyboard is in pairing mode when attempting to connect.
- **Range:** Ensure the keyboard is within the effective operating range (up to 25 meters) of your device. Obstructions can affect signal strength.
- **Hardware Reset:** If experiencing persistent connection issues, especially with Bluetooth, try a hardware reset. Turn off the keyboard, then turn it back on while holding the **F1** key. Release F1 once the keyboard powers on. The lights will blink, indicating a reset to factory settings.

Touchpad Not Working

- Ensure your fingers are clean and dry when using the touchpad.
- Check if the touchpad has been accidentally disabled (some keyboards have a function key for this, though not explicitly mentioned for this model).
- Restart the keyboard and your device.

Laser Pointer Not Working

- Ensure the battery is charged.
- Press and hold the dedicated laser pointer button firmly.

Specifications

Brand	Rii
Model	X1-BT (Rii Mini Wireless Keyboard)
Connectivity Technology	Bluetooth, RF (2.4G), USB
Keyboard Description	QWERTY
Special Features	Ergonomic, Backlit, Rechargeable, Built-in Laser Pointer, Touchpad
Dimensions (LxWxH)	6 x 2.25 x 0.5 inches (151 x 59 x 12.5 mm)

Item Weight	4.6 ounces (100g)
Operation Temperature Range	Up to 25 meters
Battery Type	Polymer Lithium-ion Battery (1 required, included)
Standby Time	500-700 hours
Charging Voltage	4.2V - 5.05V
Transmission Power	Maximum +4dBM
Supported Operating Systems	Windows 2000, Windows XP, Windows Vista, Win CE, Win 7, Win 8, Linux (Debian-3.1, Redhat-9.0 Ubuntu-8.10 Fedora-7.0 tested), Android OS (with standard USB interface)
Compatible Devices	Smartphones, PC, Notebook, Smart TV, HTPC, Android TV BOX, PS3, XBOX, Projector

Warranty and Support

For warranty information regarding your Rii Mini Wireless Keyboard X1-BT, please refer to the documentation provided at the time of purchase or contact the seller directly. Warranty terms and conditions may vary.
If you require technical support or have questions not covered in this manual, please contact the retailer or manufacturer's customer service department. Keep your purchase receipt or order number handy for faster assistance.

© 2024 Rii. All rights reserved.

Ask a question about this manual

Ask about setup, troubleshooting, compatibility, parts, safety, or missing instructions. Manuals+ will review the question and use this page's manual context to help answer it.

Name

Anonymous

Email

you@example.com

After a successful submission, we securely hash the supplied account or form email before sending it to Microsoft Advertising for conversion attribution. Privacy details.

Question

Example: How do I reset this device or fix this error?

Details

Model number, symptoms, what you tried, or the section of the manual you are using.

Submit question

Open the live page

https://manuals.plus/asin/B07TS7TQ8J

More documents and user manuals: **https://manuals.plus/**