

Manuals+

[Q & A](#) | [Deep Search](#) | [Upload](#)

manuals.plus /

› [artika](#) /

› [artika Bubble Cube 23W LED Vanity Light Fixture Instruction Manual](#)

artika VAN4BC-ON

artika Bubble Cube 23W LED Modern Vanity Light Fixture

MODEL: VAN4BC-ON

Brand: artika

Product Overview

The artika Bubble Cube LED Vanity Light Fixture is designed for bathroom lighting. It features four glass cubes with integrated LED lighting, providing 1500 lumens at 3000K warm white. The fixture has a chrome finish and can be installed to direct light upwards or downwards. It is dimmable and has a rated lifespan of 25,000 hours.

Safety Information

WARNING: Risk of electric shock. Disconnect power at the circuit breaker before installation or servicing. All wiring must be in accordance with national and local electrical codes. If you are unsure about wiring, consult a qualified electrician.

- Read all instructions carefully before beginning installation.
- Ensure the mounting surface can support the weight of the fixture.
- Do not attempt to alter the fixture or its components.
- Keep packaging materials away from children.
- This fixture is designed for indoor use only.

Package Contents

Verify that all components are present before installation:

- LED Vanity Light Fixture (1)
- Mounting Bracket (1)
- Mounting Screws (2)
- Wire Nuts (3)
- Instruction Manual (1)

Installation Instructions

Professional installation is recommended. Ensure power is disconnected at the circuit breaker before proceeding.

1. **Prepare for Installation:** Turn off the main power supply at the circuit breaker. Remove the old fixture if applicable.
2. **Attach Mounting Bracket:** Secure the mounting bracket to the junction box using the provided mounting screws. Ensure the bracket is firmly attached.
3. **Wire Connections:** Connect the fixture's wires to the house wires using wire nuts.
 - Connect the black wire (Live) from the fixture to the black wire from the junction box.
 - Connect the white wire (Neutral) from the fixture to the white wire from the junction box.
 - Connect the green or bare copper wire (Ground) from the fixture to the green or bare copper wire from the junction box.
4. **Mount the Fixture:** Carefully align the fixture with the mounting bracket and secure it with the provided screws. Ensure no wires are pinched.
5. **Restore Power:** Once the fixture is securely installed, restore power at the circuit breaker.



Image: The Artika Bubble Cube Vanity Light installed above a mirror in a modern bathroom setting. This image illustrates the fixture's appearance when mounted.



Image: Diagram showing the dimensions of the Artika Bubble Cube Vanity Light, indicating a length of 24 inches (61 cm) and a width of 5.1 inches (13 cm).

Operating Instructions

The artika Bubble Cube LED Vanity Light Fixture operates via a standard wall switch. It is designed to be dimmable with most LED dimmers. Ensure you use a compatible LED dimmer switch for optimal performance and to avoid damage to the fixture.

- **Turning On/Off:** Use the wall switch connected to the fixture.
- **Dimming:** If a compatible LED dimmer is installed, adjust the dimmer switch to control the light intensity.

Your browser does not support the video tag.

Video: This video demonstrates the features of the Artika LED Bubble Cube 4-Light Bathroom Vanity Light Fixture, including its premium bubble glass, chrome finish, integrated LED, dimmable function, 25,000-hour lifespan, and 1500 lumens output. It also shows the light installed in a bathroom setting.

Maintenance

To maintain the appearance and functionality of your light fixture:

- **Cleaning:** Always disconnect power before cleaning. Wipe the fixture with a soft, damp cloth. Do not use abrasive cleaners or solvents, as these may damage the finish or electrical components.
- **LED Care:** The integrated LED lights are designed for long life and are not replaceable. Do not attempt to open or modify the LED modules.

Troubleshooting

Problem	Possible Cause	Solution
Light does not turn on.	No power supply; loose wiring; faulty switch.	Check circuit breaker. Ensure all wire connections are secure. Test the wall switch.
Light flickers or dims improperly.	Incompatible dimmer switch; loose wiring.	Ensure an LED-compatible dimmer is used. Check wire connections.
Light output is too low.	Dimmer setting too low; fixture not suitable for room size.	Adjust dimmer to maximum. Consider if the fixture's lumen output meets room requirements.

Specifications

- **Model:** VAN4BC-ON
- **Brand:** artika
- **Power:** 23W
- **Light Source:** Integrated LED
- **Brightness:** 1500 Lumens
- **Color Temperature:** 3000K (Warm White)
- **Lifespan:** 25,000 hours
- **Dimmable:** Yes (compatible with most LED dimmers)
- **Material:** Alloy Steel, Glass
- **Finish:** Chrome
- **Product Dimensions:** 24"L x 5.1"W x 3.2"H
- **Item Weight:** 9.8 Pounds
- **Voltage:** 120 Volts
- **Installation Type:** Flush Mount
- **Indoor/Outdoor Usage:** Indoor
- **Certifications:** CSA Certified

Warranty and Support

This artika product comes with a 3-year limited warranty from the date of purchase against defects in materials and

workmanship. For warranty claims or technical support, please contact artika customer service.

Contact Information:

- **Website:** www.artika.com
- **Email:** support@artika.com
- **Phone:** 1-800-XXX-XXXX

Please have your model number (VAN4BC-ON) and proof of purchase ready when contacting support.

