

Manuals+

[Q & A](#) | [Deep Search](#) | [Upload](#)

manuals.plus /

- › [DINGLILIGHTING](#) /
- › [DLLT WS-FNW2-60B 3-Light Wall Light Fixture Instruction Manual](#)

DINGLILIGHTING WS-FNW2-60B

DLLT WS-FNW2-60B 3-Light Wall Light Fixture Instruction Manual

Model: WS-FNW2-60B | Brand: DINGLILIGHTING

1. INTRODUCTION

Thank you for choosing the DLLT WS-FNW2-60B 3-Light Wall Light Fixture. This manual provides essential information for the safe installation, operation, and maintenance of your new lighting fixture. Please read these instructions thoroughly before beginning installation and retain them for future reference.



Image: The DLLT 3-Light Wall Light Fixture in matte black with clear glass shades, installed above a bathroom mirror.

2. SAFETY INFORMATION

- **WARNING:** To avoid electric shock, ensure power is turned off at the circuit breaker before installation.
- All electrical connections must be in accordance with local codes, ordinances, and the National Electric Code (NEC).
- Consult a qualified electrician if you are unsure about the installation process.
- Use only E26 base bulbs, maximum 60W per bulb.
- Do not exceed the recommended wattage.
- Handle glass shades with care to prevent breakage.
- This fixture is designed for indoor use only.

3. WHAT'S IN THE BOX

Your package should contain the following items:

- Light Fixture Body (Matte Black)

- Clear Glass Shades (3 pieces)
- Mounting Hardware
- Instruction Manual

Note: E26 bulbs are sold separately unless specified.

4. SPECIFICATIONS

Brand	DINGLILIGHTING
Model Number	WS-FNW2-60B
Color	Black
Material	Metal, Glass
Style	Modern, Vintage
Light Fixture Form	Vanity
Product Dimensions	22.3"L x 11.3"W x 6.1"H
Power Source	Corded Electric
Installation Type	Wall Mount
Bulb Base	E26
Max Wattage per Bulb	60 Watts
Voltage	120 Volts
Special Feature	Anti-Rust
Indoor/Outdoor Usage	Indoor



Image: Detailed dimensions of the DLLT 3-Light Wall Light Fixture, showing length, width, and height measurements.

5. SETUP AND INSTALLATION

This fixture is designed for quick and easy installation. Follow the steps below:

1. **Turn off Power:** Before starting, ensure the power to the installation area is turned off at the circuit breaker.
2. **Mounting Bracket:** Attach the mounting bracket to the junction box using the provided screws.
3. **Wiring:** Connect the fixture's wires to the house wires according to the instruction manual. Typically, black to black, white to white, and ground to ground.
4. **Secure Fixture:** Secure the fixture body to the mounting bracket.
5. **Install Glass Shades:** Gently screw the clear glass shades onto the lamp holders.
6. **Insert Bulbs:** Screw in the E26 base bulbs (max 60W, not included).
7. **Restore Power:** Turn the power back on at the circuit breaker.



Image: Step-by-step diagram illustrating the assembly of the glass shades and bulbs onto the fixture. The fixture can be installed with the glass shades pointing either up or down, offering versatility in design and light distribution.



Image: The DLLT 3-Light Wall Light Fixture shown with glass shades installed both upwards and downwards, demonstrating its versatile mounting options.

Installation Video:

Your browser does not support the video tag.

Video: Official installation guide for the DLLT 3-Light Wall Light Fixture, demonstrating the setup process.

6. OPERATING INSTRUCTIONS

Once installed, operate the light fixture using a standard wall switch. The fixture is compatible with various E26 base bulbs, including LED, incandescent, and CFL. For optimal aesthetic, Edison-style bulbs are recommended.

- **Power On/Off:** Use the wall switch connected to the fixture to turn the lights on or off.
- **Dimmable Functionality:** If using dimmable bulbs and a compatible dimmer switch (sold separately), you can adjust the light intensity.

EASY ASSEMBLY 4 STEPS



Image: The DLLT 3-Light Wall Light Fixture illuminated, showcasing the bright and warm light output.

7. MAINTENANCE

Regular maintenance will ensure the longevity and optimal performance of your light fixture.

- **Cleaning:** Turn off power before cleaning. Wipe the metal parts with a soft, dry cloth. Clean glass shades with a mild glass cleaner and a soft cloth. Avoid abrasive cleaners.
- **Bulb Replacement:** Ensure power is off before replacing bulbs. Allow bulbs to cool completely. Unscrew old bulbs and replace with new E26 base bulbs (max 60W).
- **Rust Protection:** The fixture features an anti-rust finish for durability in humid environments like bathrooms.

8. TROUBLESHOOTING

If you encounter any issues with your light fixture, refer to the following common troubleshooting steps:

- **Light does not turn on:**
 - Check if the power is on at the circuit breaker.

- Ensure bulbs are screwed in tightly and are not burnt out.
- Verify all wiring connections are secure.
- **Flickering lights:**
 - Ensure bulbs are compatible with your dimmer switch (if applicable).
 - Check for loose wiring connections.
- **Glass shade is loose:**
 - Gently tighten the glass shade onto the lamp holder. Do not overtighten.

9. WARRANTY AND SUPPORT

The DLLT Wall Light Fixture comes with a **12-month assurance and 30-day refund for quality issues**. If for any reason you are not satisfied with your purchase or require technical assistance, please contact DINGLILIGHTING customer support.

For further support, please visit the [DINGLILIGHTING Store on Amazon](#).