

Manuals+

[Q & A](#) | [Deep Search](#) | [Upload](#)

[manuals.plus](#) /

> [Craftmade](#) /

> [Craftmade Que 53302-FB 2-Light Bathroom Vanity Lighting Instruction Manual](#)

Craftmade 53302-FB

Craftmade Que 2-Light Bathroom Vanity Lighting

MODEL: 53302-FB

INTRODUCTION

Thank you for purchasing the Craftmade Que 2-Light Bathroom Vanity Lighting fixture. This manual provides detailed instructions for the safe installation, operation, and maintenance of your new lighting fixture. Please read all instructions carefully before beginning installation and retain this manual for future reference.

The Que collection features clear seeded glass globes and a flat black finish, designed to enhance your home's aesthetic. This fixture is approved for indoor locations only.



Image: Craftmade Que 2-Light Flat Black Vanity Light with clear seeded glass globes, showcasing its design and finish.

SAFETY INFORMATION

- **WARNING:** To avoid electric shock, disconnect power at the circuit breaker or fuse box before installation or servicing.
- All electrical connections must be in accordance with local codes, ordinances, or the National Electric Code (NEC). Consult a qualified electrician if you are unfamiliar with proper electrical wiring connections.
- Use only the recommended bulb type and wattage to prevent overheating and potential fire hazards.
- Do not install this fixture in wet locations. It is designed for indoor use only.
- Handle glass components with care to prevent breakage.

PACKAGE CONTENTS

Verify that all components listed below are included in your package:

- Vanity Light Fixture
- Shade(s) (Clear Seeded Glass Globes)
- Hardware Pack (for mounting)
- Installation Guide (this document)

SPECIFICATIONS

Feature	Detail
Model Number	53302-FB
Dimensions (H x W x D)	10.5" x 14.5" x 7.25"
Backplate Diameter	5"
Weight	3.42 lbs
Number of Lights	2
Bulb Type	Medium Base (E26) A-Type Incandescent, CFL, Halogen, or LED (Bulbs not included)
Max Wattage per Bulb	60 Watts (Total 120 Watts)
Voltage	120 Volts
Finish	Flat Black
Shade Material	Seeded Glass
Material	Alloy Steel, Glass
Indoor/Outdoor Usage	Indoor Only
Special Feature	Dimmable (with dimmable bulbs and dimmer switch)

SETUP AND INSTALLATION

Before you begin: Ensure power is turned off at the circuit breaker. Gather necessary tools (e.g., screwdriver, wire strippers, electrical tape).

1. **Prepare the Mounting Surface:** This fixture is designed to mount to an existing junction box (junction box not included). Ensure the junction box is securely installed and capable of supporting the fixture's weight.
2. **Attach Mounting Hardware:** Secure the mounting bracket (from the hardware pack) to the junction box using the provided screws.
3. **Make Electrical Connections:** Carefully connect the fixture's wires to the corresponding wires from the junction box.
 - Connect the **black** (hot) wire from the fixture to the **black** (hot) wire from the junction box.
 - Connect the **white** (neutral) wire from the fixture to the **white** (neutral) wire from the junction box.
 - Connect the **ground** wire (bare copper or green) from the fixture to the **ground** wire from the junction box and to the mounting bracket.

Secure all connections with wire nuts and wrap with electrical tape for added safety.

4. **Mount the Fixture:** Carefully align the fixture's backplate with the mounting bracket and secure it with the decorative nuts or screws provided in the hardware pack.
5. **Install Glass Shades:** Gently screw the clear seeded glass globes onto the fixture's sockets. Do not overtighten.
6. **Install Bulbs:** Insert the recommended E26 base bulbs (not included) into the sockets.
7. **Restore Power:** Once installation is complete and all components are secure, restore power at the circuit breaker.

OPERATING INSTRUCTIONS

Your Craftmade Que vanity light is designed for straightforward operation.

- **Power On/Off:** Control the light using your standard wall switch.
- **Bulb Requirements:** This fixture uses two (2) medium base (E26) A-Type bulbs, up to 60 watts each. Compatible bulb types include Incandescent, CFL, Halogen, or LED.
- **Dimming Functionality:** If you wish to use the dimming feature, ensure you install dimmable bulbs and connect the fixture to a compatible dimmer switch (sold separately).

MAINTENANCE

Regular maintenance will help preserve the appearance and functionality of your lighting fixture.

- **Cleaning:** Turn off power and allow the fixture to cool before cleaning. Wipe the metal finish with a soft, dry cloth. For glass shades, use a mild glass cleaner on a soft cloth, then dry thoroughly. Avoid abrasive cleaners or solvents that may damage the finish or glass.
- **Bulb Replacement:** Ensure power is off and bulbs are cool before replacing. Unscrew the old bulb and screw in a new one of the correct type and wattage.
- **Inspection:** Periodically check all connections and mounting hardware to ensure they remain secure.

TROUBLESHOOTING

If your fixture is not operating correctly, refer to the following common issues:

- **Light does not turn on:**

- Check if the circuit breaker is tripped.
- Ensure the wall switch is in the 'ON' position.
- Verify that bulbs are securely screwed in and are not burnt out.
- Confirm electrical connections are secure (refer to Installation section).

- **Flickering light:**

- Ensure bulbs are fully tightened.
- If using a dimmer, ensure bulbs are dimmable and compatible with the dimmer switch.
- Check for loose electrical connections.

- **Humming noise:**

- Some dimmer switches or LED bulbs may produce a slight hum. Ensure compatibility.

If issues persist after troubleshooting, contact customer support.

WARRANTY AND SUPPORT

This Craftmade lighting fixture comes with a **1-year limited warranty** from the date of purchase. This warranty covers defects in materials and workmanship under normal use.

For warranty claims, technical assistance, or any questions regarding your product, please contact Craftmade customer support:


- **Customer Support Phone:** (800) 486-4892
- **Online Support:** Visit the official Craftmade website for additional resources and contact options.

Please have your model number (53302-FB) and proof of purchase available when contacting support.



[CRAFTMADE Outdoor Pro Plus 52" Installation Guide \(OP52\)](#)

Comprehensive installation guide for the CRAFTMADE Outdoor Pro Plus 52" ceiling fan (Model OP52). Covers safety, parts, assembly, wiring, testing, troubleshooting, and warranty for wet locations.



[Craftmade Nicolas NIC56 Ceiling Fan Installation Guide](#)

Comprehensive installation guide for the Craftmade Nicolas NIC56 ceiling fan, covering safety tips, parts inventory, assembly, wiring, operation, and troubleshooting.




[CRAFTMADE Force XL FXL60 Ceiling Fan Installation Guide](#)

Comprehensive installation guide for the CRAFTMADE Force XL FXL60 ceiling fan, covering safety tips, parts inventory, assembly, wiring, operation, testing, programming, troubleshooting, and warranty information.



[Craftmade Decorator's Choice DCF52XX5C3W Ceiling Fan Installation Guide](#)

This installation guide provides comprehensive instructions for the Craftmade Decorator's Choice DCF52XX5C3W ceiling fan. It includes safety precautions, parts inventory, step-by-step assembly for both downrod and flushmount installations, wiring diagrams, light kit installation, testing procedures, troubleshooting tips, and warranty information.



[Craftmade Cole Ceiling Fan Installation Guide \(CLE44, CLE52\)](#)

Comprehensive installation guide for the Craftmade Cole ceiling fan (models CLE44 and CLE52), covering safety, parts, assembly, wiring, testing, and troubleshooting. Includes diagrams and detailed instructions.



[Craftmade Warplanes Ceiling Fan Installation and Operation Manual](#)

Comprehensive guide for installing and operating the Craftmade Warplanes ceiling fan, including safety precautions, assembly steps, electrical connections, and troubleshooting.