

Manuals+

[Q & A](#) | [Deep Search](#) | [Upload](#)

manuals.plus /

› [Triby](#) /

› [Triby Dual Type Baby Camera BM-DW01 Instruction Manual: Smartphone and Dedicated Monitor Compatible](#)

Triby BM-DW01

Triby Dual Type Baby Camera BM-DW01 Instruction Manual

Smartphone and Dedicated Monitor Compatible

1. INTRODUCTION

Thank you for purchasing the Triby Dual Type Baby Camera BM-DW01. This device is designed to provide reliable monitoring of your child using either a dedicated monitor or your smartphone. This manual will guide you through the setup, operation, and maintenance of your new baby camera.

2. IMPORTANT SAFETY INFORMATION

- **Camera Placement:** Do not install the camera directly above your child's head or within their reach to prevent accidental injury or entanglement.
- **Wireless Interference:** The wireless connection may be interrupted or experience degraded video quality due to distance, physical obstacles (walls, furniture), or other wireless interference. Ensure optimal placement for clear signal.
- **Mobile WiFi Incompatibility:** This device is not compatible with mobile WiFi hotspots for smartphone connectivity. A stable home Wi-Fi network is required.
- **Power Source:** Use only the provided AC adapters for the camera and monitor.

3. PACKAGE CONTENTS

Please check that all items are present in your package:

- Baby Camera Unit (x1)
- Dedicated Monitor Unit (x1)
- AC Power Adapter for Camera (x1)
- AC Power Adapter for Monitor (x1)
- Instruction Manual (this document)

4. PRODUCT OVERVIEW

The Tribby BM-DW01 offers flexible monitoring options with its camera, dedicated monitor, and smartphone app compatibility.



Image: The Tribby BM-DW01 baby camera system, featuring the camera unit, a dedicated 4.3-inch monitor, and a smartphone displaying live feed of a baby.


The system includes a camera unit, a portable dedicated monitor, and supports connection to your smartphone via a dedicated application.



Image: Breakdown of the Tribby BM-DW01 system, illustrating the camera, the 4.3-inch touch panel monitor, and a smartphone

indicating app availability on Google Play and the App Store.

The dual mode allows you to choose between the dedicated monitor for home use or your smartphone for remote viewing.

 専用モニターは家の中での家事に最適！ スマートフォンを占有しない！



CASE. 05
テレワークをしながら




CASE. 06
両手が塞がっていても



CASE. 07
夕食の準備中にも



CASE. 08
夫婦で寝顔を確認

 静止画や動画をスマホに保存！



＼ 祖父母や友人、SNSで可愛い赤ちゃんの様子をシェア！！ ＼

Image: An illustration highlighting the dual mode capability of the Tribby BM-DW01, allowing users to monitor via a smartphone (iOS/Android) or the dedicated 4.3-inch touch panel monitor.

5. SETUP

5.1 Initial Charging

1. Connect the provided AC adapters to the camera and monitor units.
2. Plug the adapters into a power outlet.
3. Allow both units to charge fully before first use. The monitor's built-in battery takes approximately 6 hours to charge.

5.2 Camera Placement

Place the camera on a flat, stable surface in your child's room. Ensure it has a clear line of sight to your child's crib or play area. Avoid placing it too close to the child or in a position where it could be easily knocked over.

5.3 Dedicated Monitor Connection

The dedicated monitor and camera are designed for direct communication. Once both units are powered on, they should automatically connect. If they do not connect, ensure they are within the recommended communication range (5-10 meters, depending on obstacles).

5.4 Smartphone App Connection

To use smartphone monitoring, follow these steps:

1. Download the dedicated application from Google Play or the App Store. Search for "Tribby Baby Camera" or refer to the QR code in the included quick start guide.
2. Install the application on your smartphone.
3. Follow the in-app instructions to pair your camera with your home Wi-Fi network.
4. **Important:** When connecting your smartphone to the camera's Wi-Fi network during the setup process, temporarily disable your mobile data (data roaming) to ensure a successful connection.

充実の機能



スマホ対応

スマートフォンで外出先からもベビーカメラの映像を確認できます。場所を選ばずにモニタリングが可能になり利便性が向上いたしました。



ナイトビジョン

赤ちゃんを寝かしつけた後の真っ暗なお部屋でも赤ちゃんの様子を赤外線ですっきり確認できます。



4.3インチ画面

大画面でより見やすく進化しました。またタッチパネルで直接操作が可能です。



パンチルト機能 (上下左右リモート首振り)

タッチパネル操作でカメラを上下左右にリモートコントロール可能。動く年齢になっても安心です。



大容量充電電池 2600mAh

大容量順電池搭載で様々な場所での利用に便利です。



2WAYトーク

モニターから離れている赤ちゃんに話かけてあげることができます。起きたばかりの不安な赤ちゃんを安心させてあげることができます。



ボイスオン

泣きだしたときなどの赤ちゃんの変化を逃さず、自動的にモニターを起動します。もちろんずっとご覧いただくこともできます。



ズーム

映像を2倍に拡大することができます。話すことができない赤ちゃんのその小さなサインも見逃しません。



温度

室温が設定範囲を外れると教えてくれます。風邪や熱中症予防に便利です。



子守歌

カメラから子守歌を流して、赤ちゃんに聞かせることができます。赤ちゃんの状態に合わせてボリュームも調節できます。



オーディオモード

画面は省電力モードで電力をセーブし、音声のモニタリングのみに特化した使用も可能です。



デジタル電波

デジタル電波で安定した映像を映し出します。

Image: A network diagram illustrating how the smartphone, internet, broadband router, and the baby camera system (camera and dedicated monitor) connect within a home environment.

6. OPERATING INSTRUCTIONS

The Tribby BM-DW01 offers a range of features for comprehensive baby monitoring.

製品スペック		
共通部	周波数帯域	2.4GHz帯
	通信距離	5m~10m ※障害物、障害電波の状況により変化します
	適応温度	0~40℃
カメラ	解像度	1280×720
	レンズ	F2.4
	センサータイプ	CMOS
	電源 (W×D×H)	インプット:100-240V AC,50/60Hz,0.5A アウトプット:5V DC,2.0A
	外寸	約85×100×110mm
	重量	約223g
モニター	内蔵/バッテリー	3.7V,2600mAh
	モニターサイズ	4.3インチ
	電源 (W×D×H)	インプット : 100-240V AC,50/60Hz 0.2A アウトプット : 5V DC, 1.0A
	解像度	480×272
	バッテリー	充電:約6時間/使用:約7時間(最小電力使用時)
	外寸 (W×D×H)	約128×45×90mm
	重量	約209g

Image: An overview of the key features of the Tribby BM-DW01, depicted with icons and brief descriptions.

6.1 Basic Monitoring (Dedicated Monitor)

Once the camera and monitor are connected, the live video feed will automatically display on the 4.3-inch touch panel monitor. You can carry the monitor with you around the house for continuous monitoring.

6.2 Smartphone Monitoring

Open the dedicated app on your smartphone. After successful setup, you can view the live feed from anywhere with an internet connection. This allows for remote monitoring when you are away from home.

6.3 Pan/Tilt Control

Use the controls on the dedicated monitor's touch panel or within the smartphone app to remotely adjust the camera's viewing angle. The camera supports approximately 270° horizontal pan and 120° vertical tilt.

6.4 2-Way Audio

Press and hold the microphone button on the monitor or in the app to speak to your child through the camera's speaker. This allows you to soothe your child with your voice.

6.5 Night Vision

The camera automatically switches to infrared night vision in low-light conditions, providing a clear black-and-white image of your child even in complete darkness (0 Lux minimum illumination).

6.6 Zoom

Digitally zoom in on the image to get a closer look at your child. This feature is available on both the dedicated monitor and the smartphone app.

6.7 Lullaby Function

Select and play lullabies through the camera's speaker to help your child fall asleep or calm down. Adjust the volume as needed.

6.8 Temperature Alarm

Set a desired temperature range. If the room temperature goes outside this range, the monitor will alert you, helping you maintain a comfortable environment for your child.

6.9 Audio Mode (Voice On)

In audio mode, the monitor's screen can turn off to save power, but it will activate and alert you if it detects sound (e.g., your baby crying). This is also referred to as 'Voice On' functionality.

7. MAINTENANCE

- **Cleaning:** Gently wipe the camera lens and monitor screen with a soft, dry cloth. Do not use abrasive cleaners or solvents.
- **Battery Care:** To prolong battery life, avoid fully discharging the monitor's battery frequently. Charge it regularly. If storing the device for an extended period, charge the battery to about 50% and store in a cool, dry place.
- **Storage:** Store the device in a clean, dry environment away from extreme temperatures and direct sunlight.

8. TROUBLESHOOTING

- **No Video/Poor Quality on Monitor:**
 - Ensure both camera and monitor are powered on and charged.
 - Reduce the distance between the camera and monitor.
 - Remove any large obstacles (walls, metal objects) between the units.
 - Check for other 2.4GHz wireless devices that might be causing interference.
- **Smartphone App Cannot Connect or Disconnects Frequently:**
 - Ensure your home Wi-Fi network is stable and has internet access.
 - During initial setup, temporarily disable mobile data/data roaming on your smartphone.
 - Restart the camera unit by unplugging and re-plugging its power adapter.
 - Restart your home Wi-Fi router.
 - Ensure the camera is within range of your home Wi-Fi router.
 - Remember, the device is not compatible with mobile WiFi hotspots.
- **No Sound or Poor Sound Quality:**
 - Check the volume settings on the monitor or smartphone app.
 - Ensure there are no obstructions blocking the camera's microphone or monitor's speaker.

9. SPECIFICATIONS

Category	Item	Specification
General	Brand	Triby
	Model Number	BM-DW01
	Connectivity Technology	Wireless (2.4GHz)

Category	Item	Specification
	Connection Protocol	Wi-Fi
	Recommended Use	Baby Monitor
Camera	Resolution	1280x720 (HD)
	Lens	F2.4
	Sensor Type	CMOS
	Pan/Tilt Range	Horizontal: approx. 270°, Vertical: approx. 120°
	Field of View	60°
	Dimensions (WxDxH)	approx. 85 x 100 x 110 mm
	Weight	approx. 223 g
Monitor	Display	4.3-inch Touch Panel
	Resolution	480x272
	Built-in Battery	1 Lithium-ion battery (included)
	Battery Operation Time	approx. 7 hours
	Battery Charging Time	approx. 6 hours
	Dimensions (WxDxH)	approx. 128 x 45 x 90 mm
Weight	approx. 209 g	
Environmental	Indoor/Outdoor Use	Indoor
	Communication Range	5m-10m (varies with obstacles/interference)
	Color	White

10. WARRANTY AND SUPPORT

For warranty information and customer support, please refer to the warranty card included in your product packaging or visit the official Tribby website. Contact details for technical assistance are typically provided in the full instruction manual or on the manufacturer's support page.