Redragon GM300

Redragon Blazar GM300 USB Condenser Microphone User Manual

Model: GM300

1. Introduction

The Redragon Blazar GM300 is a USB condenser microphone designed for clear audio capture in various applications, including gaming, streaming, and content creation. Its cardioid pickup pattern focuses on sound directly in front of the microphone, minimizing ambient noise for a focused recording experience.

Key Features:

- Professional microphone suitable for streams, games, or professional content creation.
- Removable handle for easy transport and storage.
- Includes tripod, shock mount, and pop filter for a complete setup.
- Cardioid pattern pickup focuses on the user's voice, rejecting side and rear noise.
- Modern minimalist design.
- Built-in volume control and mute function for quick adjustments.

2. What's in the Box

Carefully unpack your Redragon Blazar GM300 microphone and ensure all components are present:

- Redragon GM300 Condenser Microphone
- Desktop Tripod
- Shock Mount
- Pop Filter
- USB Cable (USB Type-B to USB Type-A)



Figure 2.1: Included components of the Redragon Blazar GM300 microphone, showing the microphone unit, shock mount, tripod, pop filter, and USB cable with approximate dimensions.

3. Setup Guide

Follow these steps to set up your Redragon Blazar GM300 microphone:

1. **Attach the Shock Mount:** Gently screw the shock mount onto the top of the desktop tripod. Ensure it is securely fastened.
2. **Insert the Microphone:** Carefully place the Redragon GM300 microphone into the shock mount. The shock mount helps to isolate the microphone from vibrations and handling noise.
3. **Attach the Pop Filter:** Secure the pop filter to the tripod or the microphone stand arm (if using a separate one) so that it is positioned directly in front of the microphone's capsule. The pop filter reduces plosive sounds (like 'p' and 'b') for clearer audio.

4. **Connect the USB Cable:** Plug the USB Type-B end of the provided cable into the port at the bottom of the microphone. Connect the USB Type-A end to an available USB port on your computer (PC or Laptop).
5. **System Recognition:** Your computer should automatically detect and install the necessary drivers for the microphone. The microphone will appear as an audio input device in your operating system's sound settings.
6. **Adjust Position:** Position the microphone so that the front (where the Redragon logo and controls are located) is facing you. The cardioid pickup pattern is most sensitive to sound from this direction.



Figure 3.1: The Redragon Blazar GM300 microphone fully assembled on its desktop tripod, ready for use.

4. Operating Instructions

Once connected, the Redragon Blazar GM300 is generally plug-and-play. Here's how to operate its main functions:

4.1. Volume Control

The microphone features integrated volume control buttons (**+** and **-**) on its body. Press these buttons to adjust the

microphone's input gain (sensitivity). Adjust the gain to an appropriate level to prevent audio clipping or to boost a quiet signal.

4.2. Mute Function

To mute or unmute the microphone, press and hold one of the volume control buttons for approximately 2-3 seconds. The microphone's indicator light (often a red ring) will change color or state to indicate its mute status. Refer to the visual cues on the microphone for confirmation.

4.3. Software Settings

For optimal performance, you may need to adjust the microphone settings within your operating system or recording software:

- **Windows:** Go to *Sound Settings* > *Sound Control Panel* > *Recording* tab. Select the Redragon GM300, click *Properties*, and adjust levels or enhance settings as needed.
- **macOS:** Go to *System Preferences* > *Sound* > *Input* tab. Select the Redragon GM300 and adjust the input volume.
- **Recording/Streaming Software:** Ensure the Redragon GM300 is selected as the primary audio input device within your chosen application (e.g., OBS Studio, Discord, Zoom).



Figure 4.1: The Redragon Blazar GM300 microphone in operation, featuring its distinctive red LED lighting.

5. Maintenance

Proper care will extend the life and performance of your microphone:

- **Cleaning:** Use a soft, dry cloth to wipe the microphone body. Do not use liquid cleaners or solvents, as these can damage the microphone's components.
- **Pop Filter/Foam Cover:** The foam cover and pop filter can be gently cleaned with a damp cloth and mild soap if necessary, then allowed to air dry completely before reattaching.
- **Storage:** When not in use, store the microphone in a clean, dry place, away from extreme temperatures and humidity. Disassembling the microphone from its stand and storing it in its original packaging or a protective case is recommended for long-term storage or transport.
- **Handling:** Avoid dropping the microphone or subjecting it to strong impacts, as this can damage the internal condenser capsule.

6. Troubleshooting

If you encounter issues with your Redragon Blazar GM300 microphone, try the following solutions:

- **No Sound Output:**
  - Ensure the USB cable is securely connected to both the microphone and your computer.
  - Check your computer's sound settings to confirm the Redragon GM300 is selected as the default input device.
  - Verify the microphone is not muted (check the indicator light).
  - Increase the microphone's gain using the **+** button and check the input levels in your software.
  - Try connecting the microphone to a different USB port or another computer to rule out port or system issues.
- **Distorted or Unclear Sound:**
  - Reduce the microphone's gain using the **-** button if the sound is clipping or too loud.
  - Ensure the pop filter is correctly positioned to reduce plosives.
  - Speak directly into the front of the microphone (where the Redragon logo is) to utilize its cardioid pattern effectively.
  - Minimize background noise in your environment.
- **Microphone Not Recognized:**
  - Disconnect and reconnect the USB cable.
  - Restart your computer.
  - Try a different USB port.
  - Check your operating system's Device Manager (Windows) or System Information (macOS) to see if the device is listed, even with an error.

7. Specifications

Feature	Specification
Model Name	Blazar GM300
Connectivity Technology	USB
Connector Type	USB Type-B
Polar Pattern	Unidirectional (Cardioid)
Microphone Form Factor	Microphone Only
Material	Aluminum, ABS Plastic
Compatible Devices	PC, Laptop
Item Weight	1.65 pounds (0.75 Kilograms)
Product Dimensions (L x W x H)	3.54 x 12.6 x 15.75 inches
Impedance	2200 Ohms
Signal-to-Noise Ratio	76 dB
Power Source	Electric Power (USB)

8. Warranty Information

Redragon products typically come with a limited manufacturer's warranty. For specific details regarding the warranty period, coverage, and terms for your Redragon Blazar GM300 microphone, please refer to the warranty card included with your product or visit the official Redragon website. Keep your proof of purchase for warranty claims.

9. Support

For further assistance, technical support, or to inquire about replacement parts, please contact Redragon customer service. You can find contact information and additional resources on the official Redragon website:

Visit Redragon Official Website

© 2023 Redragon. All rights reserved.

Ask a question about this manual

Ask about setup, troubleshooting, compatibility, parts, safety, or missing instructions. Manuals+ will review the question and use this page's manual context to help answer it.

Name

Anonymous

Email

you@example.com

After a successful submission, we securely hash the supplied account or form email before sending it to Microsoft Advertising for conversion attribution. Privacy details.

Question

Example: How do I reset this device or fix this error?

Details

Model number, symptoms, what you tried, or the section of the manual you are using.

Submit question