

## Manuals+

[Q & A](#) | [Deep Search](#) | [Upload](#)

[manuals.plus](#) /

› [DBPOWER](#) /

› [DBPOWER 1080P 5" HD Video Baby Monitor Instruction Manual](#)

## DBPOWER B08CZ3MBFT

# DBPOWER 1080P 5" HD Video Baby Monitor Instruction Manual

Model: B08CZ3MBFT

What's in the

Introduction

Box

Setup

Operation

Features

Maintenance

Troubleshooting

Specifications

Warranty & Support

## 1. INTRODUCTION

Thank you for choosing the DBPOWER 1080P 5" HD Video Baby Monitor. This manual provides essential information for setting up, operating, and maintaining your new baby monitor. Please read it thoroughly before use and keep it for future reference.

This monitor is designed to provide clear, real-time video and audio of your baby, ensuring peace of mind. It features a 5-inch HD display, night vision, two-way audio, and a wide range of monitoring capabilities without requiring an internet connection.



Figure 1: DBPOWER 5-inch HD Video Baby Monitor

## 2. WHAT'S IN THE BOX

Carefully unpack the contents and ensure all items are present:

- Parent Unit (5" HD Display Monitor)
- Baby Unit (Camera)
- Power Adapter for Parent Unit
- Power Adapter for Baby Unit
- User Manual (this document)

### 3. SETUP GUIDE

#### 3.1 Charging the Parent Unit

Before first use, fully charge the Parent Unit for approximately 7-8 hours. This ensures optimal battery performance.

1. Connect the Parent Unit power adapter to the Parent Unit's charging port.
2. Plug the adapter into a power outlet.
3. The battery indicator on the screen will show charging status.

#### 3.2 Positioning the Baby Unit (Camera)

Place the Baby Unit in a location that provides a clear view of your baby. Ensure it is out of reach of children and pets.

1. Place the Baby Unit on a flat surface, such as a dresser or shelf, at least 3 feet (1 meter) away from the baby's crib.
2. Alternatively, the camera can be mounted on a wall or ceiling using appropriate mounting hardware (not included).
3. Connect the Baby Unit power adapter to the Baby Unit's power port and plug it into a power outlet.

# 340° PAN TO 100° TILT



Figure 2: Proper placement and pan/tilt functionality of the Baby Unit

### 3.3 Pairing (if necessary)

The Parent Unit and Baby Unit are pre-paired at the factory. If they lose connection or you are adding additional cameras (up to 4 cameras supported), follow these steps:

1. On the Parent Unit, press the **MENU** button.
2. Navigate to the **Camera** icon and press **OK**.
3. Select an empty camera channel (e.g., CAM 2, CAM 3, CAM 4) and press **OK**.
4. The Parent Unit will display a pairing icon.
5. Within 10 seconds, press the **PAIR** button on the back of the Baby Unit.
6. Once successfully paired, the image from the Baby Unit will appear on the Parent Unit screen.




Figure 3: Multi-camera monitoring capability

## 4. OPERATING INSTRUCTIONS

### 4.1 Basic Controls

- **Power On/Off:** Press and hold the Power button on the Parent Unit.
- **Volume Control:** Use the **UP/DOWN** arrow buttons to adjust the volume.
- **Brightness Control:** Access through the **MENU** settings.
- **Pan/Tilt/Zoom:** Use the directional arrows on the Parent Unit to remotely adjust the camera's view. Press the **OK** button to zoom in (2X).

# ONE PRESS ZOOM



Figure 4: One-press zoom function

## 4.2 Two-Way Audio

Communicate with your baby using the two-way audio feature.

1. Press and hold the **TALK** button on the Parent Unit.
2. Speak clearly into the microphone on the Parent Unit.
3. Release the **TALK** button to hear your baby.

## TWO-WAY TALK



Figure 5: Two-Way Talk feature

### 4.3 Night Vision

The Baby Unit automatically activates infrared night vision in low-light conditions, providing a clear black-and-white image.

# NIGHT VISION

A Clear View in the Night



Figure 6: Night Vision in action

## 5. ADVANCED FEATURES

### 5.1 Lullabies

Soothe your baby with built-in lullabies.

1. Press the  **MENU** button.
2. Navigate to the **Lullabies** icon and press **OK**.
3. Select a lullaby or choose to play all.



Figure 7: Lullabies feature icon

## 5.2 Sound Detection (VOX Mode)

The monitor can be set to activate the screen and/or sound when noise is detected in the baby's room.

1. Press the  **MENU** button.
2. Navigate to the  **Sound Detection** icon and press **OK**.
3. Adjust the sound sensitivity (Low, Medium, High, Off) as desired.

## 5.3 Temperature Monitoring & Alarm

The Baby Unit includes a temperature sensor to monitor the room temperature. You can set alarms for high or low temperatures.

1. Press the  **MENU** button.
2. Navigate to the  **Temperature Alarm** icon and press **OK**.
3. Set your desired high and low temperature thresholds.

## 5.4 Feeding Reminder

Set reminders for feeding times.

1. Press the  **MENU** button.
2. Navigate to the  **Feeding** icon and press **OK**.
3. Select the desired interval for feeding reminders.



Figure 8: Feeding Reminder feature icon

## 5.5 Sleep Mode

Conserve battery life and reduce screen light by setting the Parent Unit to sleep mode.

1. Press the  **MENU** button.
2. Navigate to the **Sleep Mode** icon and press **OK**.
3. Choose the screen off duration (e.g., 30 seconds, 5 minutes, 10 minutes) or turn it off.

## 6. MAINTENANCE

To ensure the longevity and optimal performance of your DBPOWER Baby Monitor, follow these maintenance guidelines:

- **Cleaning:** Use a soft, dry cloth to clean the surfaces of the Parent Unit and Baby Unit. Do not use abrasive cleaners or solvents.
- **Lens Care:** Gently wipe the camera lens with a soft, lint-free cloth. Avoid touching the lens directly with your fingers.
- **Storage:** If storing the monitor for an extended period, ensure both units are fully charged, then power them off. Store in a cool, dry place.
- **Battery Care:** For the Parent Unit, avoid completely draining the battery frequently. Recharge when the low battery indicator appears.

## 7. TROUBLESHOOTING

If you encounter issues with your DBPOWER Baby Monitor, refer to the following common problems and solutions:

Problem	Possible Solution
No image/sound on Parent Unit	Ensure both units are powered on and within range. Check power connections. Re-pair the units if necessary (refer to Section 3.3).
Poor image quality	Check for obstructions between the units. Ensure the camera lens is clean. Adjust the Parent Unit's brightness settings.
Static or interference	Move the Parent Unit closer to the Baby Unit. Avoid placing units near other electronic devices (Wi-Fi routers, microwaves) that may cause interference.
Parent Unit battery drains quickly	Reduce screen brightness. Use Sleep Mode (VOX) to turn off the screen when no sound is detected. Ensure the battery is fully charged before use.
Two-way talk not working	Ensure the <b>TALK</b> button is pressed and held while speaking. Check volume levels on both units.

## 8. SPECIFICATIONS

Feature	Detail
Screen Size	5 Inches
Video Capture Resolution	720p
Optical Zoom	2 x
Viewing Angle	360 Degrees (Pan/Tilt)
Connectivity Technology	Wireless (No Wi-Fi/App required)
Range	Up to 900ft
Battery Power (Parent Unit)	2400 mAh (5 hours video, 8 hours audio-only)
Number of Cameras Supported	Up to 4
Special Features	Night Vision, Two-Way Audio, Lullabies, Sound Detection, Temperature Alarm, Feeding Reminder, Sleep Mode
Indoor/Outdoor Usage	Indoor
Item Weight	1.81 pounds
Power Source	Air Powered (likely refers to wireless operation, but power adapters are included for charging/continuous use)

## 9. WARRANTY & SUPPORT

### 9.1 Product Warranty

The DBPOWER 1080P 5" HD Video Baby Monitor comes with a 12-month warranty from the date of purchase. This warranty covers manufacturing defects and ensures the product is free from defects in material and workmanship under normal use.

The warranty does not cover damage caused by misuse, accident, unauthorized modification, or improper installation. Please retain your proof of purchase for warranty claims.

### 9.2 Customer Support

For technical assistance, troubleshooting, or warranty inquiries, please contact DBPOWER customer support. Refer to the contact information provided on the product packaging or the official DBPOWER website.

Our support team is available to help you with any questions or concerns you may have regarding your baby

monitor.

© 2026 DBPOWER. All rights reserved.