

Manuals+

[Q & A](#) | [Deep Search](#) | [Upload](#)

manuals.plus /

- > [BELIFE](#) /
- > [BELIFE BLF-M01 TV Wall Mount Instruction Manual](#)

BELIFE BLF-M01

BELIFE BLF-M01 TV Wall Mount Instruction Manual

Model: BLF-M01 | Brand: BELIFE

INTRODUCTION

Thank you for choosing the BELIFE BLF-M01 TV Wall Mount. This manual provides detailed instructions for safe installation, operation, and maintenance of your wall mount. Please read this manual thoroughly before installation to ensure correct setup and to prevent damage or injury. This mount is designed for 32 to 55 inch flat and curved televisions or monitors weighing up to 40 kg, supporting VESA patterns up to 400x400mm.

SAFETY INFORMATION

- **Weight Capacity:** Do not exceed the maximum weight capacity of 40 kg (88 lbs). Exceeding this limit may result in serious injury or property damage.
- **Screen Size:** This mount is suitable for screens between 32 and 55 inches. Ensure your TV's VESA pattern is compatible (100x100mm to 400x400mm).
- **Wall Type:** Ensure the mounting surface can safely support the combined weight of the mount and your TV. Consult a professional if unsure about your wall's strength.
- **Tools:** Use appropriate tools for installation. Always wear safety glasses.
- **Assembly:** Do not attempt to assemble the product if any parts are missing or damaged. Contact customer support for assistance.
- **Children:** Keep children away during installation. Small parts may be a choking hazard.
- **Professional Installation:** If you have any doubts about installing this product, please contact a qualified installer.

SPECIFICATIONS

Model Number	BLF-M01
Brand	BELIFE
Compatible Screen Sizes	32 - 55 inches (79 cm - 140 cm)
Maximum Weight Capacity	40 kg (88 lbs)

VESA Compatibility	100x100, 200x200, 300x200, 300x300, 400x200, 400x400 mm
Swivel Range	Up to +/- 60 degrees (depending on screen width)
Tilt Range	+/- 8 degrees
Front Plate Rotation	+/- 3 degrees
Wall Distance (Min-Max)	48 mm - 460 mm
Material	Metal
Color	Black
Product Weight	Approximately 3.84 kg

SETUP AND INSTALLATION

Before you begin, ensure you have all necessary tools and that your wall can support the weight of the mount and your TV. Refer to the included packing list to verify all components are present.

Step 1: Identify Mounting Location and Wall Type

Choose a suitable location on your wall. Ensure there are no hidden electrical wires or plumbing. This mount is designed for solid concrete walls, brick walls, or wood stud walls. Do not install on drywall alone.

Step 2: Attach VESA Plate to TV

Carefully place your TV face down on a soft, clean surface. Identify the VESA mounting holes on the back of your TV. Select the appropriate screws and spacers from the hardware kit that fit your TV's VESA pattern. Attach the VESA plate (the part that connects to the TV) securely to the back of your TV.



Image: The VESA plate, which attaches to the back of your television, showing the four adjustable arms for various VESA patterns.



Image: Side view of the BELIFE BLF-M01 mount with the VESA plate extended, illustrating its full motion capability.

Step 3: Mark and Drill Holes for Wall Plate

Hold the wall plate (the part that attaches to the wall) against the wall at your desired height. Use a level to ensure it is perfectly horizontal. Mark the drill hole locations with a pencil. Drill pilot holes according to the recommended drill bit size for your wall type (refer to the instruction manual included in the package for specific sizes).



Image: The wall plate component of the BELIFE BLF-M01 mount, showing the various mounting points for secure attachment to the wall.

Step 4: Secure Wall Plate to Wall

Insert wall anchors (if required for your wall type) into the drilled holes. Align the wall plate with the holes and secure it using the provided lag bolts and washers. Tighten all bolts firmly, but do not overtighten.

Step 5: Mount TV to Wall Plate

With assistance, carefully lift the TV (with the VESA plate attached) and hook it onto the wall plate. Ensure the TV is securely seated on the wall plate. Engage any safety locking mechanisms to prevent accidental dislodgement.

Robuste Konstruktion

Bis 40kg ohne problemen



Image: Overview of the BELIFE BLF-M01 mount, highlighting its robust double-arm design for strength and integrated cable management features.

OPERATING AND ADJUSTMENTS

The BELIFE BLF-M01 offers various adjustment options for optimal viewing comfort.

Swivel Adjustment

Gently push or pull the TV to swivel it left or right. The mount allows for up to +/- 60 degrees of swivel, depending on the width of your television and its distance from the wall.

Tilt Adjustment

To adjust the vertical viewing angle, loosen the tilt adjustment knobs (if present, or follow specific instructions in the full manual), tilt the screen to your desired angle (up to +/- 8 degrees), and then re-tighten the knobs to secure the position.



Image: Diagram illustrating the minimum (48mm) and maximum (460mm) wall distances, as well as the tilt and rotation capabilities of the mount.

Front Plate Rotation (Level Adjustment)

If your TV is not perfectly level after installation, you can adjust the front plate rotation by up to +/- 3 degrees. This allows for fine-tuning the horizontal alignment of your screen.

MAINTENANCE

- **Regular Checks:** Periodically check all screws and bolts to ensure they remain tight and secure.
- **Cleaning:** Clean the mount with a soft, dry cloth. Avoid abrasive cleaners or solvents that could damage the finish.
- **Lubrication:** The moving parts are designed for smooth operation and generally do not require lubrication. If movement becomes stiff, consult customer support.

TROUBLESHOOTING

- **TV Not Level:** Use the front plate rotation adjustment to fine-tune the level. Ensure the wall plate was installed horizontally using a level.
- **Mount Feels Loose:** Re-check all mounting bolts on both the wall and the TV. Ensure they are securely tightened. Do not overtighten.
- **Difficulty Adjusting:** Ensure no cables are snagged or obstructing movement. Check if any adjustment knobs or screws need to be loosened before adjusting and re-tightened afterward.
- **Missing Parts:** If any parts are missing from the package, contact BELIFE customer support immediately.

WARRANTY AND SUPPORT

BELIFE offers a **10-year warranty** on this product, ensuring quality and reliability. For technical support, warranty claims, or any questions regarding your BELIFE BLF-M01 TV Wall Mount, please refer to the contact information provided with your purchase or visit the official BELIFE website.

Please retain your proof of purchase for warranty purposes.

