

Hadisala H3

Hadisala H3 Portable Wireless Speaker

USER MANUAL

Model: H3 | Brand: Hadisala

Introduction

Thank you for choosing the Hadisala H3 Portable Wireless Speaker. This manual provides essential information for setting up, operating, and maintaining your speaker. The H3 speaker features Bluetooth 5.0 for stable connections, rich bass and HD stereo sound, IPX7 waterproof rating, and up to 15 hours of playtime. It also supports True Wireless Stereo (TWS) pairing for an enhanced audio experience.



Image: The Hadisala H3 speaker, showcasing its sleek design and waterproof capability with water splashing around it.

Package Contents

Please check the box for the following items:

- Hadisala H3 Bluetooth Speaker
- User Manual (this document)
- USB-C Charging Cable
- Retail Box

Product Overview and Controls

Familiarize yourself with the speaker's layout and button functions.



Image: Detailed diagram of the Hadisala H3 speaker, highlighting its various ports and control buttons.

Speaker Controls and Ports

Feature	Description / Function
Power ON/OFF Button	Press and hold to power the speaker on or off.
Play/Pause Button	Press to play or pause audio.
Volume Down / Previous Track Button	Press to decrease volume. Hold to go to the previous track.
Volume Up / Next Track Button	Press to increase volume. Hold to go to the next track.
LED Indicator	Indicates power status, charging status, and Bluetooth pairing status.
Charging Port (USB-C)	Connect the USB-C cable for charging the speaker.
TF Card Slot	Insert a TF (Micro SD) card for direct audio playback.

Feature	Description / Function
Microphone	For hands-free calling when connected via Bluetooth.

Setup

1. Charging the Speaker

Before first use, fully charge the speaker. Connect the provided USB-C cable to the speaker's charging port and the other end to a USB power adapter (not included) or a computer's USB port.

- The LED indicator will illuminate during charging.
- A full charge takes approximately 4 hours.
- The LED indicator will turn off or change color once charging is complete.



Image: Visual representation of the speaker's 15-hour playtime capability.

2. Powering On/Off

- **To Power On:** Press and hold the Power ON/OFF button for 2-3 seconds until you hear an audible prompt and the LED indicator lights up.
- **To Power Off:** Press and hold the Power ON/OFF button for 2-3 seconds until you hear an audible prompt and the LED indicator turns off.

3. Bluetooth Pairing

The Hadisala H3 speaker uses Bluetooth 5.0 for a fast and stable connection.

1. Ensure the speaker is powered on and within 33 feet (10 meters) of your Bluetooth device.
2. The LED indicator will flash rapidly, indicating it is in pairing mode.
3. On your device (smartphone, tablet, laptop), enable Bluetooth and search for available devices.
4. Select "Hadisala H3" from the list of devices.
5. Once connected, the LED indicator will stop flashing and remain solid, and you will hear a confirmation sound.



Image: A smartphone displaying a successful Bluetooth connection to the Hadisala H3 speaker.

Operating Instructions

1. Basic Audio Playback

- **Play/Pause:** Press the Play/Pause button.
- **Volume Up:** Press the Volume Up (+) button.
- **Volume Down:** Press the Volume Down (-) button.
- **Next Track:** Hold the Volume Up (+) button.
- **Previous Track:** Hold the Volume Down (-) button.

2. True Wireless Stereo (TWS) Pairing

You can pair two Hadisala H3 speakers together for a true stereo sound experience.

1. Ensure both H3 speakers are powered off.
2. Power on both speakers simultaneously. They will enter Bluetooth pairing mode.
3. On one of the speakers, double-press the Power ON/OFF button. The speakers will attempt to pair with each other.
4. Once successfully paired, you will hear a confirmation sound, and one speaker's LED will flash (master), while the other's will be solid (slave).
5. Now, connect your device to the master speaker via Bluetooth as described in the "Bluetooth Pairing" section.

True Wireless Stereo

Enjoy the 360° surround sound of the cinema



Image: Two Hadisala H3 speakers demonstrating the True Wireless Stereo feature, providing immersive sound.

3. FM Radio Function

The Hadisala H3 speaker includes a built-in FM radio tuner.

- To switch to FM Radio mode, press the Play/Pause button briefly until you hear the FM radio.
- To auto-scan and save stations, press and hold the Play/Pause button. The speaker will scan and store available FM stations.
- Use the Volume Up (+) and Volume Down (-) buttons to navigate between saved stations.

Maintenance

1. Waterproofing (IPX7)

The Hadisala H3 speaker is IPX7 waterproof, meaning it can be submerged in water up to 1 meter (3.3 feet) for up to 30 minutes. Ensure the charging port cover is securely closed before exposing the speaker to water.



IPX7 Waterproof

Stands up to water from
the inside out

Image: The Hadisala H3 speaker demonstrating its IPX7 waterproof capability, suitable for use near water.

Important: Do not expose the speaker to saltwater or other chemicals. Always ensure the port cover is sealed tightly before water exposure.

2. Cleaning

Wipe the speaker with a soft, damp cloth. Do not use abrasive cleaners or solvents, as they may damage the surface.

Troubleshooting

Problem	Possible Cause	Solution
Speaker does not power on.	Low battery.	Charge the speaker fully.

Problem	Possible Cause	Solution
Cannot pair with Bluetooth device.	Speaker not in pairing mode; device Bluetooth off; too far apart.	Ensure speaker is in pairing mode (flashing LED). Turn device Bluetooth off/on. Move speaker closer to device.
No sound.	Volume too low; speaker not connected; audio source issue.	Increase speaker and device volume. Re-pair Bluetooth. Check audio source.
Sound distortion.	Volume too high; low battery; interference.	Reduce volume. Charge speaker. Move away from other electronic devices.
TWS pairing fails.	Speakers not reset; too far apart.	Ensure both speakers are powered off before starting TWS pairing. Keep them close during pairing.

Specifications

Feature	Detail
Model Name	H3
Connectivity Technology	Bluetooth 5.0
Wireless Range	Up to 33 feet (10 meters)
Speaker Type	Portable, Outdoor
Speaker Maximum Output Power	5 Watts
Audio Output Mode	Stereo (with TWS pairing)
Water Resistance Level	IPX7 (Waterproof)
Battery Life	Up to 15 Hours
Battery Capacity	1000 Milliamp Hours
Charging Time	Approximately 4 Hours
Charging Port	USB-C (Input Voltage: 5 Volts)
Item Weight	0.44 Pounds (7.1 ounces)
Dimensions	4.61 x 3.31 x 3.07 inches (Package Dimensions)
Included Components	Bluetooth speaker, User Manual, Retail box

Warranty and Support

Hadisala is committed to providing high-quality products and excellent customer service.

365-Day Free Return Policy

Hadisala offers a 365-day free return policy. If you encounter any issues with your product after a period of use, please contact Hadisala directly. We are dedicated to assisting you with solutions or providing a replacement to ensure a perfect shopping experience.

For support, please refer to the contact information provided with your purchase or visit the official Hadisala website.