Manuals+

Q & A | Deep Search | Upload

manuals.plus /

- > FLAMMA /
- > FLAMMA FS06 Digital Preamp Pedal User Manual

FLAMMA FS06

FLAMMA FS06 Digital Preamp Pedal User Manual

Model: FS06

1. Introduction

The FLAMMA FS06 Digital Preamp Pedal is a compact guitar effects pedal designed to provide a wide range of amplifier tones. It features 7 distinct preamp models, built-in cabinet simulation, and the ability to save custom presets. This manual provides detailed instructions for setting up, operating, and maintaining your FS06 pedal.



Image 1.1: The FLAMMA FS06 Digital Preamp Pedal.

2. PACKAGE CONTENTS

- FLAMMA FS06 Digital Preamp Pedal
- · Quick Guide
- FLAMMA Logo Sticker



Image 2.1: Contents of the FLAMMA FS06 package.

3. SETUP AND CONNECTIONS

3.1 Power Supply

The FS06 pedal requires a **9V DC power supply** with a current output of **more than 303mA**. The power supply is not included. Ensure the correct polarity and sufficient current to prevent operational issues.

3.2 Connecting Your Pedal

The FS06 can be integrated into various audio setups:

- To a Guitar Amplifier's Power Amp: Connect the pedal's output to the power amp input of your guitar amplifier.
- Direct to a Power Amplifier: Connect the pedal's output directly to a dedicated power amplifier.
- To an Audio Interface/Headphone Amplifier/Monitor Speaker/Mixer: Utilize the built-in cabinet simulation by connecting the pedal's output directly to these devices.



Image 3.1: Input jack of the FS06 pedal.



Image 3.2: Output jack of the FS06 pedal.



Image 3.3: FS06 connected to a mixer, utilizing cabinet simulation.

4. OPERATION

4.1 Controls Overview

The FS06 pedal features several knobs and a footswitch for tone shaping and preset management:

- BASS: Adjusts the low-frequency response.
- MID: Adjusts the middle-frequency response.
- TRE (Treble): Adjusts the high-frequency response.
- LEVEL: Controls the overall output volume.
- GAIN: Adjusts the amount of overdrive/distortion.
- SAVE SELECT Button: Used to select preamp models and save presets.
- Footswitch: Toggles the pedal on/off or switches between preamp channels, depending on the selected mode.



Image 4.1: Control knobs and their functions.



Image 4.2: Footswitch functionality.

4.2 Preamp Models

The FS06 offers 7 distinct preamp models, each designed to emulate classic and modern guitar amplifier tones. An LED indicator shows the currently selected effect.

Table 4.1: Preamp Models

| Number | Name | Amp Model Basis |
|--------|--------------|-------------------------------|
| 1 | DELUXEBLUE | Based on Fender® Blues Deluxe |
| 2 | AC31 | Based on Vox® AC30 |
| 3 | CORAL REEF | Based on Two Rock® Coral |
| 4 | PLEX 50 | Based on Marshall® Plexi 50 |
| 5 | BLUE EYE 100 | Based on Friedman® BE-100 |
| 6 | MB 5th Gen | Based on Mesa Boogie® MARK V |

| Number | Name | Amp Model Basis |
|--------|----------|--------------------|
| 7 | HVE 5151 | Based on EVH® 5150 |



Image 4.3: Overview of the 7 preamp models.

4.3 Saving Presets

Each preamp model has two channels, allowing you to save a unique preset for each. To save your settings:

- 1. Select your desired preamp model using the SAVE SELECT button.
- 2. Adjust the BASS, MID, TRE, LEVEL, and GAIN knobs to your preferred settings.
- 3. Press and hold the SAVE SELECT button until the LED indicator flashes, confirming the preset has been saved to the current channel.

This allows you to recall your customized tones instantly during performance or practice.

5. MAINTENANCE

To ensure the longevity and optimal performance of your FLAMMA FS06 pedal, follow these maintenance

guidelines:

- **Cleaning:** Use a soft, dry cloth to clean the pedal's exterior. Avoid abrasive cleaners or solvents, which can damage the finish.
- **Storage:** Store the pedal in a dry environment, away from extreme temperatures, direct sunlight, and high humidity.
- Handling: Handle the pedal with care. Avoid dropping it or subjecting it to strong impacts.
- Power: Always disconnect the power supply when the pedal is not in use for extended periods.

6. TROUBLESHOOTING

6.1 No Sound or Weak Signal

- Check Power Supply: Ensure the pedal is connected to a 9V DC power supply with sufficient current (over 303mA). Insufficient current can lead to improper operation or no sound.
- Cable Connections: Verify all audio cables are securely connected to the input and output jacks.
- Volume/Level Settings: Check the LEVEL knob on the pedal and the volume settings on your amplifier
 or audio interface.
- **Bypass Mode:** If the pedal is in bypass mode, ensure your amplifier or other effects are functioning correctly.

6.2 Unexpected Behavior

- Power Cycle: Disconnect and reconnect the power supply to reset the pedal.
- Factory Reset: Refer to the official FLAMMA website or contact support for instructions on performing a factory reset if issues persist.

7. SPECIFICATIONS

| Feature | Specification |
|--------------------|---|
| Model Number | FS06 |
| Item Weight | 10.5 ounces (0.3 Kilograms) |
| Product Dimensions | 2.75 x 1.97 x 4.78 inches (7 x 5 x 12.1 cm) |
| Material Type | Metal |
| Power Source | Corded Electric |
| Voltage | 9 Volts DC |
| Signal Format | Digital |
| Hardware Interface | 1/4-inch Audio |
| Preamp Models | 7 |
| Saveable Presets | Yes (2 channels per preamp model) |
| Cabinet Simulation | Built-in |

8. WARRANTY AND SUPPORT

For warranty information, technical support, or further inquiries, please visit the official FLAMMA website or contact their customer service directly. Keep your purchase receipt as proof of purchase for warranty claims.

FLAMMA Official Website: Visit the FLAMMA Store on Amazon

© 2023 FLAMMA. All rights reserved. Specifications are subject to change without notice.

Related Documents - FS06

| FLAMMA FB2CO Manual BLO FAAMMA PAAMMA PAA | Flamma FB200 Intelligent Combined Effects Pedal Manual Comprehensive user manual for the Flamma FB200 Intelligent Combined Effects Pedal, covering important notes, safety instructions, performance overview, panel description, device connections, effect modules, operation modes, additional functions, tone descriptions, and technical specifications. |
|--|---|
| FLAMMA FGZOG Outsirs Manual F1.4004. Statementures Manual Season Seas | FLAMMA FG200 Intelligent Combined Effects Pedal Owner's Manual This owner's manual provides comprehensive information on the FLAMMA FG200 Intelligent Combined Effects Pedal, covering safety precautions, performance features, panel layout, connection guides, effect module details, operation modes, additional functions like drum machine and tuner, tone descriptions, and technical specifications. |
| FLAMMA FX 1 D D Sold of the state of the s | Flamma FX100 Guitar Multi-Effects Owner's Manual Comprehensive owner's manual for the Flamma FX100 Guitar Multi-Effects pedal, detailing features, controls, connections, software, effects lists, and specifications. |
| FLAMMA FVG 4 Harmony Owener's Memoal. | FLAMMA FV04 Harmony Pedal: User Manual and Features Comprehensive user manual for the FLAMMA FV04 Harmony pedal, detailing its features, layout, instructions for use, and technical specifications. Learn about harmony modes, reverb effects, and connectivity. |
| PLAMMA FV C 1 For Fifth Correction Pedal General Measure Framma Framma Framma Framma Framma Framma | FLAMMA FV01 Vocal Pitch Correction Pedal Owner's Manual Comprehensive owner's manual for the FLAMMA FV01 Vocal Pitch Correction Pedal, detailing its features, layout, instructions for use, effect list, and technical specifications. Learn how to optimize vocal performance with this audio effects pedal. |
| FLAMMA FS 21 Brum machine & Looper predid Outer Mount FLAMMA ********************************* | FLAMMA FS21 Drum Machine & Looper Pedal Owner's Manual Owner's manual for the FLAMMA FS21 Drum Machine & Looper Pedal, detailing features, layout, operation instructions, editor software, and technical specifications for this high-quality guitar effects pedal. |



[pdf] User Manual Instructions Specifications

FS06 Manual EN V01 2020 12 17 G cdr Kelly Digital Preamp Pedal Owner's Flamma Innovation flammainnovation The LED will not blink when the cab sim is off 4 Footswitch mode has two footswitch modes Users can switch between by pressing and Features 1 7 different preamp models that cover a wide variety of classic modern guitar tones 2 Every model channels with saveable preset slot for each file url group1 M00 00 02 wKgA0GE6qiGAHnt ABJI270kO g204 fileName |||

DigitalPreampPedal OwnersManual

www.flammainnovation.comShenzhenFlammaInnovationCo.,Ltd Content Pr ... footswitchLEDwillblinkslowlywhencabsimison.TheLEDwillnotblinkwhenthecab simisoff. 4.Footswitchmode

FS06 has two foots witch modes. Users can switch between the two modes by pressing and holding the foots witch for justo...

lang:en score:23 filesize: 1.15 M page_count: 13 document date: 2020-12-17



Woodbrass Compatible Devices List

A comprehensive list of compatible devices for the MyVolts AA927MS cable, covering a wide range of audio equipment brands and models.

lang:en score:7 filesize: 359.66 K page_count: 35 document date: 2022-10-05