

SYNCO SY-XVIEW-M4



SYNCO XView SY-XVIEW-M4 Selfie Monitor Screen User Manual

Model: SY-XVIEW-M4

1. INTRODUCTION AND OVERVIEW

The SYNCO XView SY-XVIEW-M4 is a wireless selfie monitor screen designed to enhance video recording and live streaming experiences for content creators using iPhone and Android devices. This compact and versatile monitor provides real-time preview, pro-level control, and high-quality 4K 30fps recording capabilities, making it an essential tool for vlogging, interviews, and various content creation scenarios.

2. KEY FEATURES

- **Wireless Connectivity:** Utilizes Smart 5.8GHz P2P technology for encrypted, fast, and lag-free transmission to your smartphone.
- **Real-Time 4K Mirroring:** Provides instant, high-resolution mirroring of your phone's rear camera, allowing for precise framing, focusing, and shot adjustments.
- **Integrated Audio:** Features a built-in speaker for up to 3 hours of audio playback, enabling the inclusion of music, voiceovers, or ambient sounds directly during recording.
- **Remote Control:** Offers secure wireless control from up to 164 feet (50 meters) away, with dedicated buttons on the monitor to start or stop recording.
- **Magnetic Mounting:** Equipped with a magnetic grip for quick attachment to metal surfaces such as tripods, fridge doors, or gym bars.
- **Compact and Durable Design:** Smaller than most smartphones, with adjustable brightness for various lighting conditions, suitable for both indoor and outdoor use.
- **Multitasking Capability:** Supports recording 4K videos while simultaneously browsing other apps, replying to messages, or playing background music on your phone.

3. SETUP AND OPERATING INSTRUCTIONS

3.1. Initial Setup

1. **Charge the Device:** Ensure the SYNCO XView monitor is fully charged before first use.
2. **Prepare Your Phone:** For optimal magnetic performance, attach the provided magnetic ring directly to your smartphone.
3. **Enable Wi-Fi:** Ensure your smartphone's Wi-Fi is active to facilitate the P2P wireless connection.
4. **App Recommendation:** For recording 4K video, it is recommended to use a professional camera application such as the Blackmagic Camera App.

3.2. Connecting and Operation

1. **Power On:** Turn on the SYNCO XView monitor. It will automatically initiate the auto-pairing process.
2. **Connect to Phone:** The monitor will establish an encrypted 5.8GHz P2P connection with your smartphone. No manual pairing steps are typically required beyond ensuring Wi-Fi is on.
3. **Mounting:** Secure the monitor to your desired surface using its magnetic grip. This can include tripods, metal fixtures, or other compatible surfaces.
4. **Real-Time Monitoring:** The monitor will display a real-time, 4K mirrored view from your phone's rear camera.
5. **Adjust Settings:** Use the monitor's controls to adjust framing, focus, zoom, and lighting as needed.
6. **Start/Stop Recording:** Utilize the dedicated buttons on the SYNCO XView monitor to wirelessly start or stop your recording from up to 164 feet away.
7. **Audio Playback:** Leverage the built-in speaker to play audio directly from the monitor during your recording sessions.

4. SPECIFICATIONS

Feature	Detail
Model Number	SY-XVIEW-M4
Item Weight	3.73 ounces
Package Dimensions	5.31 x 3.9 x 1.81 inches
Color	Black
Material Type	Plastic
Power Source	Battery Powered
Wireless Technology	Smart 5.8GHz P2P
Video Resolution	Up to 4K 30fps mirroring/recording
Wireless Control Range	Up to 164 feet (50 meters)
Audio Playback	Built-in speaker with 3-hour runtime

5. TROUBLESHOOTING

- **No Connection:** Ensure your smartphone's Wi-Fi is enabled. Verify the monitor is powered on and fully charged.
- **Poor Magnetic Grip:** For best magnetic performance, ensure the magnetic ring is attached directly to your phone, not over a thick case.
- **No 4K Recording:** Confirm you are using a recommended camera application (e.g., Blackmagic Camera App) that supports 4K recording with external monitors.
- **Audio Issues:** Check the monitor's volume settings. Ensure no other audio devices are interfering with the connection.
- **Device Incompatibility:** Note that the SYNCO XView is not compatible with Google Pixel devices.

6. MAINTENANCE

- **Cleaning:** Use a soft, dry cloth to clean the monitor screen and body. Avoid abrasive cleaners or solvents.
- **Storage:** Store the monitor in a cool, dry place away from direct sunlight and extreme temperatures when not in use.
- **Battery Care:** Recharge the battery regularly, even if the device is not frequently used, to maintain battery health.
- **Magnetic Ring:** Periodically check the magnetic ring for secure attachment to your phone.

7. WARRANTY AND SUPPORT

For warranty information, technical support, or service inquiries, please refer to the official SYNCO website or contact SYNCO customer service directly. Keep your purchase receipt as proof of purchase for warranty claims.