

Phomemo D30

Phomemo D30 Bluetooth Thermal Label Maker Instruction Manual

Model: D30 | Brand: Phomemo

INTRODUCTION

This manual provides detailed instructions for the safe and efficient operation of your Phomemo D30 Bluetooth Thermal Label Maker. Please read this manual thoroughly before use and retain it for future reference.



Image: The Phomemo D30 Label Maker in white, accompanied by three rolls of adhesive labels and its product packaging.

SETUP

1. Unboxing and Initial Charge

Carefully remove all components from the packaging. The package includes: 1 Phomemo D30 Label Maker, 1 USB Charging Cable, 1 User Guide, and 3 Rolls of Label Paper.

Before first use, fully charge the device using the provided USB cable. The indicator light will show charging status.

2. Installing Label Roll

1. Open the label compartment by gently pressing the side release button or lifting the top cover, depending on the model design.
2. Insert the label roll with the printing surface facing upwards, ensuring it is properly seated in the designated slot.
3. Pull a small portion of the label tape out, extending it past the cutting edge.
4. Close the label compartment securely.



Thermal printing technology Fast - high quality printing No ink needed



60mm/S



203DPI

Image: A close-up view of the Phomemo D30 Label Maker with its top cover open, illustrating the correct placement of a label roll for thermal printing.

OPERATING INSTRUCTIONS

1. App Installation and Connection

Download the "Print Master" app from your device's app store (compatible with iOS and Android smartphones and tablets).

Turn on the Phomemo D30 Label Maker by pressing the power button. The indicator light will illuminate.

Open the "Print Master" app on your mobile device. Ensure Bluetooth is enabled on your device. The app will automatically detect and connect to the label maker.

2. Creating and Printing Labels

Within the "Print Master" app, you can choose from various modes and templates:

- **Lite Mode:** For simple and quick label design.
- **Creation Mode:** Offers extensive functions and materials for customized labels.

- **One-Click Print:** Pre-designed common words and phrases for instant printing.

To create a custom label:

1. Select "Creation Mode" or "New Label" in the app.
2. Choose your desired label size and type (e.g., white, continuous, cut label). The app supports label widths of 12-15mm.
3. Utilize the app's features to add text, icons (over 1000 available), borders (over 60 available), images, barcodes, QR codes, and more. You can also import data from Excel or use OCR functionality.
4. Adjust font styles, sizes, alignment, and character pitch as needed.
5. Preview your label design.
6. Tap "Print Label" or "Print Now" to send the design to the label maker.
7. Once printed, gently tear off the label along the cutting edge.

Create Labels for Every Need

Variety of templates and label styles

Label Creation Tools:

- Text: Dear Mike Happy Birthday
- Icon: Hamburger, Strawberry, Flower, Fork, Knife
- Shape line: Circle, Square, Rectangle
- Border: Dear Mike
- 1D Code: Memoqueen 0627283618
- QR Code: QR code linking to Memoqueen
- Time: 05-23-2022 10:29:03
- Picture: Cat image

Label Examples:

- Jupiter
- Merry X'Mas
- Happy birthday
- Alice
- 2022-05-16
- \$1.5
- Memoqueen 0627283618
- T-shirt

Image: Screenshot of the "Print Master" app, displaying diverse label creation tools and templates for text, icons, barcodes, and QR codes.

Bluetooth Connectivity Technology Easy to Use

Free app is easy to create custom



Support iOS&Android



Image: The Phomemo D30 Label Maker shown alongside a smartphone running the "Print Master" app, highlighting Bluetooth connectivity and customization options like fonts and templates.

Video Demonstrations

Your browser does not support the video tag.

Video: A quick look at the Phomemo D30 Label Maker, demonstrating its compact size and ease of use with the companion app.

Your browser does not support the video tag.


Video: A thorough review demonstrating the Phomemo D30 app's features and the quality of the printed labels.

MAINTENANCE

To ensure optimal performance and longevity of your Phomemo D30 Label Maker, follow these maintenance guidelines:

- **Cleaning:** Regularly clean the print head with a soft, lint-free cloth. Do not use harsh chemicals or abrasive materials.
- **Storage:** Store the label maker in a cool, dry place away from direct sunlight and extreme temperatures.

- **Battery Care:** Charge the device regularly, even if not in frequent use, to maintain battery health. Avoid fully discharging the battery for extended periods.
- **Label Rolls:** Use only genuine Phomemo D30 thermal label rolls to prevent damage to the print head and ensure print quality.



Creation Mode

Blank label 12x40

Recently Label

- 12X30mm
- 12X40mm
- 12X50mm
- 12.5X74mm
- 14X25mm

Blank label

planet B

planet A

planet C

■ Smarter and Smaller

■ Lighter and portable for you to take away.

■ Printer anytime, anywhere.

2.5X smaller

3X lighter

2X Faster

DPI increased by 25%

Mobile input

Phomemo D30

VS

Keyboard label makers



Image: A visual comparison emphasizing the compact and portable design of the Phomemo D30 Label Maker.

TROUBLESHOOTING

Problem	Possible Cause	Solution
Device not turning on	Low battery; Power button not pressed correctly	Charge the device fully; Press and hold the power button for a few seconds.
Unable to connect via Bluetooth	Bluetooth off on device; App not detecting printer; Printer too far from device	Ensure Bluetooth is enabled; Restart app and printer; Move devices closer (within 10m).

Problem	Possible Cause	Solution
Poor print quality / Faint print	Print head dirty; Incorrect label roll insertion; Low battery	Clean the print head; Re-insert label roll correctly; Charge the device.
Labels not feeding correctly	Label roll jammed or improperly installed	Open compartment, clear any jams, and re-install label roll.

SPECIFICATIONS












Feature	Detail
Model Name	D30
Printing Technology	Thermal (Inkless)
Connectivity	Bluetooth
Print Resolution	203 x 203 DPI
Max Print Speed (Monochrome)	1 ppm (60mm/s)
Compatible Label Width	12-15 mm (0.47-0.59 inches)
Compatible Devices	Smartphones, Tablets (iOS & Android)
Battery Capacity	1000 mAh
Product Dimensions	1.14"D x 2.95"W x 5.17"H (approx. 2.9 x 7.5 x 13.1 cm)
Item Weight	5.5 ounces (approx. 156 grams)
Included Components	Label Maker, USB Cable, User Guide, 3 Roll Paper

WARRANTY AND SUPPORT

The Phomemo D30 Label Maker comes with a limited warranty. For specific warranty terms and conditions, please refer to the warranty card included in your product packaging or visit the official Phomemo website.

For technical support, troubleshooting assistance, or to purchase additional label rolls, please contact Phomemo customer service through their official channels.

Related Documents - D30

<div> <div> <div>Instruction</div> <div>D30</div> <div>Product Instruction</div> </div> <div>  <div>Please read this instruction book carefully before operating the product.</div> </div> </div>	<div> <div>Phomemo D30 Smart Mini Label Maker Product Instruction Manual</div> <div>Comprehensive user guide for the Phomemo D30 Smart Mini Label Maker, detailing item checklist, specifications, parts and features, power and indicator lights, usage instructions, app download and connection, label size identification, printing modes (Lite and Creation), daily cleaning, troubleshooting, warranty information, and FCC compliance.</div> </div>
<div> <div> <div>Quick Start Guide</div> <div>D30</div> </div> <div>  <div>English</div> </div> </div>	<div> <div>Phomemo D30 Label Maker Quick Start Guide</div> <div>A quick start guide for the Phomemo D30 portable thermal label maker, covering unboxing, setup, app connection, paper roll replacement, and charging instructions.</div> </div>
<div> <div> <div>Quick Start Guide</div> <div>D30</div> </div> <div>  <div>English</div> </div> </div>	<div> <div>Phomemo D30 Label Maker Quick Start Guide</div> <div>A quick start guide for the Phomemo D30 Label Maker, covering product introduction, getting started, replacing the paper roll, connection methods, charging, and button/indicator light instructions.</div> </div>
<div> <div>  </div> </div>	<div> <div>Phomemo M220 Quick Start Guide</div> <div>A concise guide to setting up and using the Phomemo M220 label maker, covering preparation, Bluetooth smartphone connection, and PC connectivity via USB, including FCC compliance information and support details.</div> </div>
<div> <div> <div>Instruction</div> <div>D30</div> <div>Product Instruction</div> </div> <div>  <div>Please read this instruction carefully before using this product and keep it properly. For more detailed information, please check the official website: www.phomemo.com</div> <div>  <div>Operation guide QR code</div> <div>• Mobile: Please scan the QR code to get the printer operation guide.</div> </div> <div> <div>Table of Contents</div> <div> <div>01</div> <div>02</div> <div>03</div> <div>04</div> </div> <div> <div>Packing List</div> <div>Parts Description</div> <div>App Download Method</div> <div>Best Guide</div> </div> <div> <div>05</div> <div>06</div> <div>07</div> <div>08</div> </div> <div> <div>Paper Roll Installation</div> <div>Printer Connection</div> <div>Confirm the Label Size</div> <div>Printing Guide</div> </div> <div> <div>09</div> <div>10</div> <div>11</div> </div> <div> <div>Product Specifications</div> <div>Daily Cleaning</div> <div>Solutions for Common Problems</div> </div> <div> <div>12</div> <div>13</div> <div>14</div> </div> <div> <div>Product Warranty</div> <div>FCC Caution</div> <div>Warranty / Maintenance Card</div> </div> </div> <div> <div>01. Packing List</div> <div>    <div>Printer*1 Product instruction*1 Charging cable*1</div> </div> <div>The number of paper rolls in the list is subject to the actual shipment.</div> </div> <div> <div>02. Parts Description</div> <div>Appearance Introduction</div> <div> <div>Printer display</div> <div>  <div> <div>Paper compartment cover</div> <div>Decorative keyring</div> <div>Power button</div> <div>Charging port</div> <div>Paper roll</div> <div>Print head</div> <div>Paper label</div> <div>Indicator light</div> <div>Recharge hole</div> </div> </div> <div> <div>Label paper display</div> <div>  <div> <div>Various labels available for purchase</div> <div>Gap paper display</div> </div> </div> </div> </div> </div></div></div>	

02. Parts Description Power Button and Indicator Light



Indicator light

Power button description

Action	Operation method	Functions
Power	Press and hold 2s	Turn off power
Power	Click	Print out the paper
Power	Double click	Print out the paper (the label paper)

Power indicator status

Green Keep on	Normal status (printing)
Green Flash slowly	Waiting with power on
Green Flash quickly	Charging with power on
Red Keep on	Low level of paper, over-temperature, high temperature
Red Flash slowly	20% battery
Red Flash quickly	10% battery

03. App Download Method



NOTE The app will be downloaded to your phone. Due to the requirements of mobile phone system, the hardware configuration of phone is not the same as the app. Please refer to the app description for more details.

Method 1: Please use your mobile phone to scan the QR code to download the app.



Method 2: Search and download



04. Best Guide

Press and hold for 2s to turn on



Press the power compartment cover of the machine



05. Paper Roll Installation

Take out the label paper, tear off the anti-tacking material



Put the printing paper in the compartment with the printing side left



Roll out the label paper by press it length for normal printing



Press the power compartment cover of the machine



Click the power button to identify the label position



Press out a piece of paper, positioning completed



NOTE When connecting device to the app, please make sure that your printer is turned on and the paper is not empty. Due to the requirements of mobile phone system, the hardware configuration of phone is not the same as the app. Please refer to the app description for more details.

06. Printer Connection

Turn on Bluetooth (mobile phone only)



Open the App



Click to search for the device



Connect immediately



NOTE When connecting device to the app, please make sure that your printer is turned on and the paper is not empty. Due to the requirements of mobile phone system, the hardware configuration of phone is not the same as the app. Please refer to the app description for more details.

07. Confirm the Label Size

Method 1: Touch the anti-tacking guide



Method 2: Check the label paper printing



Method 3: Use a ruler to measure



Method 4: Check the label paper printing



08. Printing Guide Select Edit Version

Lite Mode: Edit simply print quickly



Creation Mode: Multiple functions, create more easily



The user can also select multiple functions and switch editing version in the "More"



08. Printing Guide Lite Mode

Click "Label"



Click to select the corner (the label is printed)



Click the blank box to select text



Add function description



NOTE

If the printing temperature is not uniform, there will be uniformity issues in printed paper

Functions	Operation method	Example
Click to insert text, clear text, add text, delete text, copy text, paste text	Click to insert text	A - A
Add date	Click to add date	MON 2022/12/1
Add specific time point	Click to add time point	MON 10:00 pm
Unit symbol	Click to add unit symbol	MON 100ml

Phomemo D30 Small Label Printer Instruction Manual

Comprehensive instruction manual for the Phomemo D30 Small Label Printer, covering setup, app download, paper installation, printer connection, printing guides (Lite and Creation modes), product specifications, daily cleaning, and troubleshooting common issues.

After editing, click to "Print".



After the printing is completed, turn off the label.



08. Printing Guide - Creation Mode

Click the disk icon and select corresponding label size.



Click to select the corresponding label size and pattern.



If the corresponding size template is not selected correctly, there will be abnormal characters or no content printing on the paper or paper input, etc.

Click "1:1" to input text.



Click function description.



Editing function.



Editing function.



App functions will be updated with new functions in regular phone updates to the actual functions.

Function	Description
1	Click to input text. You can edit the text size, spacing and color of the text.
2	Click to input text. You can edit the text size, spacing and color of the text.
3	Click to input text. You can edit the text size, spacing and color of the text.
4	Click to input text. You can edit the text size, spacing and color of the text.
5	Click to input text. You can edit the text size, spacing and color of the text.
6	Click to input text. You can edit the text size, spacing and color of the text.
7	Click to input text. You can edit the text size, spacing and color of the text.
8	Click to input text. You can edit the text size, spacing and color of the text.
9	Click to input text. You can edit the text size, spacing and color of the text.
10	Click to input text. You can edit the text size, spacing and color of the text.
11	Click to input text. You can edit the text size, spacing and color of the text.
12	Click to input text. You can edit the text size, spacing and color of the text.
13	Click to input text. You can edit the text size, spacing and color of the text.
14	Click to input text. You can edit the text size, spacing and color of the text.
15	Click to input text. You can edit the text size, spacing and color of the text.
16	Click to input text. You can edit the text size, spacing and color of the text.
17	Click to input text. You can edit the text size, spacing and color of the text.
18	Click to input text. You can edit the text size, spacing and color of the text.
19	Click to input text. You can edit the text size, spacing and color of the text.
20	Click to input text. You can edit the text size, spacing and color of the text.

Click the print label after editing.



After the printing is completed, turn off the label.



09. Product Specifications

Product name	Small Label Printer
Product model	SLP
Printing technology	Thermal printing
Effective printing width	32mm
Supportable materials	Thermal paper, coated paper, carbonless paper
Printing resolution	Light resolution, dark resolution
Printing resolution	1200 dpi
Print head service life	100,000
Communication interface	Bluetooth 4.2
Product size	115.5 x 75.5 x 35.5 mm (W x H x D)
Power input	5V-2A
Power supply method	Micro USB
Support operating system	Android

10. Daily Cleaning

Turn off the printer.



Use a cotton swab dipped in a little alcohol.



Wipe the print head gently.



Wait for the alcohol to evaporate and then turn it on and double check the power button to print clearly.



Do not touch the print head with hard objects, otherwise the print head will be permanently damaged and cannot be repaired.

11. Solutions for Common Problems

Not centered, misplaced, offset, skipped, etc.

Problem Cause: Whether the paper roll is correctly placed in the machine?

Please make sure that the label is placed in the machine with printing side facing left. It is placed correctly (printing, printing side).

Problem Cause: Whether the label is correctly placed in the machine?

Please make sure that the label is placed in the machine with printing side facing left. It is placed correctly (printing, printing side).

Problem Cause: Whether the paper roll is correctly placed in the machine?

Please make sure that the label is placed in the machine with printing side facing left. It is placed correctly (printing, printing side).

Problem Cause: Whether the paper roll is correctly placed in the machine?

Please make sure that the label is placed in the machine with printing side facing left. It is placed correctly (printing, printing side).

Problem Cause: Whether the paper roll is correctly placed in the machine?

Please make sure that the label is placed in the machine with printing side facing left. It is placed correctly (printing, printing side).

Problem Cause: Whether the paper roll is correctly placed in the machine?

Please make sure that the label is placed in the machine with printing side facing left. It is placed correctly (printing, printing side).

Problem Cause: Whether the paper roll is correctly placed in the machine?

Please make sure that the label is placed in the machine with printing side facing left. It is placed correctly (printing, printing side).

Problem Cause: Whether the paper roll is correctly placed in the machine?

Please make sure that the label is placed in the machine with printing side facing left. It is placed correctly (printing, printing side).

Problem Cause: Whether the paper roll is correctly placed in the machine?

Please make sure that the label is placed in the machine with printing side facing left. It is placed correctly (printing, printing side).

Problem Cause: Whether the paper roll is correctly placed in the machine?

Please make sure that the label is placed in the machine with printing side facing left. It is placed correctly (printing, printing side).

Problem Cause: Whether the paper roll is correctly placed in the machine?

Please make sure that the label is placed in the machine with printing side facing left. It is placed correctly (printing, printing side).

Problem Cause: Whether the paper roll is correctly placed in the machine?

Please make sure that the label is placed in the machine with printing side facing left. It is placed correctly (printing, printing side).

Problem Cause: Whether the paper roll is correctly placed in the machine?

Please make sure that the label is placed in the machine with printing side facing left. It is placed correctly (printing, printing side).

Problem Cause: Whether the paper roll is correctly placed in the machine?

Please make sure that the label is placed in the machine with printing side facing left. It is placed correctly (printing, printing side).

Problem Cause: Whether the paper roll is correctly placed in the machine?

Please make sure that the label is placed in the machine with printing side facing left. It is placed correctly (printing, printing side).

Problem Cause: Whether the paper roll is correctly placed in the machine?

Please make sure that the label is placed in the machine with printing side facing left. It is placed correctly (printing, printing side).

Problem Cause: Whether the paper roll is correctly placed in the machine?

Please make sure that the label is placed in the machine with printing side facing left. It is placed correctly (printing, printing side).

Problem Cause: Whether the paper roll is correctly placed in the machine?

Please make sure that the label is placed in the machine with printing side facing left. It is placed correctly (printing, printing side).

Problem Cause: Whether the paper roll is correctly placed in the machine?

Please make sure that the label is placed in the machine with printing side facing left. It is placed correctly (printing, printing side).

Problem Cause: Whether the paper roll is correctly placed in the machine?

Please make sure that the label is placed in the machine with printing side facing left. It is placed correctly (printing, printing side).

Problem Cause: Whether the paper roll is correctly placed in the machine?

Please make sure that the label is placed in the machine with printing side facing left. It is placed correctly (printing, printing side).

Problem Cause: Whether the paper roll is correctly placed in the machine?

Please make sure that the label is placed in the machine with printing side facing left. It is placed correctly (printing, printing side).

Problem Cause: Whether the paper roll is correctly placed in the machine?

Please make sure that the label is placed in the machine with printing side facing left. It is placed correctly (printing, printing side).

Problem Cause: Whether the paper roll is correctly placed in the machine?

Please make sure that the label is placed in the machine with printing side facing left. It is placed correctly (printing, printing side).

Problem Cause: Whether the paper roll is correctly placed in the machine?

Please make sure that the label is placed in the machine with printing side facing left. It is placed correctly (printing, printing side).

Problem Cause: Whether the paper roll is correctly placed in the machine?

Please make sure that the label is placed in the machine with printing side facing left. It is placed correctly (printing, printing side).

Problem Cause: Whether the paper roll is correctly placed in the machine?

Please make sure that the label is placed in the machine with printing side facing left. It is placed correctly (printing, printing side).

Problem Cause: Whether the paper roll is correctly placed in the machine?

Please make sure that the label is placed in the machine with printing side facing left. It is placed correctly (printing, printing side).

Problem Cause: Whether the paper roll is correctly placed in the machine?

Please make sure that the label is placed in the machine with printing side facing left. It is placed correctly (printing, printing side).

Problem Cause: Whether the paper roll is correctly placed in the machine?

Please make sure that the label is placed in the machine with printing side facing left. It is placed correctly (printing, printing side).

12. Product Warranty

Thank you for choosing the Small Label Printer.

(1) We will provide customers with reliable "replacement/repair" support during the one-year warranty period from the date of purchase.

(2) Please keep the warranty card in a safe place so that you can read it when needed.

support@phorono.com

www.phorono.com

Please scan the QR code to get the printer operation guide.



This manual has been carefully checked. If there are printing errors or misstatements, please report them to the manufacturer.

Note: This supporting software is updated. It will be compiled into the new version of the manual when released.

13. FCC Caution

The device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions:

(1) The device may not cause harmful interference, and (2) the device must accept any interference received, including interference that may cause undesired operation.

Any changes or modifications not expressly approved by the party responsible for compliance may void the user's authority to operate the equipment.

Note: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential environment.

This equipment uses frequency hopping technology. If not installed and used in accordance with the instructions, there is a potential for interference with other electronic equipment.

Interference may occur in a particular installation. If the user experiences interference, they should stop using the equipment until the interference is resolved. The user should be advised to stop using the equipment until the interference is resolved.

Interference may occur in a particular installation. If the user experiences interference, they should stop using the equipment until the interference is resolved. The user should be advised to stop using the equipment until the interference is resolved.

Interference may occur in a particular installation. If the user experiences interference, they should stop using the equipment until the interference is resolved. The user should be advised to stop using the equipment until the interference is resolved.

Interference may occur in a particular installation. If the user experiences interference, they should stop using the equipment until the interference is resolved. The user should be advised to stop using the equipment until the interference is resolved.

Interference may occur in a particular installation. If the user experiences interference, they should stop using the equipment until the interference is resolved. The user should be advised to stop using the equipment until the interference is resolved.

Interference may occur in a particular installation. If the user experiences interference, they should stop using the equipment until the interference is resolved. The user should be advised to stop using the equipment until the interference is resolved.

Interference may occur in a particular installation. If the user experiences interference, they should stop using the equipment until the interference is resolved. The user should be advised to stop using the equipment until the interference is resolved.

Interference may occur in a particular installation. If the user experiences interference, they should stop using the equipment until the interference is resolved. The user should be advised to stop using the equipment until the interference is resolved.

Interference may occur in a particular installation. If the user experiences interference, they should stop using the equipment until the interference is resolved. The user should be advised to stop using the equipment until the interference is resolved.

Interference may occur in a particular installation. If the user experiences interference, they should stop using the equipment until the interference is resolved. The user should be advised to stop using the equipment until the interference is resolved.

Interference may occur in a particular installation. If the user experiences interference, they should stop using the equipment until the interference is resolved. The user should be advised to stop using the equipment until the interference is resolved.

Interference may occur in a particular installation. If the user experiences interference, they should stop using the equipment until the interference is resolved. The user should be advised to stop using the equipment until the interference is resolved.

Interference may occur in a particular installation. If the user experiences interference, they should stop using the equipment until the interference is resolved. The user should be advised to stop using the equipment until the interference is resolved.

13. Warranty/Maintenance Card

☐ Retailer☐ Distributor

User Information	Name	Gender	Phone
	Address		
Product Information	Date of purchase		
	Product serial number		
	Production serial number		
	Batch/Serial number		
Reason for Return	Reason for Return		
	Reason for Return		

Thank you for choosing our products!

Instruction
M220 Product
Instruction

Please read this instruction book carefully before operating the product.

[Phomemo M220 Label Maker User Manual](#)

Comprehensive guide for the Phomemo M220 label maker, covering packing list, product specifications, appearance introduction, component description, paper roll installation, app download and connection, label size confirmation, printing guide, troubleshooting, and warranty information.