

YYJLX Y-1006

YYJLX Y-1006 5-Light Round Crystal Semi-Flush Mount Ceiling Light Instruction Manual

Model: Y-1006

1. SAFETY INFORMATION

Please read these instructions carefully before installation and retain them for future reference. All electrical connections must be in accordance with local codes and ordinances. If you are unsure about wiring, consult a qualified electrician.

- **WARNING:** To avoid the risk of electrical shock, always turn off the main power supply at the circuit breaker or fuse box before beginning installation.
- Ensure the fixture is securely mounted to a structurally sound part of the ceiling.
- Do not exceed the recommended wattage for bulbs.
- Handle crystal components with care to prevent breakage.

2. PACKAGE CONTENTS

Verify that all parts are present before beginning assembly.

- Mounting Hardware
- Fixture Frame (Metal)
- Crystal Components (Various shapes and sizes)
- Light Sockets (5x E12 base)
- Instruction Manual

Note: E12 bulbs are not included and must be purchased separately.

3. TOOLS REQUIRED

- Phillips Head Screwdriver
- Wire Strippers
- Pliers
- Adjustable Wrench
- Electrical Tape
- Safety Glasses

4. SETUP AND INSTALLATION

Follow these steps carefully for proper assembly and installation. It is recommended to have a second person assist with installation due to the size and weight of the fixture.

1. **Prepare the Mounting Plate:** Attach the mounting bracket to your ceiling junction box using the provided screws. Ensure it is securely fastened.
2. **Assemble the Fixture Frame:** Connect the curved metal arms to the central light socket assembly and the outer ring. Use the provided screws and washers, tightening them with a screwdriver and wrench.
3. **Wire the Fixture:** Carefully pull the electrical wires from the ceiling junction box through the center of the mounting plate. Connect the fixture's wires to the house wires according to standard electrical codes (usually black to black, white to white, and ground to ground). Secure connections with wire nuts and electrical tape.
4. **Mount the Fixture:** Carefully lift the assembled fixture and align the mounting screws on the mounting plate with the holes in the fixture's canopy. Secure the fixture in place with the decorative nuts.
5. **Attach Crystal Components:** This step requires patience. Attach the crystal strings and prisms to the designated hooks on the fixture frame. Refer to the diagram in the included manual for the correct placement of each crystal type.
6. **Install Bulbs:** Screw five E12 base bulbs (not included, max 40W each) into the sockets.

Installation Video Guide

Your browser does not support the video tag.

This video demonstrates the assembly and installation process for the YYJLX 5-Light Crystal Chandelier. It covers connecting the frame components, wiring, and attaching the crystal elements.

Product Details and Dimensions



Image showing the overall dimensions of the YYJLX Y-1006 ceiling light fixture, with a width of 19.68 inches and a height of 18.50 inches.



Detailed analysis of the product components, highlighting the E12 light source, iron drawing top plate, and luxury crystal pendants.

5. OPERATING INSTRUCTIONS

Once installed, the YYJLX Y-1006 ceiling light can be operated via a standard wall switch. This fixture is designed to be dimmable, allowing you to adjust the light intensity with a compatible dimmer switch (not included).

Light Display Video

Your browser does not support the video tag.

This video showcases the YYJLX 5-Light Crystal Chandelier in operation, demonstrating its illumination and aesthetic appeal.

On/Off Comparison



Image illustrating the appearance of the light fixture when turned on and off, highlighting the crystal's sparkle when illuminated.

6. MAINTENANCE

Regular cleaning will help maintain the beauty and brilliance of your crystal ceiling light.

- **Cleaning the Crystals:** Gently wipe the crystal components with a soft, lint-free cloth dampened with water or a mild glass cleaner. Avoid harsh chemicals that may damage the crystal finish.
- **Cleaning the Metal Frame:** Use a soft, dry cloth to dust the metal frame. For stubborn spots, a slightly damp cloth can be used, followed by immediate drying.
- **Bulb Replacement:** Ensure the power is off before replacing any bulbs. Allow bulbs to cool completely before handling. Use only E12 base bulbs with a maximum wattage of 40W.

7. TROUBLESHOOTING

If you encounter any issues with your light fixture, refer to the following common problems and solutions:

Problem	Possible Cause	Solution
Light does not turn on	No power to the fixture, loose wiring, faulty bulb, faulty switch.	Check circuit breaker. Ensure all wire connections are secure. Replace bulb. Test switch.
Light flickers	Loose bulb, incompatible dimmer switch, loose wiring.	Tighten bulb. Ensure dimmer is compatible with LED bulbs (if using LED). Check wiring connections.
Crystals appear dull	Dust or residue buildup.	Clean crystals as per maintenance instructions.

If the problem persists after attempting these solutions, please contact customer support or a qualified electrician.

8. SPECIFICATIONS

- **Brand:** YYJLX
- **Model Number:** Y-1006
- **Color:** Black
- **Material:** Metal, Crystal
- **Product Dimensions:** 19.68"L x 19.68"W x 18.5"H
- **Number of Light Sources:** 5
- **Bulb Base:** E12
- **Voltage:** 110 Volts
- **Maximum Compatible Wattage:** 40 Watts per bulb
- **Installation Type:** Semi Flush Mount
- **Special Feature:** Dimmable
- **Item Weight:** 8.8 Pounds
- **Recommended Use:** Indoor use only

9. WARRANTY AND SUPPORT

Your YYJLX Y-1006 5-Light Round Crystal Semi-Flush Mount Ceiling Light comes with a **90-day money-back guarantee** and a **2-year replacement warranty**.

If you have any questions, concerns, or require assistance with your product, please refer to your purchase documentation for customer support contact information.

