

Manuals.plus /

> Inandon /

> Inandon KV-V5 Pro Karaoke Machine Instruction Manual

Inandon KV-V5 Pro

Inandon KV-V5 Pro Karaoke Machine Instruction Manual

Model: KV-V5 Pro

1. INTRODUCTION

Thank you for purchasing the Inandon KV-V5 Pro Karaoke Machine. This professional karaoke system is designed to provide an immersive entertainment experience with its 22-inch capacitive touch screen, wireless microphones, and extensive song library. Please read this manual carefully to ensure proper setup, operation, and maintenance of your device.



Image: The Inandon KV-V5 Pro Karaoke Machine, featuring a large touch screen display and two wireless microphones, set up for use.

2. PACKAGE CONTENTS

Ensure all components are present in the package:

- KV-V5 Pro Karaoke Machine (main unit)
- 22-inch Capacitive Touch Screen
- Wireless Microphones (2 units)
- Power Adapters (for main unit and touch screen)
- RCA Audio Cables
- VGA Cable
- Network Cable
- Optical Cable
- HDMI Cable
- User Manual (this document)

3. SETUP GUIDE

3.1. Connecting the Touch Screen

The touch screen is essential for navigating the karaoke system. Follow these steps to connect it:

1. Connect the touch screen VGA cable to the VGA output port on the karaoke machine's main unit.
2. Connect the touch screen network cable to the TOUCH SCREEN interface on the karaoke machine.
3. Connect the touch screen power adapter to the touch screen's power input.

3.2. Connecting Audio

The karaoke machine requires connection to an amplifier and speakers for sound output. There are multiple ways to connect audio:

3.2.1. RCA Cable Wiring (for Amplifier)

1. Connect the RCA red and white cables from the AUDIO OUT of the karaoke machine to the AUX IN of the microphone host.
2. Connect the RCA red and white cables from the AUDIO OUTPUT of the microphone host to the audio input of your amplifier.
3. Ensure your amplifier's input source is set to the corresponding AUX input.

3.2.2. Optical Cable Wiring (for Sound Bar/Receiver)

1. Connect the optical cable output of the microphone host to the optical input of your sound bar or receiver.
2. Switch your sound bar or receiver to the corresponding optical input source.

3.2.3. HDMI Output

The karaoke machine features an HDMI output for video and audio. Connect an HDMI cable from the HDMI OUT port on the karaoke machine to your TV or display. Ensure your TV's input source is set to the corresponding HDMI input.

3.3. Power Connections

1. Connect the power adapter of the karaoke machine to the DC12V port on the main unit.

2. Connect the microphone power adapter to the 12V port of the microphone host.
3. Plug both power adapters into a suitable power outlet.

3.4. Network Connection

The system supports Wi-Fi for cloud song downloads and online features.

- The device has a built-in Wi-Fi receiver. Access network settings via the touch screen to connect to your local Wi-Fi network.
- Alternatively, connect an Ethernet cable to the LAN port for a wired network connection.

Your browser does not support the video tag.

Video: Detailed guide on wiring the InAndOn Karaoke Machine, including connections for the touch screen, audio output to an amplifier, and power.

Delete songs intelligently to maintain hard drive capacity

Intelligently delete long-term unclicked songs according to the upper limit of hard disk storage



Image: The rear panel of the karaoke machine, highlighting ports for LAN, USB, HDMI, VGA, Audio Out, Coaxial, Optical, and DC 12V power input.

4. OPERATING INSTRUCTIONS

4.1. Powering On/Off

Locate the power button on the main unit to turn the system on or off. The touch screen will power on automatically once connected and the main unit is on.

4.2. Touch Screen Interface

The 22-inch capacitive touch screen provides access to all system functions. The system runs on a dual Android and KTV system, offering versatility.



Image: The 22-inch touch screen interface of the karaoke machine, showing various song categories and selection options.

4.3. Song Selection

- **Cloud Download:** Access a library of over 44,000 songs for free via cloud download. The song cloud updates every two weeks.
- **USB/U Disk:** Load songs into the system via a U disk using the available USB ports.
- **Built-in Songs:** The system includes built-in Chinese, English, Cantonese, Japanese, and Korean songs.

KTV intelligent scoring system

atmosphere bullet-screen comments experience

Better grasp the singing effect, let you follow the rhythm to practice the song K song is over, enjoy your singing high score



Image: The touch screen displaying an 80% online download progress for songs, with wireless microphones and the main unit visible.

4.4. Microphone Usage

The system comes with wireless microphones. Ensure they are powered on and paired with the microphone host.

- Adjust microphone volume, treble, bass, echo, and reverb using the controls on the microphone host or the touch screen interface.
- The system supports KTV intelligent scoring for an interactive singing experience.

Mobile WeChat Wireless Ordering

Support mobile phone APP and WeChat remote song ordering, song ordering is more portable, you can remotely connect and click the song you want while lying on the sofa comfortably, support smart phones, tablets and other terminals to enjoy smart portable entertainment life



Image: A family enjoying karaoke with the Inandon KV-V5 Pro, showing the KTV intelligent scoring system displayed on a large television screen.

4.5. Additional Features

- **Mobile Wireless Ordering:** Support mobile phone APP and WeChat remote song ordering. Connect smartphones, tablets, and other terminals for portable entertainment.
- **Real-time Sharing:** Share recordings directly from the system.
- **Song Up and Down Tuning:** Adjust the key of songs to match your vocal range.

More powerful functions waiting for you to discover

It can meet the needs of different people and give you a better entertainment experience



Mobile phone pick up songs



Real-time sharing of recordings



Eight-core processor



Song Up and Down Tuning

Image: The Inandon KV-V5 Pro Karaoke Machine with a mobile phone displaying a song ordering app, demonstrating wireless control capabilities.

Multi-purpose enriching family enriching family entertainment

Family karaoke/accompany parents/friends party



Caring for parents



friends gathering



Parent-child companionship



Family entertainment

Image: A collage of screenshots from the Inandon KV-V5 Pro's interface, illustrating features such as mobile phone song selection via QR code, real-time recording sharing, eight-core processor details, and song tuning options.

5. MAINTENANCE

- **Cleaning:** Use a soft, dry cloth to clean the touch screen and exterior surfaces. Avoid abrasive cleaners

or solvents.

- **Hard Drive Management:** The system can intelligently delete long-term unclicked songs to maintain hard drive capacity. Regularly check storage and manage songs as needed.
- **Software Updates:** Ensure your system's software is up-to-date for optimal performance and access to the latest features and song updates.

6. TROUBLESHOOTING

Problem	Possible Cause	Solution
No sound from speakers	Incorrect audio connections, amplifier input not selected, microphone volume too low.	Verify all audio cables are securely connected. Ensure amplifier/sound bar input is correctly selected. Increase microphone volume on the host or touch screen.
Microphone not working	Microphone not powered on, not paired, or low battery.	Ensure microphones are powered on. Check battery levels and replace if necessary. Refer to microphone pairing instructions if needed.
Touch screen unresponsive	Loose cable connection, software issue.	Check the touch screen VGA and network cables. Restart the karaoke machine.
Cannot download songs	No internet connection, server issues.	Verify Wi-Fi or Ethernet connection. Check network settings. Try again later if it's a server-side issue.
System is slow/unresponsive	Too many background apps, low storage.	Close unnecessary applications. Manage hard drive space by deleting old songs. Restart the system.

7. SPECIFICATIONS

- **Brand:** Inandon
- **Model Name:** KV-V5 Pro
- **Touch Screen:** 22-inch Capacitive
- **Processor:** High Speed Main Processor Eight-Core
- **Memory:** Up to 8GB
- **Operating System:** Dual system (Android and KTV)
- **Connectivity:** Wi-Fi, Ethernet, HDMI, USB (2 ports), RCA, Optical, VGA
- **Included Components:** Microphone (2 wireless units)
- **Power Source:** Battery Powered (for microphones), DC 12V (main unit)
- **Item Weight:** 37.5 Pounds
- **Color:** Black, Gold

8. WARRANTY AND SUPPORT

For technical support, warranty claims, or any inquiries regarding your Inandon KV-V5 Pro Karaoke Machine, please contact your seller or the manufacturer directly. You may also reach out via WeChat or LINE using the ID: inandonusa.

Please retain your proof of purchase for warranty purposes.

