MELONFARM 002

MELONFARM 19 Inch Bud Leaf Bowl Trimmer Instruction Manual

Model: 002

1. Product Overview

The MELONFARM 19 Inch Bud Leaf Bowl Trimmer is designed for efficient and precise trimming of hydroponic plants, buds, and leaves. It features sharp stainless steel blades and a manual twisted spin cut mechanism, making it suitable for both home gardening and professional use. This trimmer is also ideal for preparing plants for aromatherapy, potpourri, and essential oils.

- **Efficient Cutting:** High-quality sharp blades and metal wheels ensure a smooth and fast trimming experience. The stainless steel bottom bowl collects trimmed leaves, simplifying cleanup.
- **Flexible Blade Replacement:** Includes a four-edged straight blade for wet trimming and a serrated blade for dry trimming, allowing for easy adaptation to various plant types and conditions.
- **Safe and Precise Trimming:** Equipped with 30 food-grade rubber strips to gently sweep plants, reduce adhesion, and prevent damage. The design prioritizes user safety during operation.
- **Easy to Operate:** Features a smooth-rotating handle and a transparent plastic cover for real-time monitoring of the trimming process. Non-slip pads ensure stability during use.
- **Versatile Use:** Suitable for trimming excess leaves and branches from buds, leaves, flowers, and hydroponic plants. The set includes a 4-layer drying net for post-trimming plant handling.

2. Components Overview

Familiarize yourself with the main components of your MELONFARM 19 Inch Bud Leaf Bowl Trimmer:



Figure 1: Well-Designed Components of the Trimmer

- **Rubber Handle:** Provides a comfortable grip and smooth rotation for manual operation.
- **Clear PC Cover:** Allows for easy observation of the trimming process and contains clippings.
- **Silicone Seal:** Ensures a tight seal between the cover and the bowl.
- **Stainless Steel Bowl:** Durable and easy to clean, collects trimmed leaves.
- **Rubber Pad:** Non-slip base for enhanced stability during use.
- **Blades:** Interchangeable straight and serrated stainless steel blades for different trimming needs.
- **Grille:** Stainless steel wire grille supports the plant material during trimming.

3. Setup and Assembly

Follow these steps to assemble your MELONFARM Bud Leaf Bowl Trimmer:

1. Place the non-slip rubber pad on a stable, flat surface.
2. Position the stainless steel bowl onto the rubber pad.
3. Carefully place the mesh filter disc (grille with central shaft) into the bowl. Ensure it sits securely.
4. Attach the desired blade (straight for wet trimming, serrated for dry trimming) to the central shaft of the mesh

filter disc. Secure it firmly with the provided fasteners.

5. Place the clear PC cover onto the bowl, ensuring the silicone seal creates a snug fit.
6. Insert the rubber handle into the designated opening on top of the clear PC cover. It should fit without needing to be screwed in, allowing for free rotation.

Video 1: Visual guide on assembling and operating the Bud Leaf Bowl Trimmer.

Safety Warning: The blades are extremely sharp. Always wear protective gloves when handling or replacing blades to prevent injury.

4. Operating Instructions

Operating your trimmer is straightforward:

1. Ensure the trimmer is fully assembled with the appropriate blade for your material (straight for wet, serrated for dry).
2. Gently place your plant material onto the mesh filter disc. Do not overfill the bowl to ensure optimal trimming performance.
3. Secure the clear PC cover and insert the handle.
4. Begin turning the handle clockwise for 15-30 rounds. The rubber strips will gently move the plant material, allowing the blades below to trim excess leaves. The transparent cover allows you to observe the progress.
5. Once trimming is complete, remove the handle and lift the clear PC cover. Carefully remove the mesh filter disc with the trimmed plant material.
6. The trimmed leaves will be collected in the stainless steel bowl below.



Figure 2: Trimmer in operation, demonstrating the manual spin action.



Figure 3: Blade types for different trimming applications.

5. Maintenance and Cleaning

Regular cleaning and maintenance will ensure the longevity and optimal performance of your trimmer:

- **Disassembly:** Carefully disassemble the trimmer by removing the handle, clear PC cover, and mesh filter disc from the stainless steel bowl.
- **Blade Cleaning:** The stainless steel blades can accumulate plant residue. Use rubbing alcohol and a soft cloth or paper towel to clean the blades. Exercise extreme caution as blades are very sharp.
- **Bowl and Cover Cleaning:** Wash the stainless steel bowl and clear PC cover with warm, soapy water. Rinse thoroughly and dry completely before reassembly or storage.
- **Rubber Strips:** Clean the food-grade rubber strips with warm, soapy water to remove any plant material.
- **Storage:** Store all components in a clean, dry place when not in use.
- **Blade Replacement:** If blades become dull or damaged, replace them with genuine MELONFARM replacement blades to maintain cutting efficiency.

6. Troubleshooting

Here are some common issues and their solutions:

- **Inefficient Trimming:**
  - Ensure the correct blade type is installed for your material (wet vs. dry).
  - Check if the blades are sharp. Replace if dull.
  - Avoid overfilling the bowl; trim smaller batches if necessary.
  - Ensure the handle is rotating smoothly and consistently.
- **Stiff Handle Rotation:**
  - Disassemble and clean all moving parts, especially the central shaft and handle mechanism, to remove any sticky residue.
  - Ensure the handle is correctly inserted and not misaligned.
- **Plant Material Damage:**
  - Reduce the number of rotations or the speed of rotation.
  - Ensure the rubber strips are clean and functioning correctly to gently guide the material.

7. Specifications

Key specifications for the MELONFARM 19 Inch Bud Leaf Bowl Trimmer:



Figure 4: Product Specifications

Attribute	Value
Model	002
Diameter	19 inches
Item Weight	16.92 pounds
Package Dimensions	19.6 x 19.5 x 11.6 inches
Function	Manual Twisted Spin Cut
Material	Stainless Steel, PC Plastic, Rubber

8. Warranty and Support

For warranty information, technical support, or to purchase replacement parts, please contact MELONFARM

customer service. Keep your purchase receipt as proof of purchase.

For further assistance, please visit the MELONFARM Store on Amazon.

© 2026 MELONFARM. All rights reserved.

Ask a question about this manual

Ask about setup, troubleshooting, compatibility, parts, safety, or missing instructions. Manuals+ will review the question and use this page's manual context to help answer it.

Name

Anonymous

Email

you@example.com

After a successful submission, we securely hash the supplied account or form email before sending it to Microsoft Advertising for conversion attribution. Privacy details.

Question

Example: How do I reset this device or fix this error?

Details

Model number, symptoms, what you tried, or the section of the manual you are using.

Submit question