

## Manuals+

[Q & A](#) | [Deep Search](#) | [Upload](#)

[manuals.plus](#) /

› [LEMEGA](#) /

› [LEMEGA M2P Internet Radio Player User Manual](#)

## LEMEGA M2P

# LEMEGA M2P Internet Radio Player User Manual

Model: M2P

## INTRODUCTION

Thank you for choosing the LEMEGA M2P Internet Radio Player. This device offers a versatile audio experience, combining Internet Radio, FM Radio, and Bluetooth connectivity. It features dual alarms, a clock, and can be powered by mains electricity or its built-in rechargeable battery for portable use. This manual provides essential information for setting up, operating, and maintaining your M2P radio.

## SAFETY INFORMATION

- Read all instructions carefully before use and retain for future reference.
- Do not expose the unit to rain, moisture, or extreme temperatures.
- Ensure proper ventilation; do not block any ventilation openings.
- Use only the provided power adapter.
- Avoid placing the unit near heat sources or in direct sunlight.
- Do not attempt to disassemble or modify the unit. Refer all servicing to qualified personnel.
- Dispose of batteries responsibly according to local regulations.

## PACKAGE CONTENTS

Please check the box for the following items:

- LEMEGA M2P Internet Radio Player
- Power Adapter
- Owner's Manual (this document)

## PRODUCT OVERVIEW

Familiarize yourself with the components and controls of your LEMEGA M2P radio.



**Figure 1:** Front view of the LEMEGA M2P Internet Radio Player, showing the speaker grille on the left, the color display on the right, and an array of control buttons and a central rotary knob below the display. A brown leather-like handle is visible at the top.

## Controls and Display

- **Color Display:** Shows station information, menus, time, and settings.
- **Rotary Knob (O/VOLUME):** Rotate to navigate menus or adjust volume. Press to select an option.
- **Preset Buttons (1, 2, 3+):** Quickly access saved radio stations.
- **Navigation Buttons (I<<, I>>, II<<, II>>):** For skipping tracks or navigating lists.
- **ALARM Button:** Set and manage alarms.
- **SLEEP Button:** Set a sleep timer.
- **INFO Button:** Display additional information about the current station or track.
- **MENU Button:** Access the main menu.
- **BACK Button:** Return to the previous screen.
- **SOURCE Button:** Switch between Internet Radio, FM, and Bluetooth modes.



**Figure 2:** Rear view of the LEMEGA M2P Internet Radio Player with dimensions indicated. The radio measures approximately 9.5 inches in length, 3.5 inches in width, and 6 inches in height.

## Rear Panel Connections

- **DC IN:** Connect the provided power adapter.
- **AUX IN:** Connect external audio devices using a 3.5mm audio cable.
- **Headphone Jack:** Connect headphones for private listening.

## SETUP

### 1. Powering the Device

The LEMEGA M2P can be powered by the included AC adapter or its internal rechargeable battery.

- **Mains Power:** Connect the power adapter to the DC IN port on the back of the radio, then plug it into a wall outlet.
- **Battery Power:** The radio has a built-in 2,200mAh lithium battery, providing up to 10 hours of playback on a single charge. The battery charges automatically when connected to mains power.

## 2. Initial Setup Wizard

Upon first power-on, the radio will guide you through an initial setup wizard.



**Figure 3:** The LEMEGA M2P radio positioned on a kitchen counter, showing its color display with various menu options, indicating it is ready for initial setup or operation.

- 1. Language Selection:** Use the rotary knob to select your preferred language and press to confirm.
- 2. Time and Date:** The radio can automatically set the time and date via FM stations or network connection. You can also set it manually.
- 3. Network Configuration (Wi-Fi):**
  - Select 'Network Wizard' from the menu.
  - The radio will scan for available Wi-Fi networks.
  - Select your network from the list.
  - Enter your Wi-Fi password using the rotary knob to select characters and press to confirm each character.
  - Once connected, the radio will display a confirmation message.

## OPERATING MODES

## 1. Internet Radio

Access thousands of radio stations and podcasts from around the world via your Wi-Fi connection.



### Smart Radio Wifi

Stream and enjoy over 30,000 radios and Podcasts from local or worldwide by wifi streaming.

**Figure 4:** The LEMEGA M2P radio placed on a coffee table in a living room setting, demonstrating its use for streaming content via Wi-Fi.

1. Press the **SOURCE** button until 'Internet Radio' is selected.
2. Use the rotary knob to browse categories (e.g., Location, Genre, Podcasts).
3. Select a station or podcast and press the rotary knob to start playback.
4. **Saving Presets:** To save a station, press and hold one of the preset buttons (1, 2, or 3+). To recall, short press the corresponding button. The M2P supports up to 20 station presets.

## 2. FM Radio

Enjoy local FM broadcasts with clear sound quality.

1. Press the **SOURCE** button until 'FM Radio' is selected.
2. **Auto-Scan:** Press and hold the rotary knob to initiate an auto-scan for available FM stations. The radio will save found stations.
3. **Manual Tuning:** Rotate the rotary knob to manually tune to a frequency.
4. **Saving Presets:** Similar to Internet Radio, press and hold a preset button to save, and short press to

recall.

### 3. Bluetooth Speaker

Stream music wirelessly from your smartphone, tablet, or other Bluetooth-enabled devices.



**Figure 5:** The LEMEGA M2P radio's display showing a Bluetooth connection icon, while a hand holds a smartphone playing music, illustrating the wireless audio streaming capability.

1. Press the **SOURCE** button until 'Bluetooth' is selected. The radio will enter pairing mode, indicated on the display.
2. On your Bluetooth device, search for 'LEMEGA M2P' in the Bluetooth settings.
3. Select 'LEMEGA M2P' to pair. Once connected, the radio will confirm the connection.
4. Start playing audio on your connected device. The radio will act as a wireless speaker.

### 4. Auxiliary Input (AUX IN)

Connect external audio sources like MP3 players or CD players.

1. Connect a 3.5mm audio cable from your external device's headphone or line-out jack to the **AUX IN** port on the back of the M2P.
2. Press the **SOURCE** button until 'AUX In' is selected.
3. Control playback from your external device. The M2P's volume control will still function.

## 5. Alarms and Timers

The M2P features dual independent alarms, a sleep timer, and a snooze function.

- **Setting Alarms:** Press the **ALARM** button to access alarm settings. Follow the on-screen prompts to set alarm time, source (buzzer or radio), frequency (daily, weekdays, weekends), and volume.
- **Sleep Timer:** Press the **SLEEP** button repeatedly to cycle through available sleep timer durations (e.g., 15, 30, 60 minutes, Off). The radio will automatically turn off after the selected time.
- **Snooze:** When an alarm sounds, press the rotary knob to activate the snooze function, pausing the alarm for a short period.

## MAINTENANCE

- **Cleaning:** Wipe the radio with a soft, dry cloth. Do not use abrasive cleaners or solvents.
- **Battery Care:** For optimal battery life, avoid fully discharging the battery frequently. If storing the unit for an extended period, charge it to approximately 50% and recharge every few months.
- **Storage:** Store the unit in a cool, dry place away from direct sunlight and extreme temperatures.

## TROUBLESHOOTING

Problem	Possible Cause	Solution
No power	Power adapter not connected or faulty; battery depleted.	Ensure power adapter is securely connected and plugged into a working outlet. Charge the battery.
Cannot connect to Wi-Fi	Incorrect password; network out of range; router issue.	Double-check Wi-Fi password. Move radio closer to router. Restart your Wi-Fi router.
No sound	Volume too low; muted; incorrect source selected.	Increase volume. Check if the unit is muted. Ensure the correct audio source (Internet Radio, FM, Bluetooth, AUX) is selected.
Cannot save more than 2 presets	Incorrect method for saving presets beyond the first two.	For presets 1 and 2, a short press saves. For presets 3 and higher (accessed via '3+' button), a <b>long press</b> is required to save a station. A short press recalls.
Bluetooth connection unstable	Interference; device too far; pairing issue.	Ensure no obstructions between devices. Keep devices within 10 meters. Try unpairing and re-pairing the device.

## SPECIFICATIONS

Feature	Detail
Brand	LEMEGA

Feature	Detail
Model Number	M2P
Product Dimensions	9.5" L x 3.5" W x 6" H (24.13 x 8.89 x 15.24 cm)
Item Weight	3.99 pounds (1.81 Kilograms)
Connectivity Technology	Bluetooth, Wi-Fi
Tuner Technology	FM, Bluetooth, WiFi
Radio Bands Supported	FM
Power Source	Battery Powered and Mains Power
Special Features	Built-In Clock, Portable, Rechargeable, Dual Alarms, Sleep Timer
Display	Color TFT Display
Battery Capacity	2,200mAh (up to 10 hours playback)

## WARRANTY AND SUPPORT

LEMEGA products are designed for reliability and performance. For specific warranty details, please refer to the warranty card included with your purchase or visit the official LEMEGA website. Keep your proof of purchase for warranty claims.

For further assistance, troubleshooting, or product inquiries, please contact LEMEGA customer support. You may also find additional resources and FAQs on the LEMEGA brand store page:

[Visit the LEMEGA Store on Amazon](#)

A PDF version of the user manual is also available for download:

[Download User Manual \(PDF\)](#)

© 2024 LEMEGA. All rights reserved.

## Related Documents - M2P

	<p><a href="#">LEMEGA IR4S Internet Radio: Guide to Storing and Recalling Presets</a></p> <p>A user-friendly guide for the LEMEGA IR4S Internet Radio, detailing how to store and recall radio station presets for both quick access (1-2) and extended lists (3-20).</p>
	<p><a href="#">LEMEGA M5P Music System User Manual - CD, DAB, Internet Radio, Bluetooth</a></p> <p>Comprehensive user manual for the LEMEGA M5P Music System. Learn how to set up, operate, and troubleshoot your CD player, DAB radio, internet radio, Bluetooth streamer, and more. Includes safety instructions, control descriptions, connectivity options, and technical specifications.</p>

	<p><b>LEMEGA M3P Smart Radio with Bluetooth User Manual</b></p> <p>This user manual provides comprehensive instructions for the LEMEGA M3P Smart Radio with Bluetooth, covering setup, features, operation of various modes (Internet Radio, DAB, FM, Bluetooth, Spotify Connect), alarms, sleep functions, software updates, troubleshooting, and technical specifications.</p>
	<p><b>LEMEGA M5+ Smart Audio System User Manual</b></p> <p>Comprehensive user manual for the LEMEGA M5+ Smart Audio System, covering setup, features, operation of Internet radio, DAB, FM, Spotify Connect, Bluetooth, CD playback, alarms, troubleshooting, and technical specifications.</p>
	<p><b>LEMEGA M3P Internet Radio: Storing and Recalling Presets</b></p> <p>Instructions on how to store and recall radio station presets on the LEMEGA M3P Internet Radio. Includes contact information for support.</p>
	<p><b>LEMEGA MSY6 All-in-One Music System Owner's Manual</b></p> <p>Comprehensive owner's manual for the LEMEGA MSY6 All-in-One Music System, covering safety instructions, features, operation, troubleshooting, and technical specifications.</p>