

## Manuals+

[Q & A](#) | [Deep Search](#) | [Upload](#)

[manuals.plus](#) /

› [INVIROX](#) /

› [INVIROX 2024 Dog Training Collar User Manual - Model 2024](#)

## INVIROX 2024 Dog Training Collar

# INVIROX 2024 Dog Training Collar User Manual

Model: 2024 Dog Training Collar

## 1. INTRODUCTION AND OVERVIEW

The INVIROX 2024 Dog Training Collar is an electronic training system designed to assist in effective dog training. It features a remote control and a waterproof receiver collar, offering multiple training modes including beep, vibration, and static stimulation. This manual provides detailed instructions for safe and proper use, setup, operation, and maintenance of your training collar.

### Key Features:

- **Training Modes:** Beep (1-8 levels), Vibration (1-16 levels), Static Stimulation (1-99 levels).
- **Range:** Up to 1100 yards (approximately 1000 meters).
- **Waterproof:** IP67 rated receiver for use in various weather conditions.
- **Safety:** Keypad lock feature on the remote to prevent accidental activation.
- **Battery:** Rechargeable remote and receiver with long-lasting battery performance.
- **Adjustable:** Suitable for dogs weighing 8 to 110 pounds.

## 2. PACKAGE CONTENTS

Please inspect the package contents to ensure all items are present and in good condition:

- Remote Control
- Receiver Collar
- Adjustable Nylon Strap
- Protective Rubber Contact Point Covers
- Metal Contact Points (short and long sets)
- Test Bulb
- 2-in-1 Micro USB Charging Cable
- Wrist Strap for Remote

# PACKAGE INCLUDES



## Please Read The User Manual

Figure 2.1: Included Components

This image displays the complete set of items you should find in your INVIROX Dog Training Collar package, including the remote, receiver, collar strap, various contact points, charging cable, and accessories.

## 3. SAFETY INFORMATION AND IMPORTANT WARNINGS

Read all instructions before using this product. Failure to follow these instructions could result in harm to your dog or damage to the product.

- **Not for Aggressive Dogs:** Do not use this product on aggressive dogs. If your dog is aggressive, consult a professional dog trainer or veterinarian.
- **Skin Irritation:** Prolonged wear or improper fit can cause skin irritation or pressure necrosis (commonly known as 'collar sores').
  - Avoid leaving the collar on the dog for more than 12 hours per day.
  - Reposition the collar on the dog's neck every 1 to 2 hours.
  - Check the contact area daily for signs of rash or sores. If a rash or sore is found, discontinue

use of the collar until the skin has healed.

- Always use the appropriate length of contact points for your dog's coat type to ensure proper contact without excessive pressure.
- Children:** Keep the training collar and remote control out of reach of children.
- Proper Fit:** The collar should fit snugly, but loose enough to allow one finger to fit between the strap and your dog's neck.
- Static Stimulation:** Static stimulation should be used as a last resort and at the lowest effective level. Always start with beep or vibration modes.
- Training Tool:** This device is a training tool, not a punishment device. Use it responsibly and in conjunction with positive reinforcement training methods.



Figure 3.1: Keypad Lock for Safety

This image illustrates the importance of the keypad lock feature on the remote control, designed to prevent accidental activation of training modes, ensuring safer operation, especially around children.

## 4. SETUP

### 4.1 Charging the Devices

Before first use, fully charge both the remote control and the receiver collar.

1. Connect the 2-in-1 Micro USB charging cable to a standard USB power adapter (not included) or a computer USB port.
2. Plug the two micro USB ends into the charging ports on the remote control and the receiver collar.
3. The indicator lights on both devices will show charging status (e.g., red for charging, green for fully charged).
4. Charging typically takes 2-3 hours. Once fully charged, disconnect the cable.

**Battery Life:** The remote control can last up to 45 days on standby, and the receiver collar up to 15 days per charge, depending on usage.



Figure 4.1: Charging and Battery Life

This diagram shows the remote and receiver, highlighting their respective battery durations and the shared micro USB charging cable.

## 4.2 Fitting the Receiver Collar

Proper fit of the receiver collar is crucial for effective and safe operation.

1. Ensure the dog is standing comfortably.
2. Place the receiver collar around your dog's neck, positioning the receiver unit centrally under the chin or on the side of the neck.
3. The contact points must make direct contact with your dog's skin. For dogs with thick coats, you may need to trim some fur or use the longer contact points provided.
4. Adjust the strap so it is snug, but not too tight. You should be able to fit one finger between the collar strap and your dog's neck.
5. The collar is designed for dogs weighing between 8 and 110 pounds.



Figure 4.2: Adjustable Collar for All Dog Sizes

This image demonstrates the versatility of the INVIROX training collar, showing it comfortably fitted on dogs of various sizes, from small to large, emphasizing its adjustability for weights between 8 and 110 pounds.

### 4.3 Pairing the Remote and Receiver

The remote and receiver are typically pre-paired from the factory. If re-pairing is needed or you are adding a second receiver:

1. Ensure both devices are fully charged and turned off.
2. Turn on the remote control.
3. Press and hold the power button on the receiver collar until the indicator light flashes rapidly.

4. Within 10 seconds, press any training mode button (Beep, Vibration, or Static Stimulation) on the remote control.
5. The receiver's indicator light will stop flashing and remain solid, indicating successful pairing.

## 5. OPERATING INSTRUCTIONS

---

### 5.1 Turning On/Off

- **Remote:** Press and hold the power button until the screen illuminates. To turn off, press and hold the power button until the screen turns off.
- **Receiver:** Press and hold the power button until the indicator light flashes. To turn off, press and hold the power button until the indicator light turns off.

### 5.2 Training Modes and Levels

The remote offers three distinct training modes:

- **Beep Mode:** Provides an audible tone. Levels 1-8.
- **Vibration Mode:** Delivers a tactile vibration. Levels 1-16.
- **Static Stimulation Mode:** Provides a static pulse. Levels 1-99.

To select a mode, press the corresponding button on the remote. Use the '+' and '-' buttons to adjust the intensity level within each mode. Always start with the lowest effective level and increase gradually if necessary.

# MADE BY VETERANS

## 123 LEVELS OF CONTROL



Figure 5.1: Training Modes and Levels

This image illustrates the three primary training modes available on the INVIROX remote control, along with their respective adjustable intensity levels, providing a visual guide for selecting the appropriate correction.

### 5.3 Keypad Lock

To prevent accidental activation of training modes, slide the keypad lock switch on the side of the remote control to the locked position. This will disable the training buttons until unlocked.

### 5.4 Double Functions: Light and Dog Switching

The remote control features buttons with dual functions:

- **Light Button:** Serves as a light button for visibility in low-light conditions and also allows for switching between training modes safely.
- **Dog Switching Button (1/2):** Functions as an On/Off button for the receiver and allows switching between two paired dog receivers if you are training two dogs simultaneously.



Figure 5.2: Remote Control Double Functions

This detailed view of the remote control highlights the multi-functional buttons, explaining their roles in activating the light, switching training modes, and managing multiple dog receivers.



Figure 5.3: 1100-Yard Operation Range

This image depicts the collar's effective operation range, showing a dog being trained off-leash at a distance, emphasizing the 1100-yard capability for outdoor use.

## 6. MAINTENANCE

Regular maintenance ensures the longevity and proper functioning of your INVIROX Dog Training Collar.

- **Cleaning:** Clean the receiver collar and remote control regularly with a damp cloth. Avoid using harsh chemicals or abrasive cleaners.
- **Contact Points:** Periodically check the contact points for dirt or debris. Clean them to ensure good contact with your dog's skin.
- **Strap:** Inspect the nylon strap for wear and tear. Replace if damaged.
- **Storage:** When not in use for extended periods, store the devices in a cool, dry place. Ensure they are fully charged before storage to maintain battery health.



Figure 6.1: IP67 Waterproof Receiver

This image demonstrates the IP67 waterproof capability of the receiver collar, indicating its durability and suitability for use in wet conditions, making cleaning and outdoor activities worry-free.

## 7. TROUBLESHOOTING

If you encounter issues with your INVIROX Dog Training Collar, refer to the following common problems and solutions:

Problem	Possible Cause	Solution
Receiver not responding to remote	Low battery on either device; Not paired; Out of range	Charge both devices; Re-pair the remote and receiver; Ensure devices are within range.
No static stimulation	Poor contact with skin; Level too low; Test bulb not working	Adjust collar fit and contact points; Increase stimulation level; Test with the provided test bulb.

Problem	Possible Cause	Solution
Short range	Environmental interference; Low battery	Avoid areas with strong electromagnetic interference; Ensure devices are fully charged.
Collar causing skin irritation	Improper fit; Prolonged wear	Reposition collar frequently; Do not leave on for more than 12 hours; Check for sores daily.

If these solutions do not resolve the issue, please contact INVIROX Customer Support for further assistance.

## 8. SPECIFICATIONS

Feature	Specification
Model Name	2024 Dog Training Collar
Brand	INVIROX
Range	1100 yards (approx. 1000 meters)
Waterproof Rating	IP67 (Receiver)
Training Modes	Beep, Vibration, Static Stimulation
Beep Levels	1-8
Vibration Levels	1-16
Static Stimulation Levels	1-99
Dog Weight Capacity	8 - 110 lbs
Receiver Weight	Approx. 49 grams
Remote Battery Life	Up to 45 days (standby)
Receiver Battery Life	Up to 15 days (per charge)
Material	Polycarbonate
ASIN	B08TP8Y266

## 9. WARRANTY AND SUPPORT

### 9.1 Warranty Information

The INVIROX 2024 Dog Training Collar comes with a **1-year warranty** from the date of purchase. This warranty covers manufacturing defects and malfunctions under normal use. It does not cover damage caused by misuse, accidents, unauthorized modifications, or normal wear and tear.


### 9.2 Customer Support

For any questions, concerns, or technical assistance regarding your INVIROX Dog Training Collar, please contact our customer support team. Our award-winning support is available to help you with setup, troubleshooting, and general inquiries.

Please refer to the product packaging or the official INVIROX website for the most current contact information for customer support.

© 2024 INVIROX. All rights reserved.

## Related Documents - 2024 Dog Training Collar

 The cover of the JUGBOW DT-68 Dog Training Collar User Manual. It features a green background with a white stylized 'J' logo and the text 'JUGBOW' at the top, and 'User Manual' at the bottom.	<p><a href="#"><u>JUGBOW DT-68 Dog Training Collar User Manual &amp; Guide</u></a></p> <p>Your essential guide to the JUGBOW DT-68 dog training collar. This user manual covers setup, operation, safety precautions, troubleshooting, and maintenance for effective and humane dog training. Learn about features like vibration, tone, and shock modes, waterproof design, and long-range capabilities.</p>
 The cover of the JUGBOW DT-68 Dog Training Collar User Manual. It features a green background with a white stylized 'J' logo and the text 'JUGBOW' at the top, and 'User Manual' at the bottom.	<p><a href="#"><u>JUGBOW DT-68 Dog Training Collar User Manual   Features, Operation &amp; Safety</u></a></p> <p>Comprehensive user manual for the JUGBOW DT-68 dog training collar. Learn about components, operation, safety guidelines, troubleshooting, and maintenance for effective pet training.</p>
 The cover of the 2-in-1 Remote Dog Training & Auto Anti-Bark Collar Operating and Training Guide. It features a white background with a grid of small icons representing different training modes and features.	<p><a href="#"><u>2-in-1 Remote Dog Training &amp; Auto Anti-Bark Collar Operating and Training Guide</u></a></p> <p>This guide provides comprehensive instructions and tips for using the 2-in-1 Remote Dog Training and Auto Anti-Bark Collar. Learn about its features, operation, safety precautions, and effective training methods for your dog.</p>
 The cover of the DT310 Electronic Training Collar System User Manual. It features a white background with a grid of small icons representing different training modes and features.	<p><a href="#"><u>DT310 Electronic Training Collar System User Manual</u></a></p> <p>User manual for the DT310 Electronic Training Collar System, covering features, package contents, how-to-use instructions, safety guidelines, troubleshooting, specifications, warranty, and FCC compliance.</p>
 The cover of the Pikabiu p-collar 628 Dog Training Collar User Manual. It features a white background with a black and white photograph of the dog training collar and remote unit, along with the text 'Dog Training Collar User Manual Model p-collar 628' and a small note at the bottom: 'Before using, please read the manual carefully'.	<p><a href="#"><u>Pikabiu p-collar 628 Dog Training Collar User Manual</u></a></p> <p>Comprehensive user manual for the Pikabiu p-collar 628 Dog Training Collar, covering features, safety, operation, charging, pairing, troubleshooting, and warranty information.</p>

## [SODOG KT47 Dog Training Collar User Manual - Remote Control System](#)



Comprehensive user manual for the SODOG KT47 Dog Training Collar. Learn about components, setup, charging, features like beep and vibration, manual pairing, channel management, maintenance, and FCC compliance.