

[Manuals.plus](#) /

› [Califone](#) /

› Califone 3066-USB Deluxe Multimedia Stereo Headset User Manual

Califone 3066-USB

Califone 3066-USB Deluxe Multimedia Stereo Headset User Manual

Model: 3066-USB

INTRODUCTION

This manual provides detailed instructions for the Califone 3066-USB Deluxe Multimedia Stereo Headset. Designed for clear audio communication and listening, this headset features a USB plug for easy connectivity, an omni-directional microphone, and noise-reducing earcups. Please read this manual thoroughly to ensure proper setup, operation, and maintenance of your device.

PACKAGE CONTENTS

Verify that all items are present in your package:

- Califone 3066-USB Deluxe Multimedia Stereo Headset (Pack of 2)
- Integrated USB Cable (7-ft)



Image: Two Califone 3066-USB Deluxe Multimedia Stereo Headsets. Each headset features large, over-ear earcups, a flexible gooseneck microphone extending from the left earcup, and an integrated USB cable. The headsets are black and appear durable.

SETUP

1. **Connect the Headset:** Locate an available USB port on your computer or laptop. Insert the USB plug of the Califone 3066-USB headset into the USB port. The headset is designed for Plug and Play functionality, meaning your operating system should automatically detect and install the necessary drivers.
2. **Adjust the Headset:** The headstrap is fully adjustable to fit various head sizes. Gently extend or retract the headstrap until the earcups sit comfortably over your ears.
3. **Position the Microphone:** The microphone features a flexible gooseneck design. Position the microphone approximately 1-2 inches from your mouth for optimal voice capture.
4. **Verify Audio Settings:** After connecting, check your computer's audio settings to ensure the Califone 3066-USB is selected as the default playback and recording device. This is typically found in your operating system's Sound or Audio settings.

OPERATING INSTRUCTIONS

The Califone 3066-USB headset features an in-line control unit on its 7-ft cord for convenient audio management.

- **Volume Control:** Use the in-line volume control wheel to adjust the listening volume of the headphones. Rotate the wheel up to increase volume and down to decrease volume.
- **Microphone Mute:** The in-line control includes a switch for microphone on/off (mute). Flip the switch to the 'off' position to mute the microphone, preventing your voice from being transmitted. Flip it to the 'on' position to enable the microphone.
- **Noise Reduction:** The earcups are designed to reduce ambient noise, providing a clearer listening experience. The omni-directional microphone includes a built-in windscreen to minimize the recording of unintended background sounds.

MAINTENANCE

Proper maintenance ensures the longevity and optimal performance of your headset.

- **Cleaning:** Use a soft, dry cloth to wipe down the earcups and headstrap. For stubborn dirt, a slightly damp cloth with mild soap can be used, but ensure no moisture enters the speaker or microphone components.
- **Ear Cushions:** The leatherette ear cushions are replaceable. If they become worn or damaged, contact Califone support for replacement options.
- **Cable Care:** Avoid sharp bends or excessive pulling on the 7-ft cord. The reinforced connection is designed to resist accidental pull-out, but proper handling will prevent damage.
- **Storage:** Store the headset in a clean, dry place away from extreme temperatures and direct sunlight when not in use.

TROUBLESHOOTING

If you encounter issues with your Califone 3066-USB headset, refer to the following common solutions:

- **No Sound/Microphone Not Working:**
 - Ensure the USB plug is fully inserted into a working USB port. Try a different USB port.
 - Check the in-line volume control and microphone mute switch. Ensure volume is up and mic is not muted.
 - Verify that the Califone 3066-USB is selected as the default audio input and output device in your computer's sound settings.
 - Restart your computer.
- **Poor Audio Quality:**
 - Adjust the volume using the in-line control and your computer's system volume.
 - Ensure the microphone is positioned correctly (1-2 inches from mouth) and not obstructed.
 - Check for any loose connections.
- **Headset Not Recognized by Computer:**
 - Try connecting the headset to a different USB port or another computer to rule out a port issue.
 - Check your computer's Device Manager (Windows) or System Information (macOS) to see if the device is listed.

- Ensure your operating system is up to date.

SPECIFICATIONS

Califone 3066-USB Headset Specifications

Feature	Detail
Model	3066-USB
Connectivity	Wired USB (Backwards compatible USB 2.0)
Headphone Speaker Size	40mm Mylar
Headphone Frequency Response	20-20000 Hz
Headphone Sensitivity	110dB SPL ± 3dB at 1kHz
Microphone Type	Electret Condenser
Microphone Directivity	Omni-directional
Microphone Frequency Response	20-16000 Hz
Microphone Sensitivity	-41dB (standard -38dB, max -35dB)
Cord Length	7-ft (2.1 meters)
Controls	In-line volume control, mic on/off switch
Earcups	Noise-reducing ABS plastic with replaceable leatherette cushions
Weight (each)	0.75 lbs (12 ounces)

WARRANTY AND SUPPORT

For warranty information, technical support, or to inquire about replacement parts (such as ear cushions), please contact Califone customer service directly. Refer to the official Califone website for the most current contact details and warranty policies.

You can visit the Califone store on Amazon for more product information:[Califone Store](#)