

[Manuals.plus](#) /

› [Gemini Sound](#) /

› Gemini AS-2115BT-LT-PK 2000W Bluetooth PA Speaker User Manual

Gemini Sound AS-2115BT-LT-PK

Gemini AS-2115BT-LT-PK 2000W Bluetooth PA Speaker User Manual

Model: AS-2115BT-LT-PK

Brand: Gemini Sound

PRODUCT OVERVIEW

The Gemini AS-2115BT-LT-PK is a powerful 2000W Bluetooth PA Speaker system designed for various audio applications, from mobile DJ setups to home entertainment. It features a 15-inch woofer with LED lights, USB/SD/FM playback, wireless stereo pairing, and multiple professional audio inputs.



Figure 1: Gemini AS-2115BT-LT-PK PA Speaker with included accessories.

WHAT'S IN THE BOX

Upon unboxing, please verify that all components listed below are present:

- AS-2115BT-LT Loudspeaker
- Speaker Stand
- Remote Control
- Wired Microphone
- Power Cable
- User Manual (this document)

WHAT'S IN THE BOX

AS-2115BT-LT LOUDSPEAKER - WIRED MICROPHONE
SPEAKER STAND - POWER CABLE



Figure 2: All items included in the AS-2115BT-LT-PK package.

SETUP

Speaker Placement and Stand Assembly

For optimal sound dispersion, position the speaker on the included tripod stand. Ensure the stand is fully extended and stable on a flat surface before mounting the speaker. The speaker features fly points and a stand mount for versatile placement options.

FLY POINTS

2 - M8 FLY POINTS FOR PERMANENT INSTALLATION



Figure 3: Speaker fly points for secure installation.

Power Connection

Connect the power cable to the speaker's power input and then to a suitable electrical outlet. The unit supports switchable 110-120V / 220-240V power with fuse protection. Ensure the voltage switch is set correctly for your region before powering on.

FULL CONTROL

MIC/LINE INPUTS - VOLUME CONTROL - ADJUSTABLE BASS & TREBLE



Figure 4: Rear control panel with power input and voltage switch.

OPERATING INSTRUCTIONS

Audio Inputs and Mixer

The AS-2115BT-LT-PK features a 3-channel mixer allowing for multiple audio sources. Connect microphones, guitars, or other line-level devices using the XLR, 1/4-inch, or RCA inputs. Adjust individual channel gain controls as needed.

FULL CONTROL

MIC/LINE INPUTS - VOLUME CONTROL - ADJUSTABLE BASS & TREBLE



Figure 5: Mixer controls and input options.

Bluetooth Pairing

To connect a Bluetooth-enabled device, select the Bluetooth mode on the speaker's media player. Search for "Gemini AS-2115BT-LT-PK" on your device and pair. The speaker supports wireless stereo pairing (TWS) with another compatible unit for a wider soundstage.

BLUETOOTH

FROM ANY WHERE UP TO 25FT AWAY



Figure 6: Bluetooth connectivity for wireless audio streaming.

TWS

LINK 2ND SPEAKER FOR TRUE WIRELESS STEREO



Figure 7: True Wireless Stereo (TWS) pairing for enhanced sound.

Media Player Functions (USB/SD/FM)

Insert a USB drive or SD card into the designated slots on the media player. Use the controls to navigate tracks and adjust playback. The built-in FM radio allows for listening to local stations; extend the internal antenna for better reception.

LED Lighting Control

The speaker features vibrant beat-synced full-color LED woofer lighting. Use the controls on the rear panel or the remote control to select different lighting modes or turn the lights off.

LIGHT IT UP

MULTI-COLOR PARTY LIGHTING



Figure 8: Multi-color LED lighting in action.

Equalizer (EQ) Adjustment

Fine-tune the audio output using the onboard Bass and Treble equalizer controls. Adjust these to suit your listening environment and music genre.

Official Product Video

Your browser does not support the video tag.

Video 1: Official product overview of the Gemini AS-2115BT-LT PA Speaker, showcasing its features and capabilities.

MAINTENANCE

To ensure the longevity and optimal performance of your Gemini PA Speaker, follow these maintenance guidelines:

- **Cleaning:** Use a soft, dry cloth to clean the exterior of the speaker. Avoid using abrasive cleaners, waxes, or solvents.
- **Ventilation:** Ensure proper ventilation around the speaker to prevent overheating. Do not block any ventilation openings.
- **Storage:** When not in use for extended periods, store the speaker in a cool, dry place, away from direct sunlight and extreme temperatures.
- **Cable Management:** Regularly check all cables for signs of wear or damage. Replace any damaged cables immediately.

TROUBLESHOOTING

No Power

- Ensure the power cable is securely connected to both the speaker and a working electrical outlet.
- Check the power switch on the rear panel is in the "ON" position.
- Verify the voltage selector switch (110-120V / 220-240V) is set correctly for your region.
- Check the fuse. If blown, replace it with a fuse of the same type and rating.

No Sound Output

- Confirm the Master Volume is turned up.
- Check individual channel gain controls for connected inputs.
- Ensure audio cables are properly connected and not damaged.
- If using Bluetooth, ensure the device is paired and volume is up on both the speaker and the source device.
- If using USB/SD, ensure the media files are in a supported format and the volume is adjusted.

Bluetooth Connection Issues

- Ensure the speaker is in Bluetooth mode.
- Move your Bluetooth device closer to the speaker (within 25 feet).
- Disconnect and re-pair the Bluetooth device.
- Turn off and on both the speaker and the Bluetooth device.

SPECIFICATIONS

Feature	Detail
Model Number	AS-2115BT-LT-PK
Output Wattage	2000 Watts (Peak)
Woofers Size	15 inches with 2" High Temperature Voice Coil

Feature	Detail
Tweeter	1" Pure Titanium High-Frequency Compression Driver
Connectivity Technology	AUX, Bluetooth, NFC, RCA, XLR
Number of Channels	3
Product Dimensions (L x W x H)	14.57 x 17.4 x 27.02 inches
Item Weight	30.1 pounds
Mounting Type	Stand Mount
Power Source	Corded Electric
Color	Black
UPC	747705007711



Figure 9: Speaker components: Woofer and Tweeter.

SIZE

DIMENSIONS



Figure 10: Product dimensions.

WARRANTY AND SUPPORT

Gemini Sound products are designed for reliability and performance. For warranty information and technical support, please refer to the official Gemini Sound website or contact their customer service directly. Keep your purchase receipt as proof of purchase for warranty claims.

For further assistance, you may visit the official Gemini Sound Store: [Gemini Sound Store](#)

