

Manuals+

[Q & A](#) | [Deep Search](#) | [Upload](#)

manuals.plus /

- › [EGLO](#) /
- › [EGLO Palmaves 1 LED Ceiling Light User Manual](#)

EGLO 75555

EGLO Palmaves 1 LED Ceiling Light User Manual

Model: 75555

INTRODUCTION

This manual provides instructions for the safe installation, operation, and maintenance of your EGLO Palmaves 1 LED Ceiling Light. Please read these instructions carefully before installation and retain them for future reference. This LED ceiling light features dimmable functionality, adjustable color temperature from warm white to cool white, RGB color options, a night light mode, and is controlled via an included remote.



Image: The EGLO Palmaves 1 LED Ceiling Light, featuring two interconnected rings, installed on a ceiling in a modern living space.

SETUP AND INSTALLATION

Installation should be performed by a qualified electrician in accordance with local wiring regulations. Always ensure the main power supply is disconnected before commencing any electrical work.

Package Contents:

- EGLO Palmaves 1 LED Ceiling Light fixture
- Remote Control
- Mounting hardware (screws, wall plugs)
- Assembly Instructions (this document)

Mounting the Fixture:

1. **Safety First:** Turn off the power at the main circuit breaker before installation.
2. **Prepare Mounting Surface:** Mark the drilling points on the ceiling using the fixture's mounting bracket as a template.
3. **Drill Holes:** Drill holes at the marked points and insert appropriate wall plugs.
4. **Connect Wiring:** Connect the household electrical wires to the fixture's terminal block. Ensure correct polarity (Live, Neutral, Earth).
5. **Secure Fixture:** Attach the mounting bracket to the ceiling using screws. Secure the light fixture to the mounting bracket.
6. **Restore Power:** Once installation is complete and all connections are secure, restore power at the main circuit breaker.

Remote Control Battery Installation:

The remote control requires 2 AAA batteries (not included). Open the battery compartment on the back of the remote and insert the batteries, observing the correct polarity (+/-). Close the compartment securely.

OPERATING INSTRUCTIONS

The EGLO Palmaves 1 LED Ceiling Light is controlled using the provided 2.4G RF remote control. Ensure the remote has fresh batteries and is within range of the light fixture.





Image: The white remote control for the EGLO Palmaves 1 LED Ceiling Light, showing buttons for power, brightness, color temperature, night light, and timer functions.

Remote Control Functions:

- **ON/OFF:** Press to turn the light on or off.
- **B- / B+:** Adjust brightness levels. B- decreases brightness, B+ increases brightness.
- **WW (Warm White):** Adjusts the color temperature towards warmer tones (e.g., 3000 Kelvin).
- **CW (Cool White):** Adjusts the color temperature towards cooler tones (e.g., 6500 Kelvin).
- **Night Light Mode:** Activates a low-brightness setting (approximately 10% intensity) suitable for night use.
- **Timer:** Activates a 30-minute auto-off function. The light will turn off automatically after 30 minutes.
- **RGB:** This model supports RGB color changing. Specific buttons or combinations on the remote will cycle through or select various RGB colors. Refer to the remote's markings for exact RGB control.

CARE AND MAINTENANCE

Proper care ensures the longevity and optimal performance of your EGLO Palmaves 1 LED Ceiling Light.

- **Cleaning:** Disconnect power before cleaning. Use a soft, dry, or slightly damp cloth to wipe the surface of the fixture. Avoid abrasive cleaners, solvents, or harsh chemicals, as these can damage the finish and electronic components.
- **LEDs:** The LED light source is integrated and not user-replaceable. Do not attempt to disassemble the light fixture to replace LEDs.
- **General Inspection:** Periodically check the fixture for any signs of damage or loose connections. If any issues are found, disconnect power and consult a qualified electrician.

TROUBLESHOOTING

If you encounter issues with your EGLO Palmaves 1 LED Ceiling Light, refer to the following common problems and solutions:

Problem	Possible Cause	Solution
Light does not turn on.	No power supply. Remote control batteries are dead. Remote control not paired.	Check circuit breaker and wall switch. Replace remote control batteries (2 AAA). Refer to remote control pairing instructions (if applicable, usually involves turning light on/off and pressing a button on remote within seconds).
Light does not respond to remote control.	Remote control batteries are low/dead. Obstruction between remote and light. Remote control not paired.	Replace remote control batteries. Ensure clear line of sight to the light fixture. Re-pair the remote control with the light.
Light flickers or has inconsistent brightness.	Unstable power supply. Loose wiring connection.	Consult a qualified electrician to check the electrical supply. Disconnect power and check wiring connections (only by a qualified person).

SPECIFICATIONS

Detailed technical specifications for the EGLO Palmaves 1 LED Ceiling Light.



Image: A technical diagram illustrating the dimensions of the EGLO Palmaves 1 LED Ceiling Light, showing diameters of 29 cm and 39 cm, and a height of 7 cm.

Feature	Detail
Model Number	75555
Dimensions (L x W x H)	45 x 30 x 12 cm (overall); Large element: Ø 39 cm; Small element: Ø 29 cm; Height: 7 cm
Weight	994 Grams
Power Source	AC Power (240 Volts)
Wattage	21.6 Watts (max)
Luminous Flux	2940 Lumens (max)
Color Temperature	3000K (Warm White) - 6500K (Cool White), RGB
Dimmable	Yes
Control Method	Remote Control (2 AAA batteries required)
Material	Aluminum, Alloy Steel, Plastic
Fixture Shape	Round Ceiling Light
Installation Type	Flush Mount
Indoor/Outdoor Use	Indoor Only
Energy Class	E
Country of Origin	China

WARRANTY INFORMATION

The EGLO Palmaves 1 LED Ceiling Light comes with a limited warranty. For specific details regarding the warranty period, coverage, and terms, please refer to the warranty documentation provided with your purchase or contact EGLO customer service. Keep your proof of purchase for warranty claims.

CUSTOMER SUPPORT

If you require further assistance, have questions not covered in this manual, or need to report a defect, please contact EGLO customer service. Contact information can typically be found on the EGLO website or on your product packaging.

Website: www.eglo.com