

Manuals+

[Q & A](#) | [Deep Search](#) | [Upload](#)

[manuals.plus](#) /

› [Browning](#) /

› [Browning Strike Force Pro XD Trail Camera User Manual](#)

Browning Strike Force Pro XD

Browning Strike Force Pro XD Trail Camera

USER MANUAL

Product Overview

The Browning Strike Force Pro XD Trail Camera is designed for capturing high-quality images and videos of wildlife and for security monitoring. It features advanced Dual Camera Lens Technology, providing optimized performance for both daytime and nighttime conditions. This manual provides detailed instructions for setting up, operating, maintaining, and troubleshooting your camera.

Key Features:

- **Dual Camera Lens Technology:** Dedicated lenses for razor-sharp daytime and clear nighttime images.
- **Fast Action:** 0.15-second trigger speed and 0.5-second picture recovery time.
- **Wide Detection Range:** 80 ft. motion detection range.
- **High-Quality Video:** 1080p Full HD videos with sound (5 seconds to 2 minutes in length).
- **Illuma-Smart Technology:** Automatically adjusts IR flash for optimal night photos.
- **Internal Color Screen:** 1.5-inch color view screen for easy setup and footage review.
- **Flexible Mounting:** All-steel adjustable tree mount bracket.
- **Memory Card Support:** Compatible with up to 512GB SDXC memory cards.
- **Timelapse Plus:** Camera mode with IR triggered images.

Setup

1. Battery Installation

The Strike Force Pro XD Trail Camera requires 6 AA batteries (not included). For optimal performance and battery life, it is recommended to use high-quality alkaline or lithium batteries. The battery tray is easily removed from the bottom of the camera. Insert the batteries according to the polarity indicators (+/-) inside the tray, ensuring they snap securely into place. Reinsert the tray firmly into the camera.



Opening the front panel of the camera reveals the 1.5-inch color view screen and intuitive control buttons for easy setup and footage review.

2. SD Card Installation

The camera supports SDXC memory cards up to 512GB. Locate the SD card slot on the bottom of the unit. Insert the SD card with the label facing up until it clicks into place. To remove, gently push the card in until it springs out. Ensure the camera is powered off before inserting or removing the SD card to prevent data corruption.



The included 32GB SDHC Class 10 memory card ensures fast data write speeds for high-resolution photos and HD video.

3. Mounting the Camera

The Strike Force Pro XD comes with an all-steel adjustable tree mount bracket. Attach the camera to a tree or post using the provided strap, ensuring the bracket is snug against the mounting surface. The bracket allows for angle adjustment, enabling you to point the camera precisely where needed, even downwards towards the ground. Secure the camera firmly to prevent movement from wind or wildlife.



The back of the camera features a robust, adjustable metal bracket designed for secure tree mounting.



The camera is shown deployed on a tree, with a user demonstrating how to review captured images and videos directly on a smartphone using a compatible SD card reader.

4. Initial Settings

Once batteries and SD card are installed, power on the camera. Use the internal 1.5-inch color screen and the control buttons to navigate the menu. The menu system is straightforward: use the up and down arrow buttons to scroll through options, and the OK/Set button to select and confirm changes. Set the current time, date, and desired capture mode (photo, video, or Timelapse Plus).

Operating the Camera

Capture Modes

- Photo Mode:** Captures still images. You can set the number of multi-shot images (up to 8) or rapid-fire images (up to 8) per trigger event.
- Video Mode:** Records 1080p Full HD video clips with sound, adjustable from 5 seconds to 2 minutes in length.
- Timelapse Plus Mode:** Captures images at set intervals throughout the day, with additional IR-triggered images at night. Compatible with Browning Buck Watch Timelapse Viewer Software.

Advanced Features

- Dual Camera Lens Technology:** Automatically switches between a custom-tuned daytime lens and a dedicated night lens for superior image quality in all lighting conditions.
- Illuma-Smart Technology:** Intelligently adjusts the infrared flash power to ensure perfectly exposed night photos.
- Adjustable IR Flash Range:** Customize the flash power settings (Power Save, Long Range, Fast Motion) to suit your specific needs and environment. The flash range extends up to 120 ft.
- Picture Info Bar:** Each captured image includes an information bar displaying the time, date, temperature, moon phase, and camera ID for easy tracking.

SD Card Management

The camera features an SD Card Management option in the settings menu. This allows you to manage storage space by overwriting older files when the card is full, or to stop recording once the card is full. Regularly check your SD card capacity and transfer data to a computer or external device to prevent loss of important footage.

Maintenance

- Cleaning:** Use a soft, dry cloth to clean the camera body and lenses. Avoid abrasive cleaners or solvents. Ensure the lenses are free of dirt, dust, or smudges for clear images.
- Battery Replacement:** Replace batteries when the low battery indicator appears on the screen or when performance degrades. Always replace all batteries at once with new ones of the same type.
- SD Card Care:** Format your SD card periodically using the camera's format function to ensure optimal performance and prevent data corruption. Store SD cards in a protective case when not in use.
- Environmental Protection:** While the camera is designed for outdoor use, avoid prolonged exposure to extreme temperatures or direct water submersion. Ensure the latch is securely closed to maintain water resistance.

Troubleshooting

Problem	Possible Cause	Solution
Camera not powering on	Dead or incorrectly installed batteries; faulty battery tray.	Replace batteries with new ones, ensuring correct polarity. Check battery tray for damage.
Poor image/video quality	Dirty lens; incorrect settings; low light conditions.	Clean the camera lens. Adjust image/video resolution settings. Ensure adequate IR flash range for night captures.
Camera not detecting motion	Detection range too short; obstruction in detection zone; incorrect sensitivity settings.	Adjust camera placement. Clear any obstructions. Increase motion sensitivity in settings.
SD card errors or not recognized	Incompatible SD card; corrupted card; card not inserted correctly.	Ensure using a compatible SDXC card (up to 512GB). Format the SD card using the camera's menu. Reinsert the card. Try a different SD card. Note: Some 64MB cards may not be fully compatible.
Short battery life	Frequent triggers; extreme temperatures; low-quality batteries.	Reduce trigger frequency if possible. Use high-quality alkaline or lithium batteries. Consider external 12V power source for prolonged use.

Specifications

Feature	Detail
Model Name	Strike Force Pro XD
Trigger Speed	0.15 Seconds
Picture Recovery Time	0.5 Seconds
Detection Range	80 ft.
Flash Range	120 ft. (Adjustable IR Flash)

Feature	Detail
Video Resolution	1920 x 1080 Full HD with Sound
Video Length	5 sec. - 2 min.
Display Screen	1.5 inch Color View Screen
Memory Card Support	Up to 512GB SDXC
Power Source	6 AA Batteries (not included), 12-volt external power jack
Mounting Type	All-Steel Adjustable Tree Mount Bracket
Connectivity Technology	Infrared
International Protection Rating	IP54


Warranty and Support

For warranty information and technical support regarding your Browning Strike Force Pro XD Trail Camera, please refer to the documentation included with your purchase or visit the official Browning Trail Cameras website. You may also contact the product licensee, The Prometheus Group, for assistance. Keep your proof of purchase for any warranty claims.

For additional resources and software compatibility, such as the Browning Buck Watch Timelapse Viewer Software, please visit the manufacturer's support page.

© 2024 Browning Trail Cameras. All rights reserved.

Related Documents - Strike Force Pro XD

 INSTRUCTION MANUAL	<p>Browning Strike Force FHD Trail Camera BTC-5FHDR Instruction Manual</p> <p>Comprehensive instruction manual for the Browning Strike Force FHD Trail Camera, Model BTC-5FHDR. Learn about setup, operation, features, and maintenance.</p>
	<p>Browning Defender Pro Scout Max HD Cell Camera Instruction Manual</p> <p>Comprehensive instruction manual for the Browning Defender Pro Scout Max HD 4G LTE Cell Camera, covering setup, operation, mobile app integration, and warranty information.</p>

 INSTRUCTION MANUAL	<p><u>Browning Recon Force Advantage BTC-7A Trail Camera Instruction Manual</u></p> <p>This manual provides instructions for setting up and using the Browning Recon Force Advantage BTC-7A Trail Camera, covering features like capture modes, photo and video quality, and installation.</p>
 INSTRUCTION MANUAL	<p><u>Browning Recon Force 4K Trail Camera BTC-7-4K Instruction Manual</u></p> <p>Instruction manual for the Browning Recon Force 4K Trail Camera, Model BTC-7-4K. Covers setup, operation, features, and specifications.</p>
 INSTRUCTION MANUAL	<p><u>Browning Strike Force HD Extreme BTC-5FHD Trail Camera Instruction Manual</u></p> <p>Comprehensive instruction manual for the Browning Strike Force HD Extreme BTC-5FHD trail camera, covering setup, features, settings, warranty, and specifications.</p>
 INSTRUCTION MANUAL	<p><u>Browning Recon Force Platinum Series BTC-7FHD-P Trail Camera Instruction Manual</u></p> <p>Comprehensive instruction manual for the Browning Recon Force Platinum Series BTC-7FHD-P trail camera, covering setup, operation, features, specifications, and warranty.</p>

Documents - Browning – Strike Force Pro XD



[\[pdf\] Warranty Accessories Catalog](#)

Browning Trail Cameras 2018 Catalog browningtrailcameras zendesk hc en us article attachments
360001994913 |||

2018 PRODUCT CATALOG WELCOME When you are in the field, there are three things that matter with a ... RIKE FORCE PRO XD Model# BTC-5PXD The most feature rich camera in the Strike Force line up is the Strike Force Pro XD. Our flagship Strike Force model features Dual Camera Lens Technology . We have...
lang:en **score:18** filesize: 8.37 M page_count: 17 document date: 2017-12-06



[\[pdf\] Warranty Accessories Catalog](#)

2019 Browning Trail Cameras Catalog browningtrailcameras zendesk hc en us article attachments
360021751634 |||

2019 PRODUCT CATALOG When you are in the field, there are three things that matter with a trail c ... RIKE FORCE PRO XD Model# BTC-5PXD The most feature rich camera in the Strike Force line up is the Strike Force Pro XD. Our flagship Strike Force model features Dual Camera Lens Technology . We have...
lang:en **score:17** filesize: 13.36 M page_count: 36 document date: 2018-11-19



[\[pdf\]](#)

Microsoft Word 2017 Browning TrailCam BTC5HD 850 Dell Browning Trail Cameras Strike Force Pro XD
The most feature rich camera in the series of cameras is Our flagship BTC5PXD Information CTcc
cameratraps co za 2019 05 |||

■ ■

lang:en score:15 filesize: 496.93 K page_count: 1 document date: 2018-06-01



[pdf] Catalog

BTC 2020 Catalog browningtrailcameras zendesk hc en us article attachments 360056782093 |||
2020 PRODUCT CATALOG WELCOME When we are in the field, there are three things that matter with a ... RIKE FORCE PRO XD Model# BTC-5PXD The most feature rich camera in the Strike Force line up is the Strike Force Pro XD. Our flagship Strike Force model features Dual Camera Lens Technology . We have...

lang:en score:14 filesize: 7.22 M page_count: 19 document date: 2019-12-09



[\[pdf\]](#) Catalog

BTC 2021 CATALOG browningtrailcameras zendesk hc en us article attachments 1260800855290 ||| b rown i n gtrailcame ra s .com 2021 PRODUCT CATALOG Because of our hectic farming schedule, we ... ail Cameras Brand Ambassador and Host at McMillan Sportsman Channel 18 BROWNING TRAIL cameraS Strike Force Pro XD Model# BTC-5PXD The most feature rich camera in the Strike Force line up is th... lang:en score:13 filesize: 9.03 M page_count: 40 document date: 2021-01-08

[pdf]


BTC 2020 Comparison Chart browningtrailcameras zendesk hc en us article attachments 360055906474

11

BROWNING TRAIL CAMERAS 2020 COMPARISON CHART SD CARD

MANAGEMENT By turning the SD Card Management f ... 6 STRIKE FORCE HD MAX BTC-5HD-MAX STRIKE FORCE APEX BTC-5HD-APX STRIKE FORCE HD PRO X BTC-5HDGX **STRIKE FORCE PRO XD** BTC-5PXD DARK OPS HD MAX BTC-6HD-MAX DARK OPS APEX BTC-6HD-APX DARK OPS HD PR...

lang:en score:12 filesize: 14.92 M page count: 1 document date: 2020-01-08



[pdf]

Darin Stephens 2018 Detection Shootout Edited 3849913497911451629 cdn shopify s files 1 1065 8354

Item 10R 10L 20R 20L 30R 30L 40R 40L 50R 50L 60R 60L 70R 70L 80R 80L 90R 90L
100R ... 4 4 5 6 8 7 10 8 8 8 10 8 4 5 3 3 1 2 0 0 0 0 0 0 104 132 79 Browning Strike
Force Pro XD 5 6 8 8 8 8 7 7 6 5 7 3 8 3 5 4 1 3 0 0 0 0 0 0 102 11...

lang:tl score:11 filesize: 363.35 K page_count: 1 document date: 2018-06-22