

[Manuals.plus](#) /

› [UrbanX](#) /

› UrbanX Mini Bluetooth Receiver User Manual

## UrbanX UrbanX BT Receiver 5.0

# UrbanX Mini Bluetooth Receiver User Manual

Model: UrbanX BT Receiver 5.0

## INTRODUCTION

This manual provides detailed instructions for the UrbanX Mini Bluetooth Receiver. This device allows you to wirelessly stream audio from your Bluetooth-enabled devices to non-Bluetooth audio systems, such as car stereos, home speakers, or wired headphones. It also supports hands-free calling.

## PRODUCT OVERVIEW

The UrbanX Mini Bluetooth Receiver is a compact and versatile audio adapter designed for convenience and high-quality sound. It features Bluetooth 4.1 technology for stable connectivity and includes a built-in microphone for hands-free communication.

### Key Features:

- Advanced Bluetooth 4.1 for stable and fast connection.
- High-sensitivity microphone for clear calls.
- Noise-cancelling chip integrated.
- Compact and portable design.
- Supports A2DP, AVRCP, HSP, and HFP profiles.
- Converts 3.5mm audio systems into wireless Bluetooth systems.

### Package Contents:



Bluetooth receiver



3.5mm audio connector



USB cable

#### Bluetooth

##### Product description

This product is a Bluetooth music receiver (speaker) with Bluetooth function on the front panel. It is suitable for almost all of the input audio receiver with plug, audio or audio system to the vehicle your smart mobile phone. It can be used for talking through car audio solutions, phone calls and music playback. It has a built-in echo cancellation microphone, only for hands-free calls, stored in the phone to be used.

##### Charge description

For the first time, it is suggested that the battery is fully charged. 1 the mini-USB input interface is connected to the charging interface, then the Bluetooth music receiver will power after the red light.

##### Bluetooth operation instructions

- 1 long press the music receiver on the button for the mobile phone Bluetooth function to open, the "Receiver BT"
- 2 select "Receiver BT" and connect it to some of

user manual

The package includes the Bluetooth receiver unit, a detachable 3.5mm audio connector, and a USB charging cable.

### Component Identification:



This image displays the key components of the UrbanX Mini Bluetooth Receiver, including the Multifunction Key, Indicator light, Charging Port, 3.5mm Audio Interface, and Microphone. The 3.5mm Audio Connector is also shown separately.

- **Multifunction Key:** Used for power on/off, play/pause, answer/end calls, redial.
- **Indicator:** LED light showing device status (pairing, connected, charging).
- **Charging Port:** Micro USB port for charging the device.
- **3.5mm Audio Interface:** Connects to audio output devices like headphones or speakers.
- **Microphone:** For hands-free calling.
- **3.5mm Audio Connector:** Detachable connector for plugging into AUX ports.

#### Wide Compatibility:



The receiver is compatible with a wide range of devices, including smartphones, tablets, laptops, PCs, smart TVs, and can connect to car AUX inputs, headphones, and speakers.

## SETUP

### 1. Charging the Receiver:

1. Connect the provided USB charging cable to the receiver's charging port.
2. Plug the other end of the USB cable into a DC 5V power source (e.g., USB wall adapter, computer USB port).
3. The LED indicator will show charging status. A full charge takes approximately 1.5 hours.
4. Ensure the device is fully charged before first use. If the device does not turn on, the battery may be low.

### 2. Pairing with a Bluetooth Device:

1. **Power On:** Press and hold the Multifunction Key for approximately 3 seconds until the LED indicator flashes blue and red alternately. This indicates the receiver is in pairing mode.
2. **Activate Bluetooth:** On your mobile phone or other Bluetooth-enabled device, turn on Bluetooth.

3. **Search for Devices:** Search for available Bluetooth devices. You should see "Receiver BT" or "UrbanX BT Receiver 5.0" in the list.
4. **Connect:** Select "Receiver BT" or "UrbanX BT Receiver 5.0" to pair. Once successfully paired, the LED indicator will flash blue slowly.
5. **Connect to Audio System:** Plug the 3.5mm audio connector into the AUX input of your car stereo, home speaker system, or directly into your wired headphones.



## Turn Car Aux to be Bluetooth Speaker

hands-free calls,  
enjoy breezily driving

Listening to music,  
Enjoy a pleasant journey

The receiver can be used to enable hands-free calls and music streaming in your car by connecting it to the car's AUX input.

# For Home Audio System

Turn Normal Speaker into Wireless Bluetooth Speaker



Transform your home audio system into a wireless Bluetooth speaker by connecting the receiver to its audio input.

# Change wired headphones into Bluetooth headphones

Remote control the volume, tracks and pauses from the receiver.



Convert your wired headphones into Bluetooth headphones by plugging them into the receiver's 3.5mm audio interface.

## OPERATING INSTRUCTIONS

### Power On/Off:

- **Power On:** Press and hold the Multifunction Key for 3 seconds. The LED indicator will flash blue.
- **Power Off:** Press and hold the Multifunction Key for 3 seconds. The LED indicator will turn off.

### Music Playback:

- **Play/Pause:** Short press the Multifunction Key.
- **Next Track:** Double press the Multifunction Key.
- **Previous Track:** Triple press the Multifunction Key.
- Volume control is typically managed directly from your connected Bluetooth device (phone, tablet).

### Hands-Free Calling:

- **Answer Call:** Short press the Multifunction Key when a call comes in.
- **End Call:** Short press the Multifunction Key during a call.
- **Reject Call:** Press and hold the Multifunction Key for 2 seconds when a call comes in.
- **Redial Last Number:** Double press the Multifunction Key when not on a call.



Enjoy handsfree time and safe driving



Answer



Redial  
last number



Reject



The receiver enables safe, hands-free communication while driving.

## MAINTENANCE

- **Cleaning:** Use a soft, dry cloth to clean the device. Do not use liquid cleaners or aerosols.
- **Storage:** Store the device in a cool, dry place away from direct sunlight and extreme temperatures.
- **Temperature:** Do not expose the receiver to temperatures above 45°C (113°F) or prolonged direct sunlight, as this can affect its service life.
- **Charging:** Always use a DC 5V power source for charging. Using a higher input voltage may damage the receiver.

## TROUBLESHOOTING

**Device does not turn on:**

The battery may be low. Charge the device fully before attempting to power it on again.

**Cannot pair with Bluetooth device:**

- Ensure the receiver is in pairing mode (LED flashing blue and red alternately).
- Make sure Bluetooth is enabled on your source device (phone, tablet).
- Ensure the receiver is within the 10-meter (30ft) connection range of your source device.
- Try restarting both the receiver and your source device.

**No audio or poor audio quality:**

- Check that the 3.5mm audio connector is securely plugged into both the receiver and your audio system's AUX input.
- Ensure the volume on both your source device and the audio system is turned up.
- Verify that the receiver is successfully paired and connected to your source device.
- Check for any interference from other wireless devices.

## SPECIFICATIONS

|                    |                                      |
|--------------------|--------------------------------------|
| Model Name         | UrbanX BT Receiver 5.0               |
| Bluetooth Version  | V4.1                                 |
| Charging Voltage   | DC 5V                                |
| Charging Time      | Up to 1.5 Hours                      |
| Working Time       | 5 Hours                              |
| Connection Range   | 10 Meters / 30 Feet                  |
| Headphone Jack     | 3.5mm                                |
| Supported Profiles | A2DP, AVRCP, HSP, HFP                |
| Material           | Composite                            |
| Weight             | 0.55 oz                              |
| Battery Type       | 1 Lithium Ion battery (rechargeable) |

## WARRANTY AND SUPPORT

For warranty information and customer support, please refer to the product packaging or contact UrbanX customer service directly. You can often find support details on the official UrbanX website or through your retailer.

For further assistance, please visit the [UrbanX Store on Amazon](#).

## ASK A QUESTION ABOUT THIS MANUAL

Ask about setup, troubleshooting, compatibility, parts, safety, or missing instructions. Manuals+ will review the question and use this page's manual context to help answer it.

### Name

Anonymous

### Email

you@example.com

After a successful submission, we securely hash the supplied account or form email before sending it to Microsoft Advertising for conversion attribution. [Privacy details](#).

### Question

Example: How do I reset this device or fix this error?

### Details

Model number, symptoms, what you tried, or the section of the manual you are using.

Submit question