

Manuals.plus /

› GANPE /

› GANPE LED Bathroom Mirror with Motion Sensor and Bluetooth (Model GPHC1025HBI) Instruction Manual

GANPE GPHC1025HBI

GANPE LED Bathroom Mirror Instruction Manual

Model: GPHC1025HBI

Brand: GANPE

1. INTRODUCTION

Thank you for choosing the GANPE LED Bathroom Mirror. This manual provides essential information for the safe installation, operation, and maintenance of your new mirror. Please read these instructions thoroughly before installation and keep them for future reference.

2. SAFETY INFORMATION

- Always disconnect power at the circuit breaker before installation or maintenance.
- Installation should be performed by a qualified electrician in accordance with local electrical codes.
- This mirror is rated IP44, indicating protection against splashing water. Do not submerge or expose to direct water jets.
- Handle the mirror with care to prevent damage. The mirror glass is fragile.
- Do not attempt to repair or modify the mirror. Contact customer support for assistance.
- Keep packaging materials away from children.

3. PACKAGE CONTENTS

Please check that all components are present and undamaged:

- GANPE LED Bathroom Mirror
- Mounting Hardware (screws, wall anchors)

- Installation Cardboard Template
- Instruction Manual

4. SETUP AND INSTALLATION

The GANPE LED Bathroom Mirror can be installed either horizontally or vertically to best suit your bathroom layout.

4.1 Choosing Installation Orientation

Decide whether to mount the mirror horizontally or vertically. Ensure the chosen location has access to the electrical connection.



Image: The GANPE LED Bathroom Mirror supports both horizontal and vertical installation.

4.2 Mounting Steps

1. **Prepare the Wall:** Ensure the wall surface is clean, dry, and capable of supporting the mirror's weight (approximately 9.07 kg or 20 lbs).
2. **Mark Drilling Points:** Use the provided installation cardboard template to mark the precise drilling locations on the wall. Ensure the template is level.



Image: Use the installation cardboard template for accurate drilling.

3. **Drill Holes:** Drill holes at the marked positions using an appropriate drill bit for your wall type.
4. **Insert Wall Anchors:** Insert the wall anchors into the drilled holes until flush with the wall surface.
5. **Attach Mounting Brackets:** Secure the mounting brackets to the wall using the provided screws.
6. **Electrical Connection:** Connect the mirror's electrical wiring to your household electrical supply. This step must be performed by a qualified electrician. Ensure proper grounding.
7. **Hang the Mirror:** Carefully lift the mirror and align its hanging slots with the wall brackets. Gently lower the mirror until it is securely seated on the brackets.
8. **Test Functionality:** Restore power at the circuit breaker and test all mirror functions.

5. OPERATING INSTRUCTIONS

Your GANPE LED Bathroom Mirror is equipped with several intelligent features for enhanced convenience.

5.1 Power On/Off and Motion Sensor

The mirror features an upgraded human body induction sensor that intelligently turns on the lights when motion is detected within approximately 1.5 meters. The lights will automatically turn off after 2 minutes of no motion.

- **Activate/Deactivate Motion Sensor:** The detection function can be freely activated or deactivated. Refer to the touch controls on the mirror for specific instructions on toggling this feature.
- **Traditional Switch Mode:** If the motion sensor is deactivated, the mirror can be operated using a traditional wall switch or the touch controls on the mirror.



Image: Human body induction motion sensor automatically turns lights on and off.

5.2 Lighting Control (3-Color & Dimmable)

The mirror offers three color temperature options and adjustable brightness to suit various needs and preferences.

- **Color Temperature Selection:** Tap the light control button on the mirror to cycle through 3000K (Warm Light), 4000K (Natural Light), and 6500K (White Light).
- **Brightness Adjustment:** Press and hold the light control button to dim or brighten the LED illumination. Release the button when the desired brightness is achieved.
- **Memory Function:** The mirror remembers your last selected brightness and color temperature settings when turned off and on again.



Image: Adjust color temperature and brightness with touch controls.

5.3 Bluetooth Speaker

Enjoy music with 360-degree surround sound while using your bathroom mirror.

1. **Activate Bluetooth:** Tap the Bluetooth icon on the mirror to turn on the speaker.
2. **Pairing:** On your smartphone or tablet, search for Bluetooth devices and select the mirror's name (e.g., "Mirror Audio"). The default PIN is **6688**.
3. **Play Music:** Once paired, you can play audio from your device through the mirror's speakers.

Bluetooth Speaker



Image: Connect your device via Bluetooth to enjoy music.

5.4 Anti-fog Function

The mirror is equipped with an anti-fog film that activates automatically when the mirror's light is turned on. This ensures a clear reflection even in steamy conditions.

- The defogger film will work with the light.
- The anti-fog function will automatically turn off after 1 hour to conserve energy.

CRI > 95

IP44 Waterproof / ANTI-FOG

The defogger film will work with the light ▲

Enjoy music anytime, anywhere

Image: The anti-fog feature ensures a clear mirror surface.

6. MAINTENANCE

Proper maintenance will ensure the longevity and optimal performance of your mirror.

- **Cleaning the Mirror Surface:** Use a soft, lint-free cloth and a non-abrasive glass cleaner. Spray the cleaner onto the cloth, not directly onto the mirror, to avoid liquid seeping into electrical components.
- **Cleaning the Frame:** Wipe the frame with a soft, damp cloth. Avoid harsh chemicals or abrasive materials that could damage the finish.
- **Electrical Components:** Ensure the mirror is disconnected from power before cleaning any electrical parts. Do not spray water directly onto the mirror's electrical components.
- **Regular Inspection:** Periodically check the mounting hardware for tightness and the electrical connections for any signs of wear or damage.

7. TROUBLESHOOTING

If you encounter issues with your mirror, refer to the following common problems and solutions:

Problem	Possible Cause	Solution
Lights do not turn on.	No power supply; Motion sensor deactivated; Faulty wiring.	Check circuit breaker; Activate motion sensor or use touch control; Consult a qualified electrician.
Bluetooth not connecting.	Bluetooth not activated on mirror; Device not in pairing mode; Incorrect PIN.	Tap Bluetooth icon on mirror; Ensure device Bluetooth is on and discoverable; Enter PIN 6688.
Anti-fog not working.	Mirror light is off; Anti-fog function timed out.	Turn on the mirror light; The anti-fog function automatically turns off after 1 hour.
Motion sensor is too sensitive or not sensitive enough.	Environmental factors; Sensor settings.	Ensure no obstructions near the sensor; Refer to touch control instructions to adjust sensitivity or deactivate if desired.

If the problem persists after attempting these solutions, please contact customer support.

8. SPECIFICATIONS

Brand	GANPE
Model Number	GPHC1025HBI
Dimensions (L x W x H)	91.44 x 71.12 x 0.01 cm (approx. 36 x 28 x 0.004 inches)
Item Weight	9.07 Kilograms (approx. 20 lbs)
Features	LED Illumination, Motion Sensor, Bluetooth Speaker, 3-Color Light (3000K, 4000K, 6500K), Dimmable, Memory Function, Anti-fog, IP44 Waterproof, Copper-free Silver Mirror, CRI 95, Explosion-proof Technology, Horizontal/Vertical Mounting
Type of Mounting	Wall Mount
Room Type	Bathroom

9. WARRANTY INFORMATION

This product comes with a standard manufacturer's warranty. Please refer to the warranty card included in your package or

contact GANPE customer support for detailed warranty terms and conditions. Keep your proof of purchase for warranty claims.

10. CUSTOMER SUPPORT

For technical assistance, troubleshooting, or any questions regarding your GANPE LED Bathroom Mirror, please contact our customer support team. Contact information can typically be found on the product packaging or on the official GANPE website.

When contacting support, please have your model number (GPHC1025HBI) and purchase date ready.