

## Manuals+

[Q & A](#) | [Deep Search](#) | [Upload](#)

manuals.plus /

› [ZOKOP](#) /

› [ZOKOP ALW-J16 Slow Masticating Juicer Instruction Manual](#)

## ZOKOP ALW-J16

# ZOKOP ALW-J16 Slow Masticating Juicer Instruction Manual

Model: ALW-J16

## INTRODUCTION

Thank you for choosing the ZOKOP ALW-J16 Slow Masticating Juicer. This appliance is designed to efficiently extract juice from various fruits and vegetables, preserving nutrients through its slow-speed masticating process. This manual provides essential information for the safe and effective operation, maintenance, and troubleshooting of your juicer.

The ZOKOP ALW-J16 features a 7-spiral masticating system for maximum juice yield and minimal oxidation, ensuring a high retention of vitamins, enzymes, and minerals. Its low-speed operation (80 RPM) reduces heat and friction, resulting in less foaming and no clogging. The small feeder chute design allows for easy seed removal and enhances safety, especially around children.



*Image: The ZOKOP ALW-J16 Slow Masticating Juicer, fully assembled and ready for use, with separate containers for juice and pulp.*

## **IMPORTANT SAFETY INSTRUCTIONS**

Please read all instructions carefully before using the appliance. Failure to follow these instructions may result in electric shock, fire, or serious injury.

- Always unplug the juicer from the power outlet before assembling, disassembling, or cleaning.
- Do not immerse the motor base in water or other liquids.
- Keep hands and utensils away from moving parts during operation to prevent injury.
- Ensure all parts are correctly assembled before operating the juicer.
- Do not operate the appliance with a damaged cord or plug, or after the appliance malfunctions or has been damaged in any manner.
- This appliance is not intended for use by persons (including children) with reduced physical, sensory or mental capabilities, or lack of experience and knowledge, unless they have been given supervision or instruction concerning use of the appliance by a person responsible for their safety.
- Use only attachments recommended or sold by the manufacturer.

- Do not use outdoors.

## SETUP AND ASSEMBLY

Follow these steps to correctly assemble your ZOKOP ALW-J16 Slow Masticating Juicer before first use.

1. **Step 1:** Place the juicing body onto the main motor body, ensuring it clicks securely into place.
2. **Step 2:** Insert the spiral pusher (auger) inside the juicing body.
3. **Step 3:** Place the juice strainer inside the juicing body, aligning it properly.
4. **Step 4:** Attach the squeezer component onto the juicing body.
5. **Step 5:** Place the feeding tray onto the top of the juicing body.
6. **Step 6:** Position the pulp collector cup and the juice jar under their respective outlets on the main body.

# Begin Your Healthy Life



**1** Place the Juicing body on Main body



**2** Put the Spiral pusher inside the Juicing body



**3** Then, place the Juice strainer inside Juicing body



**4** Put the squeezer on



**5** Put the Tray on juicing body



**6** Place the pulp Collector and Juicer Jar



**7** Put in fruits or vegetables



**8** Turn on the juicer and use the push rod to press down the food to squeeze the juice

*Image: A visual guide demonstrating the eight steps for assembling and preparing the juicer for operation, from placing the juicing body to setting up the collection cups.*

## OPERATING INSTRUCTIONS

Once assembled, your juicer is ready for use. Follow these steps for optimal juicing results.

1. **Preparation:** Wash all fruits and vegetables thoroughly. Cut ingredients into pieces small enough to fit into the feeder chute. Remove hard pits, large seeds, and thick peels.
2. **Power On:** Ensure the juicer is properly assembled and the juice jar and pulp collector are in place. Plug the power cord into a suitable electrical outlet. Turn the power switch to the "ON" position.
3. **Juicing:** Gradually feed the prepared fruits or vegetables into the feeder chute. Use the food pusher to gently guide the ingredients down. Do not force ingredients into the chute, as this can damage the motor or clog the juicer.
4. **Reverse Function (R):** If ingredients become jammed, switch the juicer to the "R" (Reverse) position for a few seconds to clear the blockage, then switch back to "ON" to continue juicing.
5. **Completion:** Once juicing is complete, turn the power switch to "OFF" and unplug the appliance from the outlet.

The ZOKOP ALW-J16 operates at a low speed of 80 RPM, which minimizes heat buildup and oxidation, resulting in a higher yield of nutrient-rich juice compared to centrifugal juicers. This slow masticating process ensures that more vitamins, enzymes, and minerals are retained in your juice.

# LOW DECIBEL MOTOR



Less than 60 decibels  
Quiet and Simple to Operate



MASTICATING JUICER

VS

CENTRIFUGAL JUICER



40-60 dbs

Quiet Operation ✓



80-95 dbs

As Loud As Blender ✗

*Image: An illustration comparing the low noise level (40-60 dB) of a masticating juicer like the ZOKOP ALW-J16 to the higher noise level (80-95 dB) of a centrifugal juicer, highlighting its quiet operation.*

## CLEANING AND MAINTENANCE

Regular cleaning and maintenance will ensure the longevity and optimal performance of your juicer. Always unplug the appliance before cleaning.

1. **Disassembly:** Disassemble the juicer by reversing the assembly steps.
2. **Rinsing:** Rinse all removable parts (juicing body, spiral pusher, strainer, squeezer, tray, juice jar, pulp collector) under running water immediately after use to prevent pulp from drying and sticking.
3. **Washing:** Wash the removable parts with warm, soapy water using a brush to clean the strainer thoroughly. All removable parts are dishwasher safe for convenience.
4. **Motor Base:** Wipe the motor base with a damp cloth. Never immerse the motor base in water or any other liquid.
5. **Drying and Storage:** Dry all parts completely before reassembling or storing the juicer. Store in a clean, dry

place.

## TROUBLESHOOTING

If you encounter issues with your ZOKOP ALW-J16 Juicer, refer to the following common problems and solutions:

Problem	Possible Cause	Solution
Juicer does not turn on.	Not plugged in; power switch off; improper assembly.	Ensure power cord is securely plugged in. Turn power switch to "ON". Check if all parts are correctly assembled and locked.
Juicer stops during operation or jams.	Too much food fed at once; hard ingredients; pulp buildup.	Switch to "R" (Reverse) for a few seconds, then back to "ON". Reduce the amount of food fed at one time. Cut hard ingredients into smaller pieces. Clean the juicer if pulp buildup is significant.
Excessive vibration or noise.	Improper assembly; uneven surface.	Ensure all parts are correctly assembled and locked. Place the juicer on a stable, flat surface.
Low juice yield or wet pulp.	Strainer clogged; ingredients too soft or overripe.	Clean the strainer thoroughly. Alternate between soft and hard ingredients. Ensure ingredients are fresh.

If the problem persists after attempting these solutions, please contact customer support.

## PRODUCT SPECIFICATIONS

Below are the technical specifications for the ZOKOP ALW-J16 Slow Masticating Juicer:

**Model:** ALW-J16

**Brand:** ZOKOP

**Power:** 150W

**Voltage:** 120V

**Juice Cup Capacity:** 800ml

**Pulp Collector Capacity:** 1000ml

**Material:** Plastic

**Special Feature:** Portable

**Product Care:** Dishwasher Safe parts

**UPC:** 718255027924

**ASIN:** B097HLVQLZ



5\*3.8cm

Wide Mouth Feeder Chute

150W

Powerful Motor

100%

Natural Juice

1000ml

Juicer Jug Volume

800ml

Pulp Collector Volume

*Image: A detailed view of the ZOKOP ALW-J16 Juicer, illustrating key specifications such as the wide mouth feeder chute dimensions, 150W motor, and the capacities of the juice jug (1000ml) and pulp collector (800ml).*

## WARRANTY AND SUPPORT

For warranty information or technical support, please refer to the documentation included with your purchase or contact ZOKOP customer service directly. Keep your purchase receipt as proof of purchase for any warranty claims.

For further assistance, you may visit the official ZOKOP website or contact their customer support channels.