

[Manuals.plus](#) /

> [UME](#) /

> UME LED Outdoor Indoor Wall Lantern Instruction Manual

## UME B0986GT2TX



# UME 2 Pack LED Outdoor Indoor Wall Lantern

INSTRUCTION MANUAL - MODEL B0986GT2TX

## 1. Product Overview

The UME LED Outdoor Indoor Wall Lantern is designed to provide efficient and durable lighting for various outdoor and indoor applications. This fixture features an integrated LED light source, ensuring long-term performance and energy savings. Its robust construction is engineered to withstand diverse weather conditions.



Image 1.1: Two UME LED Outdoor Indoor Wall Lanterns, showcasing their black finish and modern design.

### Key Features:

- **Weather Resistant:** Constructed with heavy-duty aluminum and plastic to prevent rust and corrosion, suitable for various weather conditions including rain, snow, and heat.
- **Energy Saving:** Features integrated 9W LED, offering significant electricity cost savings and an average lifespan of 60,000 hours.
- **Durable Construction:** Made with high-quality aluminum and anti-rust plastic, finished in matte black for a modern aesthetic.
- **Easy Installation:** Includes all necessary wall mounting accessories for quick setup.

## 2. Safety Information

Please read all instructions carefully before installation and operation. Failure to follow these instructions may result in electric shock, fire, or other hazards.

- Always disconnect power at the circuit breaker before installing, servicing, or cleaning the fixture.

- Installation must be performed by a qualified electrician or in accordance with local electrical codes.
- Ensure the mounting surface can support the weight of the fixture.
- Do not attempt to modify the integrated LED light source. It is not replaceable.
- Keep packaging materials away from children.

### 3. Package Contents

Verify that all components are present and undamaged before beginning installation. If any parts are missing or damaged, contact customer support.

- UME LED Wall Lantern (2 units)
- Mounting Hardware (includes 6 x 10AWG Wire Connectors, 4 x M4-25 Phillips Head Screws)



Image 3.1: Diagram showing product dimensions (5.62"L x 4.84"W x 6.89"H) and included mounting accessories.

## 4. Specifications

Detailed technical specifications for the UME LED Wall Lantern.

Specification	Value
Brand	UME
Model	B0986GT2TX
Color	Black
Material	Polycarbonate, Aluminum (ADC12)
Style	Modern
Light Fixture Form	Sconce
Product Dimensions	5.62"L x 4.84"W x 6.89"H
Indoor/Outdoor Usage	Indoor/Outdoor
Power Source	Corded Electric
Installation Type	Wall Mount
Special Feature	Waterproof
Light Source Type	Integrated LED
Voltage	120 Volts
Wattage	9 watts
Brightness	800 lumen
Color Temperature	3000 Kelvin
Shade Material	Polycarbonate (Opal PC Diffuser)
Assembly Required	Yes
Item Weight	2.92 pounds (per unit)



## Specifications

Voltage	120V/60HZ
Wattage	9W
Color Temp	3000K
Features	Opal PC Diffuser
Bulb	Led bulb, could not change
Warranty	3 Year



Image 4.1: The UME Wall Lantern, indicating the use of ADC12 Aluminum and Opal PC for its construction.

## 5. Setup and Installation

Follow these steps for proper installation. It is recommended to consult a qualified electrician if you are unsure about any part of the process.

### 1. Prepare for Installation:

- Turn off power at the circuit breaker to the outlet box where the fixture will be installed.
- Ensure the power is completely off before proceeding.

### 2. Mount the Fixture:

- Attach the mounting bracket (if separate) to the electrical junction box using the provided screws.

- Ensure the bracket is securely fastened and level.

### 3. Wire the Fixture:

- Connect the fixture's wires to the corresponding wires from the junction box using the provided wire connectors:
  - Black (Live) to Black (Live)
  - White (Neutral) to White (Neutral)
  - Green or Bare Copper (Ground) to Green or Bare Copper (Ground)
- Ensure all connections are secure.

### 4. Secure the Fixture:

- Carefully tuck all wires into the junction box.
- Align the fixture with the mounting bracket and secure it using the remaining screws.

### 5. Restore Power:

- Once the fixture is securely installed, turn the power back on at the circuit breaker.
- Test the light to ensure it functions correctly.

For a visual guide, you may refer to the official Installation Manual (PDF) available at [UME Installation Manual](#)

## 6. Operating Instructions

The UME LED Wall Lantern operates via a standard wall switch. There are no complex controls or settings required.

### 1. Turning On/Off:

- Use the wall switch connected to the fixture to turn the light on or off.

### 2. Light Output:

- The integrated 9W LED provides 800 lumens of bright, warm white light (3000 Kelvin).
- The light output is fixed and cannot be adjusted.



Image 6.1: UME Wall Lanterns providing illumination for an outdoor patio area.

## 7. Maintenance

The UME LED Wall Lantern is designed for minimal maintenance due to its durable construction and integrated LED technology.

- **Cleaning:**

- Before cleaning, ensure the power is off at the circuit breaker.
- Wipe the fixture with a soft, damp cloth. Do not use abrasive cleaners or solvents, as they may damage the finish or polycarbonate diffuser.

- **LED Longevity:**

- The integrated LED has an estimated lifespan of 60,000 hours and does not require bulb replacement.

- **Weather Resistance:**

- The fixture is designed to be waterproof and anti-rust. Periodically inspect for any debris accumulation, especially in the conical lampshade, and clear as needed to maintain optimal performance.



Image 7.1: Visual representation of the UME Wall Lantern's waterproof, heat resistance, snowproof, and anti-rust properties.

**Ours** 😊



**High Quality Aluminum**

**Opal PC diffuser**

**Anti-rust**

**Waterproof**



😞 **Others**



Inferior Quality Metal

Fragile Thin Glass

Easy to Rust

Not Waterproof



Image 7.2: Comparison highlighting the superior quality aluminum and Opal PC diffuser of UME lanterns against inferior metal and fragile glass of other products, emphasizing anti-rust and waterproof features.

## 8. Troubleshooting

If you encounter issues with your UME LED Wall Lantern, refer to the following common problems and solutions:

Problem	Possible Cause	Solution
Light does not turn on.	No power to the fixture, loose wiring, faulty switch.	Check circuit breaker. Ensure all wire connections are secure. Test the wall switch.

Problem	Possible Cause	Solution
Light flickers.	Loose wiring, incompatible dimmer switch (though not designed for dimming).	Check wire connections. Ensure a standard on/off switch is used.
Bugs accumulating inside the fixture.	Small gaps allowing insect entry.	While the design aims to be sealed, small insects may find entry. Periodically clean the interior if accessible, or consider sealing minor gaps with clear silicone sealant if necessary.
Fixture does not sit flush on recessed boxes.	Design not optimized for deeply recessed electrical boxes.	This fixture is designed for surface wall mount applications. If your electrical box is deeply recessed, additional spacers or a different mounting solution may be required, or the fixture may not be suitable for that specific installation.

If the problem persists after attempting these solutions, please contact UME customer support.

## 9. Warranty and Support

UME stands behind the quality of its products.

- **Warranty:** This product comes with a **3-Year Warranty** from the date of purchase, covering defects in materials and workmanship.
- **Customer Support:** We provide 24/7 after-sales service. For any questions, concerns, or warranty claims regarding your UME LED Wall Lantern, please feel free to contact us.
- **Contact Information:** Please refer to the contact details provided on the product packaging or the official UME website for support.