

NEDIS WIFIP121FWT

NEDIS SmartLife WLAN Smart Plug User Manual

Model: WIFIP121FWT

1. INTRODUCTION

Thank you for choosing the NEDIS SmartLife WLAN Smart Plug. This device allows you to control electrical appliances remotely, monitor power consumption, and automate your home using the intuitive SmartLife app or voice commands via Amazon Alexa, Google Home, or Siri. This manual provides essential information for safe and efficient use of your smart plug.

Package Contents:

- 1 x NEDIS SmartLife Smart Plug (Model: WIFIP121FWT)



Image: Front view of the NEDIS SmartLife WLAN Smart Plug, showing the socket and the power button on top.

2. SAFETY INFORMATION

Please read these safety instructions carefully before using the product.

- Do not disassemble or modify the device.
- Do not expose the device to water or high humidity.
- Use the device only indoors.
- Ensure the connected appliance's power consumption does not exceed 3680 W.
- Keep out of reach of children.
- Unplug the device from the wall socket before cleaning.

3. SETUP

3.1. App Installation

The NEDIS SmartLife Smart Plug operates with the SmartLife app.

1. Download the "SmartLife" app from the App Store (iOS) or Google Play Store (Android).

2. Register a new account or log in if you already have one.

3.2. Connecting the Smart Plug

Follow these steps to connect your smart plug to your Wi-Fi network:

1. Plug the NEDIS SmartLife Smart Plug into a standard wall socket.
2. Open the SmartLife app on your smartphone or tablet.
3. Tap the "+" icon in the top right corner to add a device.
4. Select "Electrical Outlet" or "Smart Plug" from the device list.
5. Confirm that the indicator light on the smart plug is blinking rapidly. If not, press and hold the power button on the plug for 5-10 seconds until it blinks rapidly.
6. Enter your Wi-Fi network name and password in the app. Ensure you are connected to a 2.4 GHz Wi-Fi network.
7. The app will begin connecting to the device. Once connected, the indicator light on the plug will stop blinking and remain solid.
8. You can now rename your smart plug within the app for easier identification (e.g., "Living Room Lamp").



Image: The smart plug shown in a home environment, with a smartphone displaying the SmartLife app's control interface, indicating remote control capabilities.

4. OPERATING INSTRUCTIONS

4.1. Basic On/Off Control

You can turn the connected appliance on or off directly from the SmartLife app by tapping the power icon next to the device name.

4.2. Scheduling and Timers

Automate your devices by setting schedules or timers:

- **Schedule:** Set specific times for the plug to turn on or off daily or on selected days of the week.
- **Timer:** Set a countdown timer for the plug to turn off after a certain duration.
- **Circulate:** Configure the plug to cycle on and off at set intervals.
- **Random:** Turn the plug on and off randomly within a set period, useful for simulating occupancy.

4.3. Power Consumption Monitoring

The integrated power meter allows you to monitor the real-time and historical power consumption of the connected appliance.

1. In the SmartLife app, select your smart plug.
2. Look for the "Power Statistics" or "Energy Monitoring" section.
3. Here you can view current power usage (in Watts) and historical data (daily, monthly consumption).



Image: The smart plug connected to a wall outlet, with a smartphone screen showing the energy monitoring feature of the SmartLife app, displaying real-time power consumption.

4.4. Voice Control Integration

The NEDIS SmartLife Smart Plug is compatible with Amazon Alexa, Google Home, and Siri for voice control.

1. For Amazon Alexa:

- Open the Alexa app, go to "Skills & Games", search for "SmartLife".
- Enable the SmartLife skill and link your SmartLife account.
- Discover devices. You can now say, "Alexa, turn on [Plug Name]".

2. For Google Home:

- Open the Google Home app, tap "Add" > "Set up device" > "Works with Google".
- Search for "SmartLife", link your SmartLife account.
- You can now say, "Hey Google, turn off [Plug Name]".

3. For Siri (Shortcuts):

- In the SmartLife app, go to the device settings.
- Look for "Siri Shortcuts" or "Add to Siri".
- Record a custom phrase for specific actions (e.g., "Hey Siri, turn on my lamp").

5. MAINTENANCE

To ensure optimal performance and longevity of your smart plug:

- Clean the device with a soft, dry cloth. Do not use liquid or aerosol cleaners.
- Store the device in a cool, dry place when not in use.
- Avoid exposing the device to extreme temperatures or direct sunlight.

6. TROUBLESHOOTING

Problem	Possible Cause	Solution
Smart plug cannot connect to Wi-Fi.	Incorrect Wi-Fi password; 5 GHz Wi-Fi network; plug too far from router.	Double-check password. Ensure your phone is connected to a 2.4 GHz Wi-Fi network. Move the plug closer to the router. Reset the plug by holding the power button until it blinks rapidly.
Device is offline in the app.	Wi-Fi signal loss; power outage; plug unplugged.	Check Wi-Fi router and internet connection. Ensure the plug is securely plugged in and powered. Re-add the device if necessary.
Voice control not working.	Incorrect skill/action enabled; device name mismatch; internet connection issue.	Verify SmartLife skill/action is enabled and linked. Ensure the device name used in voice command matches the app. Check internet connection.
Power consumption data is inaccurate.	Temporary software glitch.	Unplug the smart plug for 10 seconds and plug it back in. Restart the SmartLife app.

7. SPECIFICATIONS

Feature	Specification
Model Number	WIFIP121FWT
Brand	NEDIS
Color	White
Dimensions (L x W x H)	6.3 x 10.7 x 12.7 cm
Weight	50 g
Input Voltage	220-240 V AC
Max Current	16 A
Max Power	3680 W
Wireless Technology	Wi-Fi 2.4 GHz
Operating Mode	ON-OFF
Compatibility	Amazon Alexa, Google Home, Siri

8. WARRANTY AND SUPPORT

NEDIS products are manufactured to high quality standards. In the unlikely event of a defect during the warranty period, please contact your retailer for support.

For further assistance, technical support, or to view the full warranty terms, please visit the official NEDIS website or contact their customer service.

Online Support: www.nedis.com/support