

Manuals+

[Q & A](#) | [Deep Search](#) | [Upload](#)

[manuals.plus](#) /

› [MEIXISUE](#) /

› [MEIXISUE C2130-6 Black Modern Sputnik 6-Light Semi Flush Mount Ceiling Light Instruction Manual](#)

MEIXISUE C2130-6

MEIXISUE C2130-6 Black Modern Sputnik 6-Light Semi Flush Mount Ceiling Light Instruction Manual

Model: C2130-6

Brand: MEIXISUE

PRODUCT OVERVIEW

The MEIXISUE C2130-6 is a modern Sputnik-style semi-flush mount ceiling light designed to enhance various indoor spaces such as bedrooms, living rooms, dining rooms, and kitchens. Its distinctive design features six black metal arms with gold-finished bulb sockets, creating a contemporary aesthetic.



Image: The MEIXISUE C2130-6 ceiling light fixture with Edison bulbs, showcasing its modern design in a living space.

1. SAFETY INFORMATION

Please read and understand this entire manual before attempting to assemble, operate, or install the product. Failure to do so could lead to electric shock, fire, or other injuries that could be fatal or cause serious damage.

- Always turn off the power at the main circuit breaker panel and disconnect the main power supply before installation.
- Consult a qualified electrician if you have any electrical questions.
- This fixture is intended for indoor use only.
- Do not exceed the maximum wattage for bulbs (60W per bulb, total 360W).
- Ensure all electrical connections are secure and comply with local codes and ordinances.
- Handle glass components with care.

2. PACKAGE CONTENTS

Carefully unpack all components and inspect for any damage. Ensure all parts are present before beginning installation.

- Mounting Bracket (1)
- Canopy (1)
- Fixture Body with 6 Arms (1)
- Mounting Screws (2)
- Wire Nuts (3)
- Ground Screw (1)
- Instruction Manual (1)



Image: Detailed view of the fixture's components, showing the black metal base, connecting arms, and gold-colored bulb holders. This illustrates the parts included in the light kit.

3. SPECIFICATIONS

Brand	MEIXISUE
Model Name	C2130-6
Color	Black

Material	Metal
Style	Modern
Light Fixture Form	Semi Flush Mount
Product Dimensions	7.87"L x 28.74"W x 7.87"H
Number of Light Sources	6
Bulb Base	E26
Maximum Wattage (per bulb)	60 Watts
Voltage	110 Volts
Installation Type	Ceiling Light
Certification	UL Listed
Indoor/Outdoor Usage	Indoor use only



Image: Product dimensions diagram, illustrating the overall size of the fixture (7.87"H x 28.74"W).

4. SETUP AND INSTALLATION

Before starting, ensure the power is turned off at the circuit breaker. This fixture is designed for easy installation, with pre-wired branches.

1. **Prepare the Mounting:** Attach the mounting bracket to your ceiling's electrical box using the provided mounting screws.
2. **Assemble the Fixture Body:** The fixture's branches are pre-wired. Carefully connect and fix each branch to the central body as per the instructions provided in the package. Ensure all connections are secure.
3. **Electrical Connections:** Connect the fixture's wires to your household electrical wires. Typically, connect the black wire from the fixture to the black wire from the outlet box, the white wire from the fixture to the white wire from the outlet box, and the ground wire to the ground wire. Use wire nuts to secure connections.
4. **Mount the Canopy:** Carefully push the canopy up to the ceiling, covering the electrical box and mounting bracket. Secure it in place with the provided screws or nuts.
5. **Install Bulbs:** Screw E26 base bulbs (not included) into each of the 6 sockets. Do not exceed 60W per bulb.
6. **Restore Power:** Once installation is complete and all connections are secure, restore power at the main circuit breaker.

Your browser does not support the video tag.

Video: An overview of the MEIXISUE C2130-6 ceiling light fixture, demonstrating its modern design and ease of installation. This video highlights the product's features and how it appears once installed.

5. OPERATING INSTRUCTIONS

This MEIXISUE C2130-6 ceiling light operates like a standard light fixture. Once properly installed and powered, it can be controlled via a wall switch (not included).

- **Turning On/Off:** Use the wall switch connected to the fixture to turn the light on or off.
- **Bulb Compatibility:** The fixture is compatible with E26 base bulbs, including LED, energy-saving, and halogen bulbs, up to a maximum of 60W per bulb.
- **Dimmable Functionality:** If a dimmer switch is installed and compatible dimmable bulbs are used, the light output can be adjusted.

6. MAINTENANCE

Regular maintenance will help preserve the appearance and functionality of your light fixture.

- **Cleaning:** Always turn off the power before cleaning. Wipe the fixture with a soft, dry cloth. Do not use abrasive cleaners or solvents as they may damage the finish.
- **Bulb Replacement:** Ensure the power is off and bulbs have cooled before replacing. Unscrew the old bulb and screw in a new E26 base bulb (max 60W).
- **Inspection:** Periodically check all connections and mounting hardware to ensure they remain secure.

7. TROUBLESHOOTING

Problem	Possible Cause	Solution
Light does not turn on.	Power is off. Loose wire connections. Faulty bulb.	Check circuit breaker and wall switch. Turn off power, check and secure all wire connections. Replace bulb with a new one.
Light flickers.	Loose bulb. Incompatible dimmer switch/bulbs.	Tighten bulb securely. Ensure dimmer switch and bulbs are compatible for dimming.
Fixture is unstable.	Loose mounting.	Turn off power, check and tighten all mounting screws.

8. WARRANTY AND SUPPORT

The MEIXISUE C2130-6 Black Modern Sputnik 6-Light Semi Flush Mount Ceiling Light comes with a **3-year product warranty**.

If you have any questions, suggestions, or require assistance with your product, please do not hesitate to contact MEIXISUE customer support. We are available 24 hours a day to ensure your satisfaction.

Your satisfaction with home decoration is our greatest pursuit.