

## Inrico T529A

# Inrico T529A 4G LTE POC Radio User Manual

Model: T529A

## 1. INTRODUCTION

---

This user manual provides comprehensive instructions for the operation, maintenance, and troubleshooting of your Inrico T529A 4G LTE POC Radio. Please read this manual thoroughly before using the device to ensure proper functionality and safety.

The Inrico T529A is a robust 4G LTE Push-to-Talk Over Cellular (POC) radio designed for professionals and outdoor enthusiasts, offering long-range communication, water resistance, and integration with Bluetooth and Wi-Fi networks.

## 2. PRODUCT OVERVIEW

---

Familiarize yourself with the components and controls of your T529A radio.



**Figure 2.1:** Front and Back View of T529A Radio with Labeled Components.

This image displays the Inrico T529A radio from both the front and back. Key components labeled include the antenna, group selector knob, switch/volume knob, microphone, lanyard hole, belt clip, battery compartment, and charging contacts at the bottom.



**Figure 2.2:** Side View of T529A Radio with Labeled Interfaces and Buttons.

This image shows the side profiles of the Inrico T529A radio. Labeled interfaces include the microphone interface, earphone jack, and USB interface. On the opposite side, the Push-to-Talk (PTT) button, recording playback & individual call button, and a user-defined button are clearly marked.

## 2.1 Package Contents

Upon unboxing, verify that all items are present:

- 1 x Inrico T529A Radio
- 1 x Antenna
- 1 x Battery
- 1 x Charging Dock
- 1 x Power Adapter
- 1 x Belt Clip
- 1 x Lanyard
- 1 x User Manual (this document)



Figure 2.3: Inrico T529A Package Contents.

This image displays all items typically included in the Inrico T529A radio package. It shows the radio unit, its charging dock, a removable battery, the antenna, a belt clip, a lanyard, the power adapter, and the printed user manual.

## 3. SETUP AND INITIAL USE

### 3.1 Battery Installation and Charging

1. **Install Battery:** Align the battery with the battery compartment on the back of the radio. Gently push down until it clicks into place.
2. **Attach Antenna:** Screw the antenna clockwise into the connector on the top of the radio until it is finger-tight.
3. **Initial Charge:** Place the radio into the charging dock. Connect the power adapter to the charging dock and plug it into a power outlet. The charging indicator light on the dock will illuminate (typically red) during charging and change color (typically green) when fully charged.
4. **First Use:** For optimal battery life, fully charge the battery before the first use.



**Figure 3.1:** Inrico T529A in Charging Dock.

This image shows the Inrico T529A radio securely seated in its dedicated charging dock. The radio's antenna is attached, and the dock appears ready for connection to a power source.

## 3.2 Powering On/Off

- **Power On:** Rotate the Switch/Vol knob clockwise until you hear a click and the radio powers on.
- **Power Off:** Rotate the Switch/Vol knob counter-clockwise until you hear a click and the radio powers off.

## 3.3 Network Connection (SIM Card / Wi-Fi)

The T529A operates on 4G LTE networks and supports Wi-Fi connectivity. A SIM card is required for cellular network operation.

- **SIM Card Installation:** (Refer to specific instructions for SIM card slot access, usually under the battery or a dedicated slot). Insert a valid 4G LTE SIM card into the designated slot.
- **Wi-Fi Connection:** Navigate to the radio's settings menu (if applicable, via screen or companion app) to connect to a Wi-Fi network.

## 4. OPERATING INSTRUCTIONS

---

### 4.1 Adjusting Volume

Rotate the Switch/Vol knob clockwise to increase volume and counter-clockwise to decrease volume.

### 4.2 Selecting Channels/Groups

Rotate the Group Selector knob to switch between available channels or talk groups. The radio will typically announce the selected group or display it on a screen if available.

### 4.3 Push-to-Talk (PTT) Operation

1. **To Transmit:** Press and hold the PTT button (located on the side of the radio). Speak clearly into the microphone.
2. **To Receive:** Release the PTT button to listen for incoming transmissions.
3. **Important:** Wait for the channel to be clear before transmitting. Do not interrupt ongoing conversations.

### 4.4 Bluetooth Connectivity

The T529A supports Bluetooth for connecting compatible accessories like headsets.

1. **Enable Bluetooth:** Access the radio's settings menu to turn on Bluetooth.
2. **Pairing:** Put your Bluetooth accessory into pairing mode. Select the accessory from the list of available devices on the radio's screen (if applicable) or follow the radio's pairing prompts.





**Figure 4.1:** T529A Features Overview.

This image highlights key features of the Inrico T529A radio, including GPS for location services, Wi-Fi for network connectivity, Bluetooth for wireless accessories, and an SOS function for emergency signaling.

## 5. MAINTENANCE AND CARE

---

- **Cleaning:** Use a soft, damp cloth to clean the radio's exterior. Do not use harsh chemicals or abrasive cleaners.
- **Battery Care:** Avoid overcharging or completely draining the battery. Store the radio and battery in a cool, dry place when not in use for extended periods.
- **Water Resistance:** The T529A is water-resistant (IP65 rated). While it can withstand splashes and light rain, do not submerge it in water. Ensure all port covers are securely closed to maintain water resistance.
- **Antenna:** Do not bend or modify the antenna. A damaged antenna can affect communication range.

## 6. TROUBLESHOOTING

---

Problem	Possible Cause	Solution
Radio does not power on.	Battery is low or not installed correctly.	Charge the battery. Reinstall the battery, ensuring it clicks into place.
Cannot transmit or receive.	No network signal; incorrect group selected; PTT button not pressed correctly.	Check network signal strength. Verify the correct group is selected. Ensure PTT button is fully pressed and held during transmission.
Poor audio quality.	Weak signal; microphone/speaker obstructed; volume too low/high.	Move to an area with better signal. Clear any obstructions. Adjust volume.
Bluetooth device won't pair.	Bluetooth not enabled; device not in pairing mode; out of range.	Ensure Bluetooth is enabled on radio. Put accessory in pairing mode. Move devices closer.

## 7. SPECIFICATIONS

Feature	Detail
Model Number	T529A
Dimensions (L x W x H)	5.31 x 2.36 x 1.46 inches
Connectivity	4G LTE, Wi-Fi, Bluetooth
Water Resistance Level	IP65 (Water Resistant)
Included Components	Radio, Antenna
Special Features	Long Range, Portable, Voice Operated Transmission, Waterproof
Operating System	Android 7.1

## 8. WARRANTY AND SUPPORT

For warranty information and technical support, please refer to the warranty card included with your product or visit the official Inrico website. You may also contact your point of purchase for assistance.

**Manufacturer:** INRICO

**Contact:** Refer to [Inrico Store on Amazon](#) or official Inrico channels for support.





[pdf] Specifications Accessories

SpecSheet GoRugged 529A Inrico 529A GoRuggedThe Inrico T529A will ensure that all our hardware are 4G LTE capable for the first time ever! This unit is an excellent upgrade from T199 so your specsheet gorugged 529gorugged co za pf 667ab6c07ff10 specsheetsheet 529 srsltid AfmBOopdy4pSBY junBDDm7hHIO6oRvd74gk rJYl 9rGJFKZyUzLhvH GoRuggedinrico your The 529v1gorugged 9rGJFKZyUzLhvHgorugged AfmBOooAKoFht4V Cwv5 ok6Abc 7XThNHmg gbbELG7z3eDBHg5Og8w 529specsheetsheet AfmBOorAI7RMIAOlCfXxROf14GRGpvJG4DaS84tPwNS20gdlw8OeGT3Xgorugged ||| ||| INRICO T529A INRICO T529A The Inrico T529A will ensure that all our hardware are 4G/LTE capable for the first time ever This unit is an excellent upgrade from the T199 so all your T199 accessories such as batteries and cradles will work on ||| INRICO T529A INRICO T529A The Inrico T529A will ensure that all our hardware are 4G/LTE capable for the first time ever This unit is an excellent upgrade from the T199 so all your T199 accessories such as batteries and cradles will work on ||| INRICO T529A INRICO T529A The Inrico T529A will ensure that all our hardware are 4G/LTE capable for the first time ever This unit is an excellent upgrade from the T199 so all your T199 accessories such as batteries and cradles will work on the T529A. Only the antenna is different from the T199 due...

lang:en score:40 filesize: 535.15 K page\_count: 2 document date: 2024-06-25

[pdf] Test Report



Inrico Technologies Co Ltd T529A 2AIV6 2AIV6T529A 529a  
FEDERAL COMMUNICATION COMMISSION Laboratory Division 7435 Oakland Mills Road Columbia, MD 21046 June ... ass: PCB-PCS Licensed Transmitter Applicant Name: Shenzhen Inrico Electronics Co.,Ltd FCC ID: 2AIV6-T529A TCB Name: Bay Area Compliance Laboratory Corp. Confirmation Number: TC141669 Dear Sir or Mada...


lang:en score:38 filesize: 10.81 K page\_count: 2 document date: 2021-06-29

[pdf] Test Report

Microsoft Word Attestation letter dg06157 Letter Inrico Technologies Co Ltd T529A Intelligent Two Way Radio 2AIV6 2AIV6T529A 529a  
Shenzhen Inrico Electronics Co.,Ltd ADD: 3/F, Building No.118, High Tech Industrial Park, 72 Guowei ... eport generation for the following project s : Product name: Intelligent Two Way Radio, Model name: T529A,FCC ID:2AIV6-T529A The chipset MT6739V supports LTE Band, But only Band2/4/5/7/12/17/38/40/66 ...

lang:en score:35 filesize: 157.66 K page\_count: 1 document date: 2020-08-21





263 Walsall Road, Great Wyrley, Walsall, WS6 6DL  
Established 1997. Open Monday - Friday 9am - 5pm and Saturday 9.30am - 4pm  
Tel: 01922 414 796 Fax: 01922 417829 Skype: radioworld\_uk



Inrico T529A 4G Network Handheld Radio with NFC  
£149.99

DESCRIPTION  
The T529A is a compact and robust POC (Push-to-Talk) radio that stands out for its impressive performance relative to its price. Designed for ease of use, it incorporates a Micro USB port, simplifying the programming and setup process compared to other models in the market. This feature lets users connect the radio to a computer for quick configuration, making it an ideal choice for casual and professional users. One of the notable advantages of the T529A is its compatibility with free software that simulates a screen on your PC. This functionality enables users to install PTT applications like Zello easily. Once set up, the software can auto-start upon booting the computer, ensuring the radio is always ready for immediate communication. This streamlined setup process enhances user experience and efficiency. The T529A package includes everything needed: a handheld radio, a 4G LTE antenna for optimal connectivity, a battery, a belt clip for easy carrying, and a charger dock with a plug. This comprehensive bundle ensures users can rely on the T529A for effective communication in various environments. It is a valuable tool for teams that require dependable and quick access to PTT capabilities.

[pdf] Installation Guide

Inrico T529A 4G Network Handheld Radio with NFC £149 99 Designed for ease of use it incorporates a Micro USB port simplifying the programming and setup process compared to other models in market This product 19141756 v 1747940244 shopwired business files s3 eu west 1 amazonaws 7 226987 s ||| 263 Walsall Road, Great Wyrley, Walsall, WS6 6DL Established 1997. Open Monday - Friday 9am - 5pm and Saturday 9.30am - 4pm Tel: 01922 414 796 Fax: 01922 417829 Skype: radioworld\_uk Inrico **T529A** 4G Network Handheld Radio with NFC 149.99 DESCRIPTION The **T529A** is a compact and robust POC Push-to-Talk... lang:en score:31 filesize: 215.97 K page\_count: 1 document date: 2025-05-25



263 Walsall Road, Great Wyrley, Walsall, WS6 6DL  
Established 1997. Open Monday - Friday 9am - 5pm and Saturday 9.30am - 4pm  
Tel: 01922 414 796 Fax: 01922 417829 Skype: radioworld\_uk




Inrico T529A 4G Network Handheld Radio with NFC  
£149.99


DESCRIPTION  
The T529A is a compact and robust POC (Push-to-Talk) radio that stands out for its impressive performance relative to its price. Designed for ease of use, it incorporates a Micro USB port, simplifying the programming and setup process compared to other models in the market. This feature lets users connect the radio to a computer for quick configuration, making it an ideal choice for casual and professional users. One of the notable advantages of the T529A is its compatibility with free software that simulates a screen on your PC. This functionality enables users to install PTT applications like Zello easily. Once set up, the software can auto-start upon booting the computer, ensuring the radio is always ready for immediate communication. This streamlined setup process enhances user experience and efficiency. The T529A package includes everything needed: a handheld radio, a 4G LTE antenna for optimal connectivity, a battery, a belt clip for easy carrying, and a charger dock with a plug. This comprehensive bundle ensures users can rely on the T529A for effective communication in various environments. It is a valuable tool for teams that require dependable and quick access to PTT capabilities.

[pdf] Installation Guide

Inrico T529A 4G Network Handheld Radio with NFC £149 99 Designed for ease of use it incorporates a Micro USB port simplifying the programming and setup process compared to other models in market This product 19141756 v 1747164564 shopwired business files s3 eu west 1 amazonaws 7 226987 s ||| 263 Walsall Road, Great Wyrley, Walsall, WS6 6DL Established 1997. Open Monday - Friday 9am - 5pm and Saturday 9.30am - 4pm Tel: 01922 414 796 Fax: 01922 417829 Skype: radioworld\_uk Inrico **T529A** 4G Network Handheld Radio with NFC 149.99 DESCRIPTION The **T529A** is a compact and robust POC Push-to-Talk... lang:en score:31 filesize: 215.97 K page\_count: 1 document date: 2025-05-19



POC RADIO  
IN TOUCH TIMELY EVERYWHERE





**T529A**  
Instructions

Phone: +44 (0)1922 414 796 Fax: +44 (0)1922 417829 Skype: radioworld\_uk

Inrico T529A POC Radio User Manual: Operation, Features, and Specifications

This user manual provides comprehensive instructions for the Inrico T529A POC radio, covering unpacking, setup, basic functions, advanced features, troubleshooting, system parameters, and specifications. Learn how to operate your Inrico T529A for reliable communication. lang:en score:30 filesize: 4.16 M page\_count: 9 document date: 2021-12-31

SAR EVALUATION REPORT


For

Shenzhen Inrico Electronics Co.,Ltd

3/F, Building No.118, High Tech Industrial Park, 72 Guowei Road, Luohu District, Shenzhen China

FCC ID: 2AIV6-T529A

Report Type: Original Report	Product Type: Intelligent Two Way Radio
---------------------------------	--



Report Number: RDG200407009-20	
Report Date: 2020-08-14	
Reviewed By: Rocky Xiao RF Engineer	
Prepared By: Ray Asia Compliance Laboratories Corp. (Dongguan) 3rd/F, Pingliang, Pingliang Industry Area, Tangxia, Dongguan, Guangdong, China Tel: +86-769-88050091 Fax: +86-769-88050092 www.bacel.com.cn	

\*Note: This report is prepared for the customer (here shown) and for the device described herein. It may not be reproduced or used in part without prior reference to the Ray Asia Compliance Laboratories Corp. (Dongguan).  
This report and its use by the customer is subject to the conditions, agreement or endorsement by BACL as the agent of the Public Government. \* This report may contain data that is not covered by the BACL Accreditation and is subject to its audit.

[pdf] Test Report SAR Rating

Microsoft Word SAR Report RDG200407009 20 dg06237 Inrico Technologies Co Ltd T529A Intelligent Two Way Radio 2AIV6 2AIV6T529A t529a

SAR EVALUATION REPORT For Shenzhen Inrico Electronics Co.,Ltd 3/F, Building No.118, High Tech Industrial Park, 72 Guowei Road, Luohu District, Shenzhen China  
FCC ID: 2AIV6-**T529A** Report Type: Original Report Product Type: Intelligent Two Way Radio Report Number: RDG200407009-20 Report Date: 2020-...  
lang:en score:25 filesize: 1.05 M page\_count: 70 document date: 2020-08-20

SAR EVALUATION REPORT


For

Shenzhen Inrico Electronics Co.,Ltd

3/F, Building No.118, High Tech Industrial Park, 72 Guowei Road, Luohu District, Shenzhen China

FCC ID: 2AIV6-T529A

Report Type: Original Report	Product Type: Intelligent Two Way Radio
---------------------------------	--

Report Number: RDG200407009-20	
Report Date: 2020-08-14	
Reviewed By: Rocky Xiao RF Engineer	
Prepared By: Ray Asia Compliance Laboratories Corp. (Dongguan) 3rd/F, Pingliang, Pingliang Industry Area, Tangxia, Dongguan, Guangdong, China Tel: +86-769-88050091 Fax: +86-769-88050092 www.bacel.com.cn	

\*Note: This report is prepared for the customer (here shown) and for the device described herein. It may not be reproduced or used in part without prior reference to the Ray Asia Compliance Laboratories Corp. (Dongguan).  
This report and its use by the customer is subject to the conditions, agreement or endorsement by BACL as the agent of the Public Government. \* This report may contain data that is not covered by the BACL Accreditation and is subject to its audit.

[pdf] Test Report SAR Rating

Microsoft Word SAR Report RDG200407009 20 dg06237 Reference Inrico Technologies Co Ltd 2 T529A Intelligent Two Way Radio 2AIV6 2AIV6T529A t529a

SAR EVALUATION REPORT For Shenzhen Inrico Electronics Co.,Ltd 3/F, Building No.118, High Tech Industrial Park, 72 Guowei Road, Luohu District, Shenzhen China  
FCC ID: 2AIV6-**T529A** Report Type: Original Report Product Type: Intelligent Two Way Radio Report Number: RDG200407009-20 Report Date: 2020-...  
lang:en score:24 filesize: 1.31 M page\_count: 70 document date: 2020-08-24



[pdf] Specifications Accessories

SpecSheet GoRugged etera T529 specsheet gorugged t529 co za pf 667ab6c07ff10 |||

INRICO **T529A** INRICO **T529A** The Inrico **T529A** will ensure that all our hardware are 4G/LTE capable for the first time ever This unit is an excellent upgrade from the T199 so all your T199 accessories such as batteries and cradles will work on the **T529A**. Only the antenna is different from the T199 due...


lang:en score:24 filesize: 535.15 K page\_count: 2 document date: 2024-06-25



[pdf] Agent Authorization

Microsoft Word FCC ID Authorization letter dg06139 Inrico Technologies Co Ltd T529A Intelligent Two Way Radio 2AIV6 2AIV6T529A t529a


Shenzhen Inrico Electronics Co.,Ltd ADD: 3/F, Building No.118, High Tech Industrial Park, 72 Guowei Road, Luohu District, Shenzhen China TEL: 0755-83273589 FAX: 0755-82689912 E-mail: 2850399099 qq.com FCC Authorization Date: 2020-04-09  
FEDERAL COMMUNICATIONS COMMISSION Authorization and Evaluation D...  
lang:en score:24 filesize: 54.05 K page\_count: 1 document date: 2020-08-21



[pdf] Test Report

Microsoft Word RDG200407009 00B Part 22H 24E 27 dg06237 Test Report part1 Inrico Technologies Co Ltd T529A Intelligent Two Way Radio 2AIV6 2AIV6T529A t529a

FCC PART 22H, PART 24E, PART 27 MEASUREMENT AND TEST REPORT For Shenzhen Inrico Electronics Co.,Ltd 3/F, Building No.118, High Tech Industrial Park, 72 Guowei Road, Luohu District, Shenzhen China FCC ID:2AIV6-**T529A** Report Type: Original Report Product Type: Intelligent Two Way Radio Report Number:...  
lang:tl score:22 filesize: 5.63 M page\_count: 80 document date: 2020-08-20




[pdf] User Manual Accessories SAR Rating

T529A cdr Miss User manual Inrico Technologies Co Ltd T529A Intelligent Two Way Radio 2AIV6 2AIV6T529A t529a

Android -106dBm GPS2G/3G/4G 0-40C Sound output power B1/B3/B7/B8/B20/B28 B1/B8 B3/B8 B2/B4/B5/B7/B12/B17 B38/B40/ A.B /B66 B2/B5 B5/B2 SAR tests are conducted using standard operating positions accepted by the FCC with the device transmitting at its highest certified power level in all tes...

lang:en score:21 filesize: 4.2 M page\_count: 9 document date: 2020-08-21



[\[pdf\]](#) Test Report

Inrico Technologies Co Ltd T529A 2AIV6 2AIV6T529A t529a

To: Date: Subject: Alemayehu Behulu 7/9/2021 21:30:00 Missing 38 Duty Cycle Per 27.50 a 3 Message: Dear FCC, The duty cycle less 38 was actually tested by the lab and provided on Page 35-39 of test report Part 1. Could you please double check  
Thanks, BACL ...

lang:en score:16 filesize: 6.12 K page\_count: 1 document date: 2021-07-10




[\[pdf\]](#)

SZ10150 Attestation Letter Inrico Technologies Co Ltd 2 T529A Intelligent Two Way Radio 2AIV6 2AIV6T529A t529a

...

lang:en score:14 filesize: 19.92 K page\_count: 1 document date: 2021-12-31



[\[pdf\]](#) SAR Rating

Microsoft Word SAR Plots dg06237 Scan Inrico Technologies Co Ltd T529A Intelligent Two Way Radio 2AIV6 2AIV6T529A t529a

...


lang:en score:13 filesize: 1019.5 K page\_count: 40 document date: 2020-08-18

lang:en score:13 filesize: 3.91 M page\_count: 53 document date: 2020-08-21

lang:en score:13 filesize: 62.61 K page\_count: 1 document date: 2021-12-31

lang:en score:13 filesize: 1.12 M page count: 8 document date: 2020-08-18





[\[pdf\]](#) Product Photos Teardown

Microsoft Word internal photos dg06237 Internal Photos Inrico Technologies Co Ltd T529A Intelligent

Two Way Radio 2AIV6 2AIV6T529A t529a

EXHIBIT C - EUT INTERNAL PHOTOGRAPHS ...

lang:en score:13 filesize: 356.13 K page\_count: 2 document date: 2020-08-18




[\[pdf\]](#) Confidentiality Request Letter

Date Yen Pin Wen Confidential Letter Inrico Technologies Co Ltd 2 T529A Intelligent Two Way Radio

2AIV6 2AIV6T529A t529a

...

lang:en score:13 filesize: 82.11 K page\_count: 1 document date: 2021-12-31




[\[pdf\]](#) SAR Rating

Microsoft Word SAR EUT Test Position Photos dg06237 Setup Inrico Technologies Co Ltd T529A

Intelligent Two Way Radio 2AIV6 2AIV6T529A t529a

...

lang:en score:13 filesize: 611.77 K page\_count: 2 document date: 2020-08-20



### [\[pdf\]](#) Decleration of Conformity SAR Rating

Microsoft Word SAR Report CR21120024 SAA1 doc dg06210 Inrico Technologies Co Ltd 2 T529A Intelligent Two Way Radio 2AIV6 2AIV62T529A t529a

...

lang:en score:13 filesize: 1.04 M page\_count: 12 document date: 2021-12-31



### [\[pdf\]](#) Product Photos

Microsoft Word External Photos winnie xiao Ext Inrico Technologies Co Ltd 2 T529A Intelligent Two Way Radio 2AIV6 2AIV62T529A t529a

...

lang:en score:13 filesize: 968.55 K page\_count: 5 document date: 2021-12-31



### [\[pdf\]](#) Product Photos Teardown

Microsoft Word Internal Photos winnie xiao Int Inrico Technologies Co Ltd 2 T529A Intelligent Two Way Radio 2AIV6 2AIV62T529A t529a

...

lang:en score:13 filesize: 1.28 M page\_count: 6 document date: 2021-12-31



[pdf]

Microsoft Word Test Photos winnie xiao Setup Inrico Technologies Co Ltd 2 T529A Intelligent Two Way Radio 2AIV6 2AIV62T529A t529a

...

lang:en score:13 filesize: 420.24 K page\_count: 3 document date: 2021-12-31



[pdf]

Microsoft Word Test Photos winnie xiao Setup Inrico Technologies Co Ltd 2 T529A Intelligent Two Way Radio 2AIV6 2AIV62T529A t529a

...

lang:en score:13 filesize: 420.24 K page\_count: 3 document date: 2021-12-31




[pdf] Confidentiality Request Letter

Microsoft Word FCC Long Term Confidential Authorization Form dg06139 long term Inrico Technologies Co Ltd T529A Intelligent Two Way Radio 2AIV6 2AIV6T529A t529a

...

lang:en score:13 filesize: 102.36 K page\_count: 1 document date: 2020-08-21



[\[pdf\]](#) Label

T529A cdr iniricohs ID Label and Location Inrico Technologies Co Ltd Intelligent Two Way Radio  
2AIV6 2AIV6T529A t529a

...

lang:en score:13 filesize: 295.91 K page\_count: 1 document date: 2020-08-21




[\[pdf\]](#) Label

Microsoft Word ID Label and Location winnie xiao FCC Inrico Technologies Co Ltd 2 T529A Intelligent  
Two Way Radio 2AIV6 2AIV6T529A t529a

...

lang:en score:13 filesize: 215.92 K page\_count: 1 document date: 2021-12-31




[\[pdf\]](#) Test Report

Microsoft Word RDG200407009 00B Part 22H 24E 27 dg06237 Test Report part2 Inrico Technologies Co  
Ltd T529A Intelligent Two Way Radio 2AIV6 2AIV6T529A t529a

Bay Area Compliance Laboratories Corp. Dongguan Report No.: RDG200407009-  
00B LTE Band 17 QPSK\_5 MHz Ref 25 dBm \* Att Offset 9 dB 20 D1 17.32 dBm T1 1  
PK 10 MAXH 30 dB 0 1 D2 -8.68 dBm -10 \* RBW 100 kHz \* VBW 300 kHz SWT 2.5  
ms Delta 1 T1 -1.21 dB 5.160000000 MHz OBW 4.520000000 MHz ...

lang:af score:12 filesize: 5.23 M page\_count: 50 document date: 2020-08-20




[\[pdf\]](#) Test Report

Microsoft Word RDG200407009 00B Part 22H 24E 27 dg06237 Test Report part4 Inrico Technologies Co Ltd T529A Intelligent Two Way Radio 2AIV6 2AIV6T529A t529a

...

lang:af score:12 filesize: 5.38 M page\_count: 63 document date: 2020-08-20




[\[pdf\]](#) Test Report

Microsoft Word RDG200407009 00B Part 22H 24E 27 dg06237 Test Report part3 Inrico Technologies Co Ltd T529A Intelligent Two Way Radio 2AIV6 2AIV6T529A t529a

...

lang:af score:12 filesize: 5.47 M page\_count: 58 document date: 2020-08-20



[\[pdf\]](#)

Microsoft Word RDG200407009 00B Part 22H 24E 27 dg06237 Reference Report 2 Inrico Technologies Co Ltd T529A Intelligent Two Way Radio 2AIV6 2AIV6T529A t529a

...

lang:af score:12 filesize: 5.24 M page\_count: 50 document date: 2020-08-20





ATC



**TEST REPORT**

Applicant Name : Inrico Technologies Co., Ltd  
Address : 3/F, Building No.118, High Tech Industrial Park, 72 Guowen Road, Luohu District, Shenzhen, China  
Report Number : SZGMA210719-29779E-RF-00BA1  
FCC ID : 2AIV6-2-T529A

**Test Standard (s)**  
FCC PART 15.247

**Sample Description**  
Product Type: Intelligent Two-Way Radio  
Model No.: T529A  
Trade Mark: INRICO  
Date Received: 2021/07/19  
Date of Test: 2021/08/04-2021/11/26  
Report Date: 2021/12/31

Test Results:

\* In the configuration tested, the EUT Complied with the standards above.

**Prepared and Checked By:**  
  
Fan Yang  
EMC Engineer

**Approved By:**  
  
Campbell  
EMC Engineer

Note: This report may contain information not covered by the FCC's confidentiality and is not to be used for any other purpose. This report is the property of ATC and is not to be used for any other purpose. The user is responsible for the accuracy of the information provided in this report. The user is responsible for the accuracy of the information provided in this report. The user is responsible for the accuracy of the information provided in this report.

Shenzhen Inrico Technologies Co., Ltd.  
3/F, Building A, Guoguang New Industrial Park, Luohu District, Shenzhen, China  
Tel: 0755-88888888 Fax: 0755-88888888 Email: info@inrico.com.cn

Version 12: 2021-11-08 Page 1 of 80 FCC: R02A2-05-WF1

[pdf] Test Report

Microsoft Word SZGMA210719 29779E RF 00BA1 FCC Part 15 247 BLE 2 4Wi Fi Report winnie xiao

Test Inrico Technologies Co Ltd T529A Intelligent Two Way Radio 2AIV6 2AIV62T529A t529a

...

lang:af score:11 filesize: 2.34 M page\_count: 59 document date: 2021-12-31

ATC



**TEST REPORT**

Applicant Name : Inrico Technologies Co., Ltd  
Address : 3/F, Building No.118, High Tech Industrial Park, 72 Guowen Road, Luohu District, Shenzhen, China  
Report Number : SZGMA210719-29779E-RF-00CA1  
FCC ID : 2AIV6-2-T529A

**Test Standard (s)**  
FCC PART 27, FCC PART 22H, FCC PART 2.4E

**Sample Description**  
Product Type: Intelligent Two-Way Radio  
Model No.: T529A  
Trade Mark: INRICO  
Date Received: 2021/07/19  
Date of Test: 2021/08/04-2021/11/26  
Report Date: 2021/12/31

Test Results:

\* In the configuration tested, the EUT complied with the standards above.

**Prepared and Checked By:**  
  
Fan Yang  
EMC Engineer

**Approved By:**  
  
Campbell  
EMC Engineer

Note: This report may contain information not covered by the FCC's confidentiality and is not to be used for any other purpose. This report is the property of ATC and is not to be used for any other purpose. The user is responsible for the accuracy of the information provided in this report. The user is responsible for the accuracy of the information provided in this report. The user is responsible for the accuracy of the information provided in this report.

Shenzhen Inrico Technologies Co., Ltd.  
3/F, Building A, Guoguang New Industrial Park, Luohu District, Shenzhen, China  
Tel: 0755-88888888 Fax: 0755-88888888 Email: info@inrico.com.cn

Version 12: 2021-11-08 Page 1 of 80 FCC: R02A2-05-WF1

[pdf] Test Report

Microsoft Word SZGMA210719 29779E RF 00CA1 FCC Part 22H 24E 27 Report winnie xiao Test

Inrico Technologies Co Ltd 2 T529A Intelligent Two Way Radio 2AIV6 2AIV62T529A t529a

...

lang:af score:11 filesize: 621.47 K page\_count: 19 document date: 2021-12-31