

Manuals+

[Q & A](#) | [Deep Search](#) | [Upload](#)

manuals.plus /

> [Cargifak](#) /

> [Cargifak 12-inch Flush Mount Ceiling Light \(Model CKCL4822-2W-ORB\) Instruction Manual](#)

Cargifak CKCL4822-2W-ORB

Cargifak 12-inch Flush Mount Ceiling Light Instruction Manual

Model: CKCL4822-2W-ORB

1. SAFETY INFORMATION

Please read and understand all instructions before beginning installation. Failure to do so may result in electric shock, fire, or other injuries that could be fatal or cause property damage.

- Always turn off the power at the main circuit breaker or fuse box before installing or servicing the fixture.
- Consult a qualified electrician if you are unsure about the installation process.
- Use only bulbs of the specified type and wattage.
- Do not install this fixture in wet locations. It is designed for indoor use only.
- Handle glass components with care to prevent breakage.

2. PRODUCT OVERVIEW

The Cargifak 12-inch Flush Mount Ceiling Light (Model CKCL4822-2W-ORB) features a modern design with an oil-rubbed bronze finish and frosted glass shade. This 2-light fixture is suitable for various indoor spaces such as bathrooms, bedrooms, kitchens, and hallways.

Key Features:

- **Modern Design:** High-quality metal frame with oil-rubbed bronze finish and frosted glass for a non-glare, elegant look.
- **Versatile Application:** Ideal for kitchen, bathroom, bedroom, living room, dining room, study room, porch, and entryway.
- **Bulb Compatibility:** Two E26 medium bulb bases support LED, CFL, or Edison bulbs (Max 60W each). Dimmable when used with a compatible dimmer switch and dimmable bulbs (not included).
- **Easy Installation:** Hardwired design with all necessary accessories and instructions for quick setup.



The Cargifak 12-inch Flush Mount Ceiling Light installed in a modern laundry room setting.

Your browser does not support the video tag.

An overview video showcasing the Cargifak Flush Mount Ceiling Light and its features.

3. WHAT'S IN THE BOX

Carefully unpack all components and check for any damage. Ensure all parts are present before discarding packaging materials.

- Light Fixture Body (with E26 sockets)
- Frosted Glass Shade
- Metal Frame
- Mounting Plate
- Mounting Screws and Wire Nuts
- Decorative Ball Nuts (3 pcs)
- Instruction Manual

Note: Bulbs are not included.



All components included in the package for the ceiling light.

4. SETUP (PRE-INSTALLATION)

Tools Required (Not Included):

- Phillips Head Screwdriver
- Flathead Screwdriver
- Wire Strippers
- Electrical Tape
- Ladder

Preparation Steps:

1. **Turn Off Power:** Locate the circuit breaker that supplies power to the light fixture and turn it OFF. Ensure power is completely disconnected before proceeding.
2. **Remove Old Fixture:** Carefully remove your existing light fixture. Disconnect all wiring and remove the old mounting plate.
3. **Prepare Fixture Body:** The mounting screws for the glass shade are pre-installed on the fixture body. If necessary, adjust their length to ensure the glass shade can be securely attached later.

5. INSTALLATION

Follow these steps carefully to install your new Cargifak ceiling light.

1. **Install Mounting Plate:** Secure the new mounting plate to your ceiling junction box using the provided screws. Ensure it is firmly attached.
2. **Connect Wiring:**
 - Connect the bare copper ground wire from the fixture to the green ground screw on the mounting plate, then connect it to the house ground wire using a wire nut.
 - Connect the white (neutral) wire from the fixture to the white (neutral) wire from the junction box using a wire nut.
 - Connect the black (live) wire from the fixture to the black (live) wire from the junction box using a wire nut.
 - Ensure all connections are secure and insulated with electrical tape if necessary.



Proper wiring connections for safe installation.

3. **Attach Fixture Body:** Carefully push the wired fixture body up to the mounting plate, aligning the pre-installed screws with the holes in the mounting plate. Secure the fixture body using the decorative ball nuts.
4. **Install Light Bulbs:** Screw the recommended E26 base bulbs (not included) into the sockets. Do not exceed the maximum wattage of 60W per bulb.
5. **Install Glass Shade and Metal Frame:** Place the frosted glass shade onto the fixture body, aligning it with the pre-installed screws. Then, place the metal frame over the glass shade, aligning its holes with the screws. Secure both the glass shade and metal frame by tightening the decorative ball nuts.

Your browser does not support the video tag.

A detailed video demonstrating the installation process for the Cargifak 4822 Ceiling Light.

6. OPERATION

Once installed, restore power at the circuit breaker. Your light fixture is now ready for use.

- **Turning On/Off:** Use your wall switch to turn the light fixture on or off.
- **Dimming Function:** If you have installed dimmable E26 bulbs and connected the fixture to a compatible dimmer

switch (both not included), you can adjust the light intensity using the dimmer control.



When you use with dimmer
and dimmable light bulb,
it is dimmable
(Bulb and dimmer are not included)

The light fixture supports dimming when used with dimmable bulbs and a compatible dimmer switch.

7. MAINTENANCE

Regular maintenance will ensure the longevity and optimal performance of your light fixture.

- **Cleaning:** Always turn off the power before cleaning. Wipe the fixture with a soft, dry cloth. Do not use harsh chemicals, abrasive cleaners, or polishes as they may damage the finish or glass.

- **Bulb Replacement:** Ensure power is off before replacing bulbs. Allow bulbs to cool completely before touching. Unscrew old bulbs and replace with new E26 base bulbs (Max 60W).
- **Inspection:** Periodically check all connections and mounting hardware for tightness.

8. TROUBLESHOOTING

If you experience issues with your light fixture, refer to the following common problems and solutions:

Problem	Possible Cause	Solution
Light does not turn on	<ol style="list-style-type: none"> 1. Power is off 2. Loose wiring connections 3. Faulty bulb 	<ol style="list-style-type: none"> 1. Check circuit breaker/fuse 2. Ensure all wire connections are secure 3. Replace bulb(s)
Light flickers	<ol style="list-style-type: none"> 1. Loose bulb 2. Incompatible dimmer switch/bulb 3. Loose wiring 	<ol style="list-style-type: none"> 1. Tighten bulb(s) 2. Ensure dimmer and bulbs are compatible 3. Check wiring connections
Glass shade is loose	Decorative ball nuts are not tight	Gently tighten the decorative ball nuts

9. SPECIFICATIONS

Feature	Detail
Brand	Cargifak
Model Name	CKCL4822-2W-ORB
Color	Frosted Glass & Oil Rubbed Bronze
Material	Aluminum, Glass
Style	Modern
Light Fixture Form	Close to Ceiling
Product Dimensions	12"L x 12"W x 4"H
Indoor/Outdoor Usage	Indoor
Power Source	Corded Electric
Installation Type	Flush Mount
Light Source Type	LED, Incandescent, CFL
Number of Light Sources	2
Voltage	110 Volts (AC)
Wattage	Max 60 watts per bulb
Bulb Base	E26 Medium
Brightness	1600 lumen (with appropriate bulbs)
Assembly Required	No (minor assembly for installation)

10. WARRANTY & SUPPORT

Cargifak products are manufactured to high-quality standards and are backed by a manufacturer's warranty. For specific warranty details, please refer to the documentation included with your purchase or contact Cargifak customer service.

Customer Support:

If you have any questions, require assistance with installation, or need to report a missing/damaged part, please contact Cargifak customer support through the retailer where the product was purchased or visit the official Cargifak website for contact information.