

Manuals+

[Q & A](#) | [Deep Search](#) | [Upload](#)

[manuals.plus](#) /

› [Vaporesso](#) /

› [Vaporesso Gen 160 E-Cigarette Set User Manual](#)

Vaporesso VS100G16-10

Vaporesso Gen 160 E-Cigarette Set User Manual

Model: VS100G16-10

INTRODUCTION

This manual provides detailed instructions for the safe and effective use of your Vaporesso Gen 160 E-Cigarette Set. The set includes the Gen 160 Mod and the GTX Pod 26 Clearomizer. Please read this manual thoroughly before operating the device to ensure proper function and longevity. This product is designed for adult use only and contains no nicotine.



Image: The Vaporesso Gen 160 E-Cigarette Set, featuring the pink and black textured mod with the black GTX Pod 26 Clearomizer attached at the top.

PACKAGE CONTENTS

Please verify that all items listed below are present in your package:

- 1x Vaporesso Gen 160 Mod
- 1x Vaporesso GTX Pod 26 Clearomizer (5 ml capacity)
- 1x GTX Mesh Coil 0.15 Ohm (pre-installed or separate)
- 1x GTX Mesh Coil 0.3 Ohm
- 1x USB-C Charging Cable
- 1x User Manual (this document)

Note: Two 18650 battery cells are required for operation and are *not* included in the package. These must be purchased separately.

SETUP GUIDE

1. Battery Installation

1. Open the battery compartment cover located at the bottom or side of the Gen 160 Mod.

2. Insert two 18650 battery cells according to the polarity indicators (+ and -) inside the compartment. Incorrect installation can damage the device.
3. Close the battery compartment cover securely.

2. Coil Installation (if not pre-installed)

1. Remove the GTX Pod 26 Clearomizer from the Gen 160 Mod.
2. Flip the pod upside down. The coil is press-fitted into the base.
3. Align the new GTX Mesh Coil with the slot in the pod and firmly push it into place until it is seated securely.
4. Ensure the coil is fully inserted to prevent leaks.

3. Filling the Tank

1. Locate the top-filling port on the GTX Pod 26 Clearomizer. This is usually under a silicone plug.
2. Open the silicone plug.
3. Carefully fill the tank with your desired e-liquid through the filling port. Do not overfill.
4. Close the silicone plug firmly to prevent leaks.
5. **Important:** After filling a new coil for the first time, let the pod stand for at least 5-10 minutes to allow the coil to become fully saturated with e-liquid. This prevents dry hits and extends coil life.

OPERATING INSTRUCTIONS

1. Power On/Off

- To turn the device on or off, press the fire button (main button) 5 times rapidly within 2 seconds. The OLED display will indicate the power status.

2. Adjusting Wattage

- The Gen 160 Mod operates in Variable Wattage (VW) mode by default, with an output range of 5 to 160 Watts.
- Use the '+' and '-' adjustment buttons (usually located below the display) to increase or decrease the wattage.
- Refer to the recommended wattage range for your installed coil:
 - GTX Mesh Coil 0.15 Ohm: 60 - 75 Watts
 - GTX Mesh Coil 0.3 Ohm: 32 - 45 Watts

3. Screen Information (0.91" OLED Display)

The OLED display provides essential information about your device's status:

- **Wattage:** Current power output.
- **Battery Level:** Indication of remaining battery charge.
- **Coil Resistance:** The detected resistance of the installed coil (in Ohms).
- **Puff Counter:** Tracks the number of puffs taken.
- **Vaping Time:** Duration of the last puff.

4. Vaping

- Press and hold the fire button while inhaling from the mouthpiece. Release the button when you finish inhaling.
- The device features an AXON Chip for stable performance and various safety protections.

5. Locking/Unlocking Buttons

- To lock or unlock the adjustment buttons (prevent accidental wattage changes), press the fire button 3 times rapidly. The fire button will remain active.

MAINTENANCE

1. Cleaning

- Regularly clean the connection points between the mod and the pod with a dry cloth or cotton swab to ensure good conductivity.
- Wipe down the exterior of the device with a soft, damp cloth. Do not use harsh chemicals or abrasive cleaners.
- The Gen 160 Mod is water and dust protected according to IPX5 standard, but it is not fully waterproof. Avoid submerging the device in water.

2. Coil Replacement

- Coils are consumable parts and need to be replaced periodically, typically every 1-2 weeks depending on usage and e-liquid.
- Signs that a coil needs replacement include a burnt taste, reduced vapor production, or diminished flavor.
- Follow the "Coil Installation" steps in the Setup Guide to replace the coil.

3. Charging

- Connect the supplied USB-C cable to the charging port on the Gen 160 Mod and plug the other end into a suitable USB power source (e.g., computer USB port, wall adapter).
- The device supports DC 5V/2A fast charging.
- The OLED display will show the charging status. Disconnect the charger once the batteries are fully charged.
- For optimal battery life and safety, it is recommended to charge 18650 batteries using an external dedicated battery charger.

TROUBLESHOOTING

Problem	Possible Cause	Solution
Device not turning on	Batteries not installed correctly or depleted; device off.	Check battery polarity and charge level. Press fire button 5 times rapidly to turn on.
No vapor production	Coil not installed; coil burnt out; tank empty; low battery; device locked.	Ensure coil is installed. Replace coil. Refill tank. Charge batteries. Unlock device (3 clicks of fire button).
Burnt taste	Coil not saturated; coil burnt out; wattage too high; tank empty.	Allow new coil to saturate (5-10 min). Replace coil. Reduce wattage. Refill tank.
Leaking from pod	Coil not seated properly; silicone plug not closed; damaged coil/pod.	Ensure coil is fully pushed in. Close silicone plug firmly. Replace coil or pod if damaged.
"Check Atomizer" or "No Atomizer" error	Pod not connected; coil issue; dirty connection.	Re-seat the pod. Replace the coil. Clean the 510 connection on the mod and the base of the pod.

SPECIFICATIONS

- **Model:** Vaporesso Gen 160 E-Cigarette Set
- **Mod Dimensions (with Pod):** 135.95 x 52.70 x 27.54 mm
- **Output Wattage:** 5 - 160 Watts
- **Display:** 0.91" OLED Screen
- **Chipset:** AXON Chip
- **Battery Compatibility:** 2x 18650 (not included)
- **Charging:** USB-C, DC 5V/2A
- **Water & Dust Protection:** IPX5 Standard
- **Tank Capacity:** 5 ml (GTX Pod 26 Clearomizer)
- **Filling System:** Top-Filling
- **Airflow:** Bottom-Airflow
- **Coil Compatibility:** Vaporesso GTX Coils
- **Recommended Coils (Included):**
 - GTX Mesh 0.15 Ohm (60-75W) - For Direct-to-Lung (DL) vaping
 - GTX Mesh 0.3 Ohm (32-45W) - For Direct-to-Lung (DL) vaping
- **Thread Type:** 510 (for pod connection)

SAFETY INFORMATION

- Keep the device out of reach of children and pets.
- Do not use damaged batteries or chargers.
- Do not expose the device to extreme temperatures, direct sunlight, or water (beyond IPX5 rating).
- Do not disassemble or modify the device.
- Use only genuine Vaporesso coils and accessories.
- This product is intended for use with e-liquids that do not contain nicotine.

WARRANTY AND SUPPORT

Vaporesso products typically come with a limited warranty. Please refer to the warranty card included in your original packaging or visit the official Vaporesso website for detailed warranty terms and conditions.

For technical support, troubleshooting assistance, or inquiries about your Vaporesso Gen 160 E-Cigarette Set, please contact Vaporesso customer service or the retailer from whom you purchased the product.

Manufacturer: Vaporesso

© 2024 Vaporesso. All rights reserved.
This product contains no nicotine.

Related Documents - VS100G16-10

<p>USER MANUAL</p> <p>VAPORESSO XROS PRO</p> <p></p>	<p><u>VAPORESSO XROS PRO User Manual - Vaping Device Guide</u></p> <p>Comprehensive user manual for the VAPORESSO XROS PRO pod system. Learn about setup, operation, specifications, safety precautions, and troubleshooting for your vaping device.</p>
<p>VAPORESSO XROS</p> <p></p>	<p><u>Vaporesso XROS User Manual: Operation, Specifications, and Safety Guide</u></p> <p>Comprehensive user manual for the Vaporesso XROS device, detailing specifications, usage instructions, safety precautions, and warnings. Essential guide for optimal and safe operation.</p>
<p>USER MANUAL</p> <p>LUXE XR MAX</p> <p></p>	<p><u>VAPORESSO LUXE XR MAX User Manual: Features, Instructions, and Safety</u></p> <p>Comprehensive user manual for the VAPORESSO LUXE XR MAX, detailing specifications, usage instructions, safety precautions, and troubleshooting. Covers features like airflow adjustment, wattage settings, and battery indicators.</p>
<p></p>	<p><u>Vaporesso XROS Mesh Pod - Topfill: Gebrauchsanleitung und Sicherheitshinweise</u></p> <p>Umfassende Gebrauchsanleitung für das Vaporesso XROS Mesh Pod - Topfill Verdampferset. Enthält Informationen zur Befüllung, Bedienung, Reinigung, Sicherheitshinweisen und Entsorgung.</p>

USER MANUAL

VAPORESSO LUXE X PRO

[Vaporesso Luxe X Pro User Manual](#)

Comprehensive user manual for the Vaporesso Luxe X Pro, detailing setup, usage, settings, safety features, and troubleshooting.

 VAPORESSO



[VAPORESSO GTX ONE MOD & GTX TANK 18 User Manual | Operation and Safety Guide](#)

Detailed user manual for the VAPORESSO GTX ONE MOD and GTX TANK 18 vaping device. Includes setup, operation, filling, coil replacement, safety warnings, and device protection information.