

Minka Lavery 2272-84B

Minka Lavery Tiberia 2-Light Vanity Bath Light  
Model: 2272-84B

INTRODUCTION

This manual provides detailed instructions for the safe installation, operation, and maintenance of your Minka Lavery Tiberia 2-Light Vanity Bath Light, model 2272-84B. Please read all instructions carefully before beginning installation and retain this manual for future reference.

SAFETY INFORMATION

- **WARNING:** Risk of electric shock. Disconnect power at the circuit breaker or fuse box before installation or servicing.
- All wiring connections must be in accordance with local and national electrical codes. If you are unfamiliar with proper electrical wiring connections, consult a qualified electrician.
- This fixture is intended for indoor, damp location use only. Do not install in areas exposed to direct water spray or submersion.
- Use only the specified bulb type and wattage. Exceeding the maximum wattage may cause overheating and damage to the fixture.
- Handle glass components with care to prevent breakage.
- Keep flammable materials away from the light fixture when in operation.
- This product may contain chemicals known to the State of California to cause cancer, birth defects, or other reproductive harm. Wash hands after handling. (Proposition 65 Warning)

PACKAGE CONTENTS

Carefully unpack your new light fixture and lay out all parts on a clear surface. Ensure all components listed below are present before discarding packaging materials.

- Vanity Bath Light Fixture (1)
- Clear Glass Shades (2)
- Mounting Hardware Kit (1) - *Includes screws, wire nuts, etc.*
- Instruction Manual (1)

*Note: Bulbs are not included. Recommended bulb type: T8 Candelabra, Max 60 Watt per bulb.*

SPECIFICATIONS

|                         |                                       |
|-------------------------|---------------------------------------|
| Model Number:           | 2272-84B                              |
| Dimensions (W x H x D): | 13.75 inches x 9 inches x 5.63 inches |
| Weight:                 | 4.59 lbs                              |
| Number of Lights:       | 2                                     |
| Max Wattage Per Bulb:   | 60 Watts                              |
| Total Wattage:          | 120 Watts                             |
| Recommended Bulb Type:  | T8 Candelabra (E12 Base)              |
| Voltage:                | 120 Volts                             |
| Finish:                 | Plated Pewter                         |
| Material:               | Alloy Steel, Glass                    |
| Location Rating:        | Damp Rated (Indoor Use)               |
| Dimmable:               | Yes                                   |

## SETUP AND INSTALLATION

### Before You Begin:

- Turn off power at the circuit breaker or fuse box.
- Ensure you have all necessary tools (screwdriver, wire strippers, electrical tape, etc.) and the included mounting hardware.
- This fixture is designed to be mounted to a standard electrical junction box (not included).

### Installation Steps:

- 1. Prepare the Mounting Plate:** Attach the mounting plate to your electrical junction box using the screws provided in the hardware kit. Ensure the plate is securely fastened.
- 2. Make Electrical Connections:**
  - Connect the **black** wire from the fixture to the **black** (hot) wire from the junction box.
  - Connect the **white** wire from the fixture to the **white** (neutral) wire from the junction box.
  - Connect the **ground** wire (bare copper or green) from the fixture to the **ground** wire from the junction box and to the mounting plate.
  - Secure all connections with wire nuts and wrap with electrical tape for added safety.
- 3. Mount the Fixture:** Carefully align the fixture body with the mounting plate and secure it using the provided screws or nuts. Ensure no wires are pinched during this step.
- 4. Install Bulbs:** Screw in two T8 Candelabra bulbs (max 60W each) into the sockets. Do not overtighten.
- 5. Attach Glass Shades:** Carefully place the clear glass shades over the bulb sockets and secure them according to the fixture design (e.g., using retaining rings or screws).
- 6. Restore Power:** Turn the power back on at the circuit breaker. Test the light fixture.



Image: Front view of the Minka Lavery Tiberia 2-Light Vanity Bath Light, showing the plated pewter finish and clear glass shades.



Image: Angled view of the Minka Lavery Tiberia 2-Light Vanity Bath Light, highlighting the design and bulb placement.

## OPERATING INSTRUCTIONS

Once installed, the Minka Lavery Tiberia Vanity Bath Light operates like any standard wall-mounted light fixture. It is controlled by a wall switch (not included) connected to the electrical circuit.

- **Turning On/Off:** Use the connected wall switch to turn the light fixture on or off.
- **Dimming Function:** This fixture is dimmable. If connected to a compatible dimmer switch (sold separately), you can adjust the light intensity. Follow the dimmer switch manufacturer's instructions for operation.

## MAINTENANCE

Regular maintenance will help preserve the appearance and functionality of your light fixture.

- **Cleaning:**
  - Always disconnect power before cleaning.
  - Wipe the fixture with a soft, dry cloth.
  - Do not use abrasive cleaners, solvents, or polishes as they may damage the finish.
  - For glass shades, a mild glass cleaner can be used, applied to a cloth, not directly to the fixture.
- **Bulb Replacement:**
  - Ensure power is off and bulbs have cooled before attempting to replace them.
  - Unscrew the old bulb and screw in a new T8 Candelabra bulb (max 60W).

## TROUBLESHOOTING

| Problem                 | Possible Cause               | Solution                                                                     |
|-------------------------|------------------------------|------------------------------------------------------------------------------|
| Light does not turn on. | No power to the fixture.     | Check circuit breaker or fuse.                                               |
|                         | Loose wire connections.      | Verify all wire connections are secure (ensure power is off first).          |
|                         | Faulty bulb.                 | Replace bulb with a new one.                                                 |
|                         | Faulty wall switch.          | Test wall switch or consult an electrician.                                  |
| Light flickers.         | Loose bulb.                  | Tighten bulb.                                                                |
|                         | Incorrect bulb type/wattage. | Ensure correct bulb type (T8 Candelabra) and wattage (max 60W).              |
|                         | Incompatible dimmer switch.  | Ensure dimmer switch is compatible with incandescent/LED bulbs if using LED. |
| Fixture hums.           | Incompatible dimmer switch.  | Replace dimmer switch with a high-quality, compatible model.                 |
|                         | Loose components.            | Ensure all mounting screws and fixture components are tight.                 |

If you experience issues not covered here, or if troubleshooting steps do not resolve the problem, please contact customer support.

## WARRANTY AND SUPPORT

### Manufacturer's Limited Warranty:

This Minka Lavery product is covered by a **One Year Limited Warranty** from the date of purchase. This warranty covers defects in materials and workmanship under normal use. It does not cover damage resulting from improper installation, accident, misuse, abuse, or normal wear and tear.

For warranty claims or technical support, please contact Minka Lavery customer service. Please have your model number (2272-84B) and proof of purchase available.

### Contact Information:

Refer to the Minka Lavery official website or your purchase documentation for the most current customer support contact details.

You can visit the Minka Lavery store on Amazon for more products and information: [Minka Lavery Store](#)

## ASK A QUESTION ABOUT THIS MANUAL

Ask about setup, troubleshooting, compatibility, parts, safety, or missing instructions. Manuals+ will review the question and use this page's manual context to help answer it.

### Name

Anonymous

### Email

you@example.com

After a successful submission, we securely hash the supplied account or form email before sending it to Microsoft Advertising for conversion attribution. [Privacy details](#).

### Question

Example: How do I reset this device or fix this error?

### Details

Model number, symptoms, what you tried, or the section of the manual you are using.

Submit question

---

Open the live page

<https://manuals.plus/asin/B09JQTSZQ8>

More documents and user manuals: <https://manuals.plus/>