

hofstein Naofe

Hofstein Naofe Outdoor Pathway Light Instruction Manual

Model: Naofe

1. INTRODUCTION

This manual provides detailed instructions for the safe installation, operation, and maintenance of your Hofstein Naofe outdoor pathway light. Please read this manual thoroughly before installation and retain it for future reference. This product is designed for outdoor use, providing ambient lighting for gardens, patios, and pathways.

2. SAFETY INSTRUCTIONS

- **Electrical Safety:** Always disconnect the main power supply before attempting any installation, maintenance, or bulb replacement. Installation should be performed by a qualified electrician if you are unsure about electrical wiring.
- **Outdoor Use:** This product is rated IP43, meaning it is protected against solid objects larger than 1mm and spraying water. Ensure the product is installed in an upright position and in a location suitable for its IP rating.
- **Bulb Requirements:** Use only E27 bulbs with a maximum wattage of 40W. Do not exceed the specified wattage to prevent overheating and damage.
- **Mounting:** Ensure the light is securely mounted on a stable and level surface to prevent tipping or falling.
- **Children and Pets:** Keep packaging materials and small components away from children and pets to prevent choking hazards.

3. PACKAGE CONTENTS

Please check that all components are present and undamaged before beginning installation.

- Lamp Head (with glass panels and E27 socket)
- Lamp Post Sections (typically 2 sections)
- Base Plate

- Decorative Finial
- Mounting Hardware (screws, anchors)
- Instruction Manual



Image 3.1: Exploded view showing the lamp head, post sections, base, finial, and mounting hardware.

4. SETUP AND INSTALLATION

Follow these steps for proper installation of your outdoor pathway light.

1. **Unpack:** Carefully remove all components from the packaging.
2. **Site Selection:** Choose a suitable outdoor location for the lamp. Ensure the ground is level and stable, and that there is access to a 230V power supply.
3. **Assemble Post:** Connect the lamp post sections together, ensuring they are securely fastened.
4. **Mount Base:** Position the base plate at the desired location. Mark the drilling points. Drill holes and secure the base to the ground using the provided mounting hardware (screws and anchors). Ensure the base is firmly attached.
5. **Electrical Connection:** Route the electrical wiring through the lamp post. Connect the live, neutral, and

ground wires to the corresponding terminals in the lamp head. Ensure all connections are tight and properly insulated. **If you are not confident with electrical wiring, consult a qualified electrician.**

6. **Install Bulb:** Insert an E27 bulb (max 40W, not included) into the lamp holder within the lamp head.
7. **Attach Lamp Head:** Securely attach the assembled lamp head to the top of the lamp post.
8. **Install Finial:** Place the decorative finial on top of the lamp head and secure it.
9. **Test:** Restore power to the circuit and test the functionality of the light.



Image 4.1: Dimensional diagram of the Hofstein Naofe lamp. Height: 105.5 cm, Width: 21.5 cm, Diameter: 21 cm.

hofstein®



Image 4.2: Close-up of the lamp head, illustrating the E27 bulb socket.

5. OPERATING INSTRUCTIONS

The Hofstein Naofe outdoor pathway light operates with a standard E27 bulb (max 40W). It is designed for continuous outdoor illumination when connected to a power source. There are no integrated switches, timers, or sensors; operation is controlled by your external power switch or a connected smart home system.

hofstein®



Image 5.1: The Hofstein Naofe lamp providing illumination in an outdoor environment.

6. MAINTENANCE

Regular maintenance ensures the longevity and optimal performance of your outdoor light.

- **Cleaning:** Regularly clean the metal and glass surfaces with a soft, damp cloth. Avoid using abrasive cleaners, solvents, or harsh chemicals, as these can damage the finish.
- **Inspection:** Periodically check all connections, mounting hardware, and the lamp post for tightness and stability. Inspect the electrical wiring for any signs of wear, fraying, or damage.
- **Bulb Replacement:** Before replacing the E27 bulb, always disconnect the power supply. Allow the old bulb to cool completely before removal. Install a new E27 bulb (max 40W).
- **Seals:** Ensure that all seals and gaskets are properly seated to maintain the IP43 protection against water ingress.

7. TROUBLESHOOTING

If you encounter issues with your Hofstein Naofe light, refer to the following common problems and solutions:

Problem	Possible Cause	Solution
Light does not turn on	No power supply, faulty bulb, loose wiring connection	Check the circuit breaker. Replace the bulb. Verify all electrical connections are secure (ensure power is off first).
Light flickers	Loose bulb, unstable power supply, faulty wiring	Tighten the bulb. Check for stable power. Inspect wiring for damage (with power off).
Water inside the lamp head	Improperly sealed components, damaged gasket, incorrect installation angle	Ensure all glass panels and seals are correctly seated. Verify the lamp is installed upright. Check for any cracks or damage to the housing.

8. SPECIFICATIONS

Feature	Detail
Model	Naofe
Brand	Hofstein
Dimensions (Height x Width x Diameter)	105.5 cm x 21.5 cm x 21 cm
Luminaire Material	Metal (Aluminium)
Shade Material	Glass, Metal
Luminaire Color	Black
Shade Color	Clear, Black
Bulb Socket	E27
Number of Lights	1
Max Wattage per Light	40 Watt
Power Supply	230 Volt AC
Protection Rating	IP43
Usage	Outdoor, Garden, Terrace
Style	Vintage, Countryside
Form	Elongated, Round
Special Features	Water-resistant
Energy Label	F

9. WARRANTY AND SUPPORT

This Hofstein Naofe outdoor pathway light comes with a standard manufacturer's warranty. The duration and terms of the warranty may vary depending on your region and retailer.

For warranty claims, technical support, or inquiries regarding spare parts, please contact your point of purchase or the manufacturer directly. When contacting support, please have your purchase receipt and the product model number (Naofe) available to expedite assistance.

Please note that information regarding software updates and spare parts availability is not explicitly provided for this product.