

[Manuals.plus](#) /

> [PARTPHONER](#) /

> PARTPHONER 3-Head Outdoor Lamp Post Light Instruction Manual

PARTPHONER B09P85W7H2

PARTPHONER 3-Head Outdoor Lamp Post Light Instruction Manual

Model: B09P85W7H2

INTRODUCTION

This manual provides detailed instructions for the installation, operation, and maintenance of your PARTPHONER Dusk to Dawn Sensor Outdoor Lamp Post Light. Designed for durability and aesthetic appeal, this 3-head classic black light pole with clear glass panels is ideal for enhancing the lighting and ambiance of your outdoor spaces.



Figure 1: PARTPHONER 3-Head Outdoor Lamp Post Light

PRODUCT FEATURES

- **Advanced Dusk to Dawn Sensor:** Built-in IC sensor automatically detects ambient brightness, turning the light on at dusk and off at dawn, optimizing energy efficiency.
- **Sturdy and Weather Resistant:** Constructed from anti-rust die-cast aluminum and solid clear glass, ensuring durability and resistance to rain, snow, wind, and frost with an IP65 waterproof rating.

- **Easy Installation:** Designed for straightforward setup with included mounting hardware and assembly instructions. Requires three E26 base bulbs (3x 6W LED bulbs included).
- **Classic Design:** Features a timeless 3-head design in black, adding a vintage and elegant touch to any outdoor setting.
- **Versatile Outdoor Lighting:** Perfect for illuminating backyards, gardens, terraces, porches, paths, sidewalks, landscapes, lawns, and driveways.

PACKAGE CONTENTS

Please verify that all components are present before beginning installation:

- 1 x Lamp Post Assembly (multi-section pole, 3 light heads)
- 3 x E26 Base LED Bulbs (6W each)
- Mounting Hardware (screws, nuts, washers, template)
- Instruction Manual



Figure 2: Exploded view of lamp post components

SAFETY INFORMATION

Always observe the following safety precautions during installation and operation:

- **WARNING:** Disconnect power at the circuit breaker before installation or servicing.
- Ensure the product is installed by a qualified electrician if you are unsure about electrical wiring.
- This product is designed for outdoor use and has an IP65 waterproof rating. However, ensure all electrical connections are properly sealed and protected from moisture.
- Do not exceed the maximum wattage of 100W per bulb for E26 base bulbs.
- Keep children and pets away from the installation area.

SETUP AND INSTALLATION

Follow these steps for proper installation of your lamp post light. For a visual guide on installing a lamp post into concrete, please refer to the video below.

Your browser does not support the video tag.

Video 1: How to Install a Lamp Post into Freshly Poured Concrete. This video demonstrates the process of setting up the concrete base and attaching the lamp post, including wiring connections.

1. Prepare the Foundation:

Dig a hole for the concrete base according to local building codes and the size of the lamp post base. Ensure proper drainage. Use the provided template for accurate bolt placement in the concrete foundation.



Figure 3: Simple DIY Installation with template card

2. Assemble the Lamp Post:

Carefully unbox all components. Connect the pole sections if they are separate. Attach the three light heads to the top section of the pole. Ensure all connections are secure.

3. Wiring Connections:

Route the electrical wiring through the lamp post pole. Connect the fixture's wires to your main power supply wires (black to black, white to white, ground to ground). Use appropriate wire nuts and ensure connections are tight and insulated. Refer to local electrical codes for proper wiring procedures.

4. Mount the Lamp Post:

Carefully lift the assembled lamp post and align its base with the anchor bolts in the concrete foundation. Secure the base using the provided nuts and washers. Tighten firmly but do not overtighten.

5. Install Bulbs:

Screw the three included 6W LED E26 base bulbs into each light head. The lamp post is compatible with LED, incandescent, or flame bulbs up to a maximum of 100W per head.



Figure 4: LED & Flame Light Compatible (3 LED Bulbs Included)

OPERATION

Your PARTPHONER lamp post light features an advanced dusk to dawn sensor for automated operation:

- **Automatic On/Off:** The built-in IC sensor detects ambient light levels. The light will automatically turn on when it gets dark and turn off when daylight is detected.
- Ensure the sensor is not obstructed by objects or direct artificial light sources, as this may interfere with its proper function.



Figure 5: Auto OFF at Daytime / Auto ON at Night

MAINTENANCE

Regular maintenance will ensure the longevity and optimal performance of your lamp post light:

- **Cleaning:** Periodically wipe down the aluminum frame and glass panels with a soft, damp cloth. Avoid abrasive cleaners or solvents that could damage the finish or glass.
- **Bulb Replacement:** To replace bulbs, ensure power is disconnected at the circuit breaker. Allow bulbs to cool before handling. Unscrew the old bulb and screw in a new E26 base bulb (max 100W).
- **Inspection:** Annually inspect the wiring and connections for any signs of wear, corrosion, or damage. Ensure the mounting hardware remains tight.
- Despite its IP65 rating, avoid directing high-pressure water jets directly at the light fixture.

IP65 Waterproof and Weather Resistant



Figure 6: IP65 Waterproof and Weather Resistant

TROUBLESHOOTING

If you encounter issues with your lamp post light, refer to the following common problems and solutions:

Problem	Possible Cause	Solution
Light does not turn on.	No power, faulty bulb, sensor malfunction.	Check circuit breaker. Replace bulb. Ensure sensor is not obstructed.
Light stays on during the day.	Sensor obstructed, sensor malfunction, light pollution.	Clear any obstructions from the sensor. Relocate the light if it's exposed to excessive artificial light at night.
Light flickers.	Loose wiring, incompatible bulb, power fluctuations.	Check all wiring connections. Ensure bulbs are fully screwed in. Try a different bulb.

If the problem persists after attempting these solutions, please contact customer support.

SPECIFICATIONS

Attribute	Detail
Brand	PARTPHONER
Model	B09P85W7H2
Color	Black (with sensor)
Material	Aluminum, Glass
Light Fixture Form	Path
Room Type	Outdoor
Power Source	Corded Electric
Installation Type	Pole Mount
Light Source Type	LED (Bulbs Included)
Number of Light Sources	3
Voltage	120 Volts
Wattage (Max)	100 watts per bulb
Bulb Base	E26 Medium
Switch Type	Dusk to Dawn Sensor
Water Resistance Level	IP65 Waterproof
Item Weight	17.28 pounds
Package Dimensions	27.5 x 20.15 x 11 inches





Figure 7: Product Dimensions

WARRANTY AND SUPPORT

PARTPHONER is committed to providing quality products. If you have any questions or require assistance with your lamp post light, please do not hesitate to contact us. We aim to respond and provide support within 24 hours. Optional protection plans are available for purchase to extend coverage beyond the standard warranty. Please refer to the product listing or contact your retailer for details on available protection plans.