

johgee SOFIA

Johgee WiFi Watering Computer User Manual

Model: SOFIA

Brand: johgee

1. PRODUCT OVERVIEW

The Johgee WiFi Watering Computer (Model SOFIA) is an intelligent irrigation system designed to automate garden watering. It connects to your home WiFi network via a hub, allowing for remote control and scheduling through a dedicated mobile application. This device supports various watering modes, including time-based and cyclic irrigation, and features a rain delay function to conserve water.



Figure 1: Johgee WiFi Watering Computer, showing the main unit, the WiFi hub, and the mobile application interface.

What's in the box?

What's in the box ?

Smart Water Timer *1

WiFi Hub *1

1/2" inlet adapter *1

Threaded connector *1

Instruction *1



Figure 2: What's in the box? Includes the Smart Water Timer, WiFi Hub, 1/2" inlet adapter, threaded connector, and instruction manual.

2. SETUP AND INSTALLATION

2.1. Components and Connections

Ensure all components are present as listed in the "What's in the box?" section. The watering computer connects directly to your outdoor faucet, and the WiFi hub connects to an indoor power outlet.

2 Size Rings For Standard Type Faucet




Figure 3: Installation diagram illustrating the use of 5mm O-ring for USA-type 3/4" hose faucet and 3mm O-ring with 1/2" adapter for EU-type 2/1" hose faucet. The 360° rotating connector allows for easy tightening.

To prevent leaks, ensure the irrigation timer is securely attached to the faucet and hose. If necessary, add a rubber washer and thread seal tape (PTFE tape) to the connections.

2.2. App and WiFi Hub Connection

- 1. Download the Smart Life App:** Download "Smart Life" from the App Store (iOS) or Google Play (Android). Create an account if you don't have one.
- 2. Connect the WiFi Hub:** Plug the WiFi hub into an indoor power outlet located near your smart watering timer.
- 3. Install Batteries in Water Timer:** Insert two AA batteries into the water timer.
- 4. Enable Bluetooth and WiFi:** On your smartphone, ensure both Bluetooth and WiFi are enabled. The device supports 2.4 GHz WiFi networks only.
- 5. Add Device in App (Hub):** Open the Smart Life app, log in, and tap "Add Device" or the "+" icon. Choose "Gateway Control" > "Socket Gateway (BLE)".
- 6. Pair WiFi Hub:** Press the button on the WiFi hub until the green indicator flashes rapidly. Follow the app

prompts to pair the hub.

7. **Add Device in App (Timer):** With the 2 AA batteries in the timer, press the button on the water timer until its green indicator flashes rapidly. In the app, click "Add Device" again.
8. **Program Your Timer:** Wait for the connection to reach 100%. Once connected, you can program your watering schedule via the app.



Figure 4: The optimal range between the smart watering timer and the WiFi hub is within 10 meters (32.8 feet) in an open area.

3. OPERATING INSTRUCTIONS

3.1. Smart Watering System

Once connected to your 2.4 GHz WiFi network, you can easily program and manage your irrigation schedule anytime, anywhere, using the Smart Life app. The app also allows for voice control via Alexa.






Figure 5: Remote control of the watering system is possible anytime and anywhere via the WiFi app, enhancing smart living.

3.2. Watering Modes

The irrigator offers two primary watering modes:

- **Time-based Irrigation:** Set specific start times, durations, and frequencies for watering.
- **Cyclic Irrigation:** Configure the irrigation time and soak time within a specified period. This mode is useful for allowing water to penetrate the soil effectively.



Easy Watering Schedule
Allow you watering on minutes,
hours, specific days of the week

Figure 6: The app allows for easy watering schedule setup, enabling watering on minutes, hours, or specific days of the week.

Automatic Irrigation Regularly

10:00

When working



6:00

When sleeping



16:00

When traveling



Figure 7: Automatic irrigation can be scheduled regularly, for example, at 10:00 (when working), 6:00 (when sleeping), or 16:00 (when traveling).

3.3. Rain Delay Function

The rain delay feature allows you to skip irrigation for 24, 48, or 72 hours if the weather forecast indicates rain. This helps conserve water and prevents overwatering.

Rain Delay Mode

Postpone watering for 24h, 48h or 72h

Close Delay (Nearly 24hours Nearly 48hours Nearly 72hours)



Figure 8: The rain delay mode allows postponing watering for 24h, 48h, or 72h. The device also features an IPX5 waterproof rating.

3.4. Manual Watering

You can manually activate watering without disturbing the programmed schedule. This is useful for quick, on-demand watering.



Manual Watering Function

Manual watering without distributing the programmed schedule

Figure 9: The manual watering function allows for immediate watering without affecting the pre-set schedule.

4. MAINTENANCE

- **Preventing Leaks:** Regularly check all connections for tightness. Ensure rubber washers and thread seal tape are properly installed to prevent water leakage.
- **Battery Replacement:** If the power level is low, replace the two AA batteries promptly. Ensure the water timer is dry before replacing batteries.
- **Handling and Storage:** Handle the irrigation timer carefully to avoid impacts. Do not leave the device outdoors during winter without proper protection or storage to prevent damage from freezing temperatures.

5. TROUBLESHOOTING

Problem	Possible Cause	Solution
Device not connecting to WiFi.	Incorrect WiFi frequency; WiFi hub too far from timer; temporary connection issue.	Ensure your WiFi is 2.4 GHz. Place the WiFi hub within 10 meters (32.8 feet) of the timer in an open area. Wait 5-10 seconds for the device to reconnect if it enters sleep mode.
Water leakage at connections.	Loose connection; missing or damaged rubber washer/seal tape.	Tighten all connections securely. Ensure rubber washers and thread seal tape are properly installed. Replace if damaged.
Timer not operating as scheduled.	Low battery power; incorrect schedule settings in app; device in sleep mode.	Replace AA batteries. Verify schedule settings in the Smart Life app. Allow 5-10 seconds for the device to wake from sleep mode.

6. SPECIFICATIONS

Feature	Detail
Brand	johgee
Model	SOFIA
Material	Rubber
Color	Multicolor
Package Dimensions	15.5 x 10.6 x 7.7 cm; 440 g
Batteries Required	No (but uses 2 AA batteries for the timer unit)
Water Pressure Range	7.2 psi to 116 psi
WiFi Support	2.4 GHz only
Waterproof Rating	IPX5

7. WARRANTY AND SUPPORT

Specific warranty information and direct customer support contact details are not provided in the available product

data. Please refer to the product packaging or the seller's information on the purchase platform for details regarding warranty coverage and customer support.

© 2024 Johgee. All rights reserved.