

ALFAJR CS-13

ALFAJR Azan Clock CS-13 Instruction Manual

Model: CS-13 | Brand: ALFAJR

1. INTRODUCTION

The ALFAJR Azan Clock CS-13 is a versatile Islamic table clock designed to provide automatic Azan (Athan) prayer alarms five times a day. It calculates Azan times based on your set location and displays time, date (Gregorian and Hijri), Azan time, adjustable volume, Qibla direction, and temperature. This manual provides detailed instructions for setting up and operating your clock.

2. PACKAGE CONTENTS

- ALFAJR CS-13 Azan Clock
- 2 AA batteries (included)
- Instruction Manual
- Micro USB option available (adapter not included)

3. GETTING STARTED: BATTERY INSTALLATION

To power your ALFAJR Azan Clock CS-13, install the included AA batteries.



Image: Rear view of the ALFAJR Azan Clock CS-13, highlighting the battery compartment and various control switches for daily alarm, prayer alarms, and snooze functions.

1. Locate the battery compartment cover on the back of the clock.
2. Remove the cover.
3. Insert 2 AA batteries, ensuring correct polarity (+/-).
4. Replace the battery compartment cover.

The clock can also be powered via a Micro USB cable (adapter not included).

4. INITIAL SETUP AND OPERATION

4.1. Setting Country and City

The clock automatically calculates Azan times based on your location. You can set your city by using its international dialing phone code or by entering longitude and latitude.

Your browser does not support the video tag.

Video: This video demonstrates how to set up the Azan Clock for USA, including country and city selection. It shows the process of navigating through settings to find and confirm your location.

1. Press the **SET** button to enter the settings menu.
2. Use the **UP** or **DOWN** buttons to navigate to "CITY SEL" (City Selection).
3. Press **SET** to confirm.
4. Use **UP** or **DOWN** to select your country.
5. Press **SET** to confirm the country.
6. Use **UP** or **DOWN** to select your city.
7. Press **SET** to confirm the city.

4.2. Setting Date and Time

Your browser does not support the video tag.

Video: This video provides easy step-by-step instructions for setting the date and time on the ALFAJR Azan Clock, including adjusting hours, minutes, and calendar details.

1. From the main display, press **SET** to enter the time setting mode.
2. Use **UP** or **DOWN** to adjust the hour, then press **SET**.
3. Repeat for minutes, year, month, and day.
4. The clock supports both Hijri and Gregorian calendars.

4.3. Adjusting Azan Times

Azan times are automatically calculated, but you can adjust them forward or backward by 0 to 99 minutes for each prayer time individually.

Your browser does not support the video tag.

Video: This video demonstrates how to adjust individual Azan prayer times on the clock, allowing for fine-tuning of the automatic calculations.

1. Press the **AZAN SOUND** button to cycle through prayer times.
2. When the desired prayer time is displayed, press **SET**.
3. Use **UP** or **DOWN** to adjust the minutes.
4. Press **SET** to save the adjustment and move to the next prayer time.

4.4. Daily Alarms and Extra Alarms

The clock features daily alarms with weekend options and an extra alarm for special appointments.

- To set a daily alarm, navigate to the alarm setting using the **SET** button.
- Adjust the alarm time using **UP/DOWN** and confirm with **SET**.
- Follow similar steps for the extra alarm.

4.5. Daylight Saving Time (DST)

The clock includes an option for Daylight Saving Time adjustment.

1. Navigate to the DST setting using the **SET** button.
2. Use **UP** or **DOWN** to turn DST **ON** or **OFF**.
3. Press **SET** to confirm.

5. FEATURES OVERVIEW



Image: Front view of the ALFAJR Azan Clock CS-13, showing its clear digital display with current time, date, and temperature. The control buttons are visible below the screen.

- **Clear LCD Display:** Features a bright LCD display with full screen illumination for visibility in the dark.
- **Global Prayer Times:** Supports over 100 major cities worldwide, with automatic Azan time

calculation using local Taqweem time. Adjustable for nearby cities.

- **Comprehensive Display:** Shows current time, date (Gregorian and Hijri calendar), Azan time, adjustable volume, Qibla direction, and temperature.
- **Power Options:** Operates with 2 AA batteries (included) or via Micro USB (adapter not included).
- **Compact Design:** Measures 12 by 9 by 6 centimeters, ideal for home or office use.

6. MAINTENANCE

- Clean the clock with a soft, dry cloth. Avoid abrasive cleaners or solvents.
- Do not expose the clock to extreme temperatures, direct sunlight, or high humidity.
- If using batteries, replace them when the display dims or functions become erratic. Remove batteries if the clock will not be used for an extended period.

7. TROUBLESHOOTING

Problem	Possible Cause	Solution
Clock not turning on / Display blank	Dead or incorrectly installed batteries; No power via Micro USB.	Check battery polarity, replace batteries, or connect Micro USB power source.
Incorrect Azan times	Incorrect city/country setting; Daylight Saving Time (DST) setting incorrect.	Verify city/country settings. Adjust individual prayer times if needed. Check DST setting.
Azan sound not playing	Azan sound turned off for specific prayer; Volume too low.	Ensure Azan sound is ON for the respective prayer. Increase volume using the volume control.
Display is dim or flickering	Low battery power.	Replace batteries or connect to a Micro USB power source.

8. SPECIFICATIONS

- **Brand:** ALFAJR
- **Model:** CS-13
- **Color:** Gray
- **Display Type:** Digital
- **Power Source:** Battery Powered (2 AA batteries required) or Micro USB
- **Product Dimensions:** 3.5"W x 5"H
- **Item Weight:** 8 ounces
- **Special Features:** Alarm, Temperature Display, Qibla Direction, Gregorian & Hijri Calendar
- **Material:** Plastic

9. WARRANTY AND SUPPORT

For warranty information and customer support, please refer to the documentation included with your purchase or contact the retailer. Keep your purchase receipt for any warranty claims.

