

Manuals+

[Q & A](#) | [Deep Search](#) | [Upload](#)

manuals.plus /

- › [NEDIS](#) /
- › [Nedis SmartLife Wireless Camera System SLNVR201CWT User Manual](#)

NEDIS SLNVR201CWT

Nedis SmartLife Wireless Camera System SLNVR201CWT User Manual

Model: SLNVR201CWT

INTRODUCTION

Thank you for choosing the Nedis SmartLife Wireless Camera System SLNVR201CWT. This system is designed to provide comprehensive home security with advanced features. This manual will guide you through the installation, operation, and maintenance of your new camera system, ensuring optimal performance and security.

The system includes a Network Video Recorder (NVR) and two Full HD (1080p) wireless cameras. Key features include motion and sound detection with adjustable sensitivity, instant smartphone notifications, a wide 180-degree viewing angle, night vision capabilities up to 5 meters, and two-way audio communication. Recordings are stored on a Micro SD card (not included) for convenient playback.



Image: The Nedis SmartLife Wireless Camera System, showing the central NVR unit and two wireless cameras.

SAFETY INFORMATION

- Read all instructions carefully before use.
- Keep this manual for future reference.
- Use only the power adapters supplied with the product. Using unauthorized power sources may damage the device and void the warranty.
- Do not expose the device to extreme temperatures, humidity, or direct sunlight.
- Ensure proper ventilation around the NVR unit to prevent overheating.
- Avoid placing the cameras in locations where they could be easily tampered with or damaged.
- This product is not a toy. Keep out of reach of children.
- For indoor and outdoor use. Ensure outdoor cameras are installed in a sheltered location to protect from direct heavy rain.

PACKAGE CONTENTS

Carefully unpack the box and ensure all items are present and in good condition. If any items are missing or damaged, please contact your retailer.

- 1 x Nedis SmartLife Wireless NVR Unit
- 2 x Nedis SmartLife Wireless Cameras
- 3 x Power Adapters (for NVR and cameras)
- 1 x USB Mouse
- Mounting Screws and Wall Plugs
- Drill Templates
- User Manual (this document)



Image: All components included in the Nedis SmartLife Wireless Camera System package.

SETUP

1. NVR Unit Connection

1. Place the NVR unit in a central location, ensuring good Wi-Fi signal strength for the cameras.
2. Connect the NVR to a power outlet using one of the provided power adapters.

3. Connect the USB mouse to the NVR's USB port.
4. If desired, connect the NVR to your router via an Ethernet cable for a stable network connection.



Image: Front view of the Nedis SmartLife NVR unit with indicator lights.

2. Camera Installation

1. Choose suitable locations for your cameras, considering the 180-degree viewing angle and night vision range (up to 5 meters).
2. Use the drill templates to mark the screw positions on the wall or ceiling.
3. Drill holes, insert wall plugs, and secure the camera mounts with screws.
4. Attach the cameras to their mounts and adjust the angle as needed.
5. Connect each camera to a power outlet using the remaining power adapters.



Image: Close-up of a Nedis SmartLife camera, highlighting the lens and sensor.

3. App Installation and Pairing

1. Download the 'Nedis SmartLife' app from your smartphone's app store (available for Android and iOS).
2. Register for a new account or log in if you already have one.
3. Follow the in-app instructions to add your NVR system. The app will guide you through the pairing process for the cameras.
4. Insert a Micro SD card (up to 128GB, not included) into the NVR for local storage of recordings.

OPERATING THE SYSTEM

Live View and Playback

- Open the Nedis SmartLife app on your smartphone.
- Select your camera system to view live feeds from all connected cameras.
- Use the app interface to switch between cameras, access recorded footage, and adjust settings.

- To view recorded footage, navigate to the playback section in the app and select the desired date and time.

Motion and Sound Detection

- The system is equipped with motion and sound detection. When triggered, it sends instant notifications to your smartphone.
- Adjust the sensitivity of both motion and sound detection within the Nedis SmartLife app settings for each camera to minimize false alarms.
- You can set specific detection zones for motion detection to focus on critical areas.

Two-Way Audio

- The cameras feature built-in microphones and speakers, enabling two-way communication.
- From the live view in the app, tap the microphone icon to speak through the camera's speaker. Tap again to end.
- This feature allows you to communicate with visitors or deter intruders remotely.

Night Vision

- The cameras automatically switch to night vision mode in low-light conditions.
- Night vision provides clear black-and-white video footage up to 5 meters, ensuring 24-hour surveillance.

MAINTENANCE

Cleaning

- Ensure the device is powered off and unplugged before cleaning.
- Use a soft, dry cloth to clean the NVR unit and camera bodies.
- For camera lenses, use a specialized lens cleaning cloth to avoid scratches.
- Do not use liquid or aerosol cleaners, as they may damage the components.

Firmware Updates

- Periodically check the Nedis SmartLife app for available firmware updates.
- Keeping your system's firmware up-to-date ensures optimal performance, security, and access to new features.
- Follow the in-app instructions carefully when performing updates.

Storage

- If storing the system for an extended period, ensure it is clean and dry.
- Store in a cool, dry place away from direct sunlight and extreme temperatures.

TROUBLESHOOTING

Problem	Possible Cause	Solution
No image/video from camera	Camera not powered on; Wi-Fi signal too weak; Camera not paired.	Check power connection; Move camera closer to NVR/router; Re-pair camera via app.

Problem	Possible Cause	Solution
No notifications received	Notifications disabled in app/phone settings; Detection sensitivity too low.	Enable notifications in Nedis SmartLife app and phone settings; Increase motion/sound sensitivity.
Poor night vision quality	Obstruction in front of camera; Camera too far from subject.	Clear any obstructions; Ensure subject is within 5-meter night vision range.
Two-way audio not working	Microphone/speaker permissions not granted; Volume too low.	Check app permissions for microphone; Adjust volume settings in app.
System offline in app	NVR not connected to internet; NVR powered off.	Check NVR's internet connection (Ethernet/Wi-Fi); Ensure NVR is powered on.

SPECIFICATIONS

Feature	Specification
Model Number	SLNVR201CWT
Brand	Nedis
Video Capture Resolution	1080p (Full HD)
Color	White
Number of Channels	4
Wireless Technology	Wi-Fi
Viewing Angle	180 degrees
Frame Rate	30 frames per second
Voltage	220 Volts
Wattage	48 Watts
Operating System Compatibility	Android, iOS
Batteries Included	No
Recommended Uses	Night Vision, Home Security
Special Features	High Definition, Motion Sensor, Two-Way Audio
Usage Environment	Indoor, Outdoor
Compatible Devices	Smartphone
Power Source	Corded Electric

Feature	Specification
Communication Protocol	Wi-Fi

WARRANTY AND SUPPORT

Nedis products are manufactured to high quality standards and are covered by a warranty period from the date of purchase. For detailed warranty terms and conditions, please refer to the warranty card included with your product or visit the official Nedis website.

For technical support, troubleshooting assistance, or to report any issues with your product, please contact Nedis customer service. Contact information can typically be found on the Nedis website or in your product packaging.

Please have your model number (SLNVR201CWT) and proof of purchase ready when contacting support.