

NVK B09WTZ8K24

NVK Dog Training Collar User Manual

Model: B09WTZ8K24

Brand: NVK

INTRODUCTION

Thank you for choosing the NVK Dog Training Collar. This single collar unit is designed to assist in effective and humane dog training through the use of beep, vibration, and static shock modes. It is waterproof and rechargeable, suitable for a wide range of dog sizes. Please read this manual thoroughly before use to ensure proper operation and the safety of your pet.

Note: This product package includes the single collar receiver unit only and does not come with a remote control. It is intended to be used as a replacement collar or an additional collar for an existing NVK training system with a compatible remote.

SAFETY INFORMATION

- **Not for Aggressive Dogs:** Do not use this product on aggressive dogs. If your dog is aggressive, please consult a professional dog trainer.
- **Skin Irritation:** Prolonged wear or improper fit can cause skin irritation. Inspect your dog's neck regularly for signs of redness or sores. If irritation occurs, discontinue use until the skin heals.
- **Collar Fit:** Ensure the collar is fitted snugly but not too tight. It should allow one finger to fit comfortably between the strap and your dog's neck.
- **Duration of Wear:** Do not leave the collar on your dog for more than 12 hours per day.
- **Children:** Keep out of reach of children.
- **Water Safety:** While the collar is waterproof, ensure the charging port is completely dry before charging to prevent damage.

PACKAGE CONTENTS

- 1 x NVK Dog Training Collar Receiver
- 4 x Replacement Silicone Caps (for contact points)

- (NVK charging cable not included, please use a compatible magnetic charging cable)

PRODUCT OVERVIEW



The NVK Dog Training Collar receiver unit.



Close-up of the contact points on the collar, with silicone caps shown for comfort and safety.

The NVK Dog Training Collar receiver features a compact design with integrated contact points for static correction, a speaker for beep tones, and an internal vibrator for vibration mode. It is attached to an adjustable nylon and PU collar strap.

- **Contact Points:** Deliver static correction. Comes with silicone caps for comfort.
- **Speaker:** Emits beep tones.
- **Indicator Light:** Shows power status and mode activation.
- **Magnetic Charging Port:** For recharging the collar.
- **Adjustable Strap:** Durable nylon and PU material, adjustable from 0 to 26 inches.

SETUP

1. Charging the Collar

Before first use, fully charge the collar receiver. The collar takes approximately 2 to 3 hours to fully charge and can last for about 15 days on a single charge.

1. Locate the magnetic charging port on the collar receiver.
2. Connect a compatible NVK magnetic charging cable (not included) to the port.
3. Plug the USB end of the cable into a USB power adapter (e.g., phone charger, computer USB port).
4. The indicator light will show charging status (e.g., red for charging, green for fully charged).



The collar features an IPX7 waterproof rating and a magnetic charging port for double waterproof protection.

2. Fitting the Collar

Proper fit is essential for the collar's effectiveness and your dog's comfort and safety. This collar is suitable for dogs weighing 10 to 110 lbs, with neck girths from 0 to 26 inches.

1. Place the collar on your dog's neck, ensuring the receiver unit is positioned centrally under the chin or on the side of the neck.
2. Adjust the strap so that the contact points are making direct contact with your dog's skin.
3. You should be able to fit one finger snugly between the collar strap and your dog's neck. A fit that is too loose will prevent consistent contact and effectiveness, while a fit that is too tight can cause discomfort or skin irritation.
4. If the strap is too long, you may trim it. If trimming, carefully singe the cut end with a lighter to prevent fraying.

Suitable for all sizes dogs from 10 to 110 lbs



10lbs 110lbs



0-26 inches adjustable Nylon and PU collar



If you have to cut some off, please singe the collar end with a lighter immediately to avoid fraying

Visual guide for fitting the collar, showing suitability for dogs from 10 to 110 lbs and adjustable strap length.

US Dog Training Collar Size Chart

Brand Size	Neck Girth (in)	Weight Capacity (lb)
One Size	0 - 26	10 - 110

OPERATING INSTRUCTIONS

This NVK Dog Training Collar receiver is designed to be controlled by a compatible NVK remote control (not included). The collar supports three training modes: Beep, Vibration, and Static Shock.

3 Training Modes

Select the proper training mode for your dog



Vibration Mode
(0-9) Level



Beep Mode



Static Mode
(00-99) Level
⚠ High level warning



Overview of the three training modes: Beep, Vibration, and Static Shock.

Pairing (if necessary)

If your collar is not responding to your NVK remote, it may need to be paired. Refer to your NVK remote control's manual for specific pairing instructions. Generally, this involves putting the collar into pairing mode (often by holding a button on the collar) and then activating pairing on the remote.

Training Modes

- **Beep Mode:** Emits an audible tone. This is often used as a warning or a positive reinforcement signal.
- **Vibration Mode:** Delivers a non-harmful vibration. This mode has 1-9 adjustable levels, allowing you to find the appropriate intensity for your dog.
- **Static Shock Mode:** Delivers a static correction. This mode has 0-99 adjustable levels. Start at the lowest level and gradually increase until your dog responds. Use this mode responsibly and only when necessary.

The specific buttons and procedures for activating these modes and adjusting levels will be on your NVK remote control.



The NVK training system, showing the collar and a compatible remote control (remote not included with this product).

TRAINING TIPS

Effective training requires consistency, patience, and positive reinforcement. The training collar is a tool to aid in communication, not a substitute for proper training methods.

- **Start with Beep/Vibration:** Always begin with the least intrusive modes (beep or low-level vibration) before resorting to static correction.
- **Timing is Key:** Deliver the correction immediately when your dog exhibits the unwanted behavior.
- **Consistency:** Use the collar consistently for specific behaviors you want to correct.
- **Positive Reinforcement:** Always reward desired behaviors with praise, treats, or toys.
- **Short Sessions:** Keep training sessions short and positive to maintain your dog's engagement.

Before



Barking



Biting



Chewing



Jumping



Digging

After



Sit



Stay



Come



Follow



Motion

Illustrates common unwanted behaviors (barking, biting, chewing) and desired trained behaviors (sit, stay, come).

MAINTENANCE

- **Cleaning:** Wipe the collar receiver and strap with a damp cloth. Do not use harsh chemicals.
- **Contact Points:** Regularly check the contact points for dirt or debris and clean them to ensure proper function.
- **Storage:** Store the collar in a cool, dry place when not in use.
- **Battery Life:** Recharge the collar when the battery indicator is low. The collar features a 7-hour auto-off protection to conserve battery.



The collar automatically turns off after 7 hours of inactivity to save battery.



The collar offers extended

battery life, reducing the need for frequent recharging.

TROUBLESHOOTING

Problem	Possible Cause	Solution
Collar not responding to remote.	Not paired; out of range; low battery on collar or remote.	Ensure collar is charged and powered on. Re-pair the collar with the remote (refer to remote manual). Move closer to the collar. Charge both devices.
No static correction.	Poor contact with skin; level too low; contact points dirty.	Adjust collar fit to ensure good contact. Increase static level on remote. Clean contact points. Ensure silicone caps are properly seated or removed if longer contact is needed for thick-coated dogs.
Collar not charging.	Charging cable not connected properly; faulty cable/adaptor; dirty charging port.	Ensure magnetic cable is securely attached. Try a different USB adaptor or port. Clean the magnetic charging port.
Skin irritation on dog's neck.	Collar too tight; worn for too long; contact points rubbing.	Loosen collar slightly. Do not leave collar on for more than 12 hours. Reposition collar periodically. Discontinue use until skin heals. Consult a vet if irritation persists.

SPECIFICATIONS

- **Brand:** NVK
- **Model:** B09WTZ8K24 (Single Collar Receiver)
- **Training Modes:** Beep, Vibration (1-9 levels), Static Shock (0-99 levels)
- **Waterproof Rating:** IPX7
- **Battery Life:** Up to 15 days (receiver)
- **Charging Time:** 2-3 hours
- **Collar Material:** Nylon, Polyurethane, Silicone
- **Adjustable Collar Length:** 0-26 inches
- **Suitable Dog Weight:** 10-110 lbs
- **Item Weight:** 4.2 ounces
- **Product Dimensions (Receiver):** Approximately 15.75 x 0.79 x 0.04 inches (collar strap length included)

WARRANTY AND SUPPORT

NVK strives to provide high-quality products. While specific warranty details are not provided in this manual, please retain your proof of purchase. For any product inquiries, technical support, or warranty claims, please contact NVK customer service through the retailer where you purchased the product or visit the official NVK brand store online.

You can visit the NVK Store for more information: [NVK Official Store](#)

© 2025 NVK. All rights reserved.
Manual Version: 1.0