

BESFUR 920-m

BESFUR Metal Storage Cabinet Model 920-m Instruction Manual

Model: 920-m | Brand: BESFUR

1. INTRODUCTION

Thank you for choosing the BESFUR Metal Storage Cabinet Model 920-m. This manual provides detailed instructions for the safe assembly, operation, and maintenance of your new storage cabinet. Please read this manual thoroughly before beginning assembly and retain it for future reference.

This versatile cabinet is designed for various environments including home offices, garages, utility rooms, and basements, offering secure and organized storage solutions.

2. IMPORTANT SAFETY INFORMATION

- Always follow the assembly instructions carefully to avoid injury.
- Do not overload the shelves. Each shelf can hold up to 180 pounds.
- Keep the cabinet away from heat sources and do not use it for flammable materials.
- Always keep the cabinet locked when not in use to prevent unauthorized access, especially if storing hazardous materials or valuable items.
- Ensure the cabinet is placed on a level surface to prevent tipping. Consider anchoring the cabinet to a wall for added stability, especially in households with children or pets.
- Wear appropriate safety gear, such as gloves, during assembly to prevent cuts or pinches.

3. PACKAGE CONTENTS

Before beginning assembly, please verify that all parts listed below are present and undamaged. If any parts are missing or damaged, please contact customer support.



Figure 1: BESFUR Metal Storage Cabinet (assembled view)

The package typically includes:

- Left Side Panel (A)
- Right Side Panel (B)
- Left Back Panel (C)
- Right Back Panel (D)
- Top Panel (E)
- Bottom Panel (H)
- Hanging Panels (F) - 2 pieces
- Shelves (G) - 3 pieces
- Upper Frame (I)
- Lower Frame (J)
- Left Door (K)
- Right Door (L)
- Door Hanging Panel (M)
- Hanging Rod (N)
- Heel Post (R)
- Heel Post Gasket (Q)
- Anti-Friction Mat (S)

- Lock Cover (V)
- Self-tapping Screws (O)
- Lock (R) with Lock Rod (P)
- Wall Anchoring Kit (Screws, Washers, Dowels) (U)



Figure 2: Cabinet Dimensions

4. ASSEMBLY INSTRUCTIONS

Follow these steps carefully for proper assembly. An electric screwdriver is recommended for efficiency.

4.1. Step-by-Step Assembly Video

Your browser does not support the video tag.

Video 1: Detailed assembly guide for the BESFUR Metal Storage Cabinet.

Your browser does not support the video tag.

Video 2: Alternative assembly guide for the BESFUR Steel Storage Cabinet.

4.2. Written Assembly Steps

1. **Prepare Panels:** Identify the left side panel (A), right side panel (B), left back panel (C), and right back panel (D). Note the "Up" and "Down" markings on the panels.
2. **Assemble Back and Side Panels:** Connect the left side panel (A) with the left back panel (C) using self-tapping screws (O). Repeat for the right side panel (B) and right back panel (D) using self-tapping screws (O).
3. **Install Frames:** Install the upper frame (I) and lower frame (J) to the top and bottom edges of the assembled side and back panels. Secure with self-tapping screws (O).
4. **Attach Top and Bottom Panels:** Install the top panel (E) and bottom panel (H) to the corresponding frames, securing them with self-tapping screws (O).
5. **Install Hanging Panels:** Fit the half of self-tapping screws (O) into the back panels, not fully tightened. Install the lower hanging panel (F) first, then the upper hanging panel (F). Fix the panels by fully tightening the self-tapping screws (O).
6. **Insert Shelf Clasps and Shelves:** Put the shelf clasps (P) onto the holes of the back and side panels at your desired height. Then, place the 3 shelves (G) onto the shelf clasps (P).
7. **Install Doors:** Install the heel post (R) and heel post gasket (Q) onto the bottom of the cabinet. Then, install the left door (K) and right door (L) by aligning the hinges with the cabinet frame and securing them.
8. **Attach Door Accessories:** Install the door hanging panel (M), hanging rod (N), anti-friction mat (S), and lock cover (V) to the inside of the doors as shown in the diagram.
9. **Install Locks:** Install the lock (R) with the lock rod (P) on the right door (K).
10. **Wall Anchoring (Optional but Recommended):** For enhanced stability, fix the cabinet onto the wall by installing the provided screws, washers, and dowels (U) through the designated holes at the top rear of the cabinet.

5. PRODUCT FEATURES

- **Locking Mechanism:** The cabinet is equipped with a high-quality lock and comes with two keys, ensuring the security of your documents and personal belongings.
- **Adjustable Shelves:** Two shelves are adjustable, allowing you to customize storage space according to your needs. Each shelf supports up to 180 pounds.
- **Sturdy Construction:** Made from heavy-gauge cold-rolled steel plates, providing durability and stability. The powder-coated finish offers a smooth, easy-to-clean surface.
- **Magnetic Door Stoppers:** Shock pads and magnets on the doors keep them securely closed and reduce noise.
- **Versatile Use:** Suitable for various settings including garages, offices, utility rooms, pantries, basements, schools, and workshops.

• FEATURES •



Figure 3: Key Features of the Cabinet

Your browser does not support the video tag.

Video 3: Overview of the BESFUR Locking Storage Cabinet, showcasing its features and functionality.

6. OPERATING INSTRUCTIONS

6.1. Locking and Unlocking

Insert one of the provided keys into the lock on the right door. Turn the key clockwise to lock the cabinet and counter-clockwise to unlock it. Ensure both doors are fully closed before locking. The magnetic stoppers will help keep the doors shut even when unlocked.

6.2. Adjusting Shelves

To adjust a shelf, first remove all items from the shelf. Carefully lift the shelf to disengage it from the shelf clasps. Reposition the shelf clasps into the desired holes on the side and back panels, ensuring they are level. Then, place the shelf back onto the clasps, making sure it is securely seated.

7. MAINTENANCE

- **Cleaning:** Wipe the cabinet surfaces with a soft, damp cloth. Avoid abrasive cleaners or harsh chemicals that could damage the powder-coated finish.

- **Inspection:** Periodically check all screws and connections to ensure they remain tight. Tighten any loose fasteners as needed.
- **Lubrication:** If the door hinges or lock mechanism become stiff, apply a small amount of silicone-based lubricant.
- **Load Management:** Do not exceed the maximum weight capacity of 180 pounds per shelf to prevent damage or injury. Distribute weight evenly.

8. TROUBLESHOOTING

- **Doors not closing properly:** Check if the cabinet is on a level surface. Ensure hinges are properly aligned and screws are tightened. Verify that nothing is obstructing the doors from closing fully.
- **Shelves are wobbly:** Ensure shelf clasps are fully inserted into the holes and the shelf is seated correctly on all four clasps. Check that the cabinet itself is stable and all assembly screws are tight.
- **Lock mechanism is stiff:** Apply a small amount of graphite powder or silicone spray lubricant to the keyhole and the locking mechanism.

9. SPECIFICATIONS

Attribute	Detail
Brand	BESFUR
Model Name	M STORAGE CABINET (Model 920-m)
Color	Black
Product Dimensions	15.75"D x 31.5"W x 36"H
Material	Metal (Heavy-gauge cold-rolled steel)
Finish Type	Powder Coated
Special Features	Adjustable Shelf, Lockable
Number of Shelves	2 (Adjustable)
Weight Limit (per shelf)	180 Pounds
Item Weight	49 Pounds
Mounting Type	Floor Mount (Freestanding, Wall Anchorable)
Recommended Uses	Files & Folders, Tools, Household Items, Office Supplies, Books, Food

10. WARRANTY AND SUPPORT

For warranty information or technical support, please contact BESFUR customer service. Details can typically be found on the product packaging or the retailer's website where the product was purchased. Please have your model number (920-m) and purchase date available when contacting support.

